



Sanyo SCP-7400 | User's Guide



www.qwestwireless.com

SANYO

Table of Contents

Welcome to Qwest®	i
Introduction	ii
Section 1: Getting Started	1
1A. Setting Up Service	2
Getting Started	3
Setting Up Your Voicemail	4
Account Passwords	5
Getting Help	6
Section 2: Your Phone	7
2A. Your Phone: The Basics	8
Front View of Your Phone	9
Key Features	10
Viewing the Display Screen	12
Features of Your Wireless Phone	14
Changing the Faceplate	15
Turning Your Phone On and Off	16
Using Your Phone's Battery and Charger	17
Displaying Your Phone Number	19
Making and Answering Calls	20
Making Calls	20
Dialing Options	21
Answering Calls	22
Using the Speakerphone	24
Changing the Ringer Volume	25
Adjusting Volume During a Conversation	25
Muting a Call	25
Missed Call Notification	26
Calling Emergency Numbers	26
In-Call Options	27
End-of-Call Options	28
Saving a Phone Number	28
Finding a Phone Number	29
Dialing and Saving Phone Numbers With Pauses	29

Making International Calls With Plus Code Dialing	30
Dialing From the Contacts Directory	30
Using Speed Dialing	31
Using Abbreviated Dialing	31
Entering Text	32
Selecting a Character Input Mode	32
Entering Characters Using T9 Text Input	33
Entering Characters by Tapping the Keypad	34
Entering Symbols, Numbers, Preset Suffixes, Smileys, and Emoticons	35
2B. Controlling Your Phone's Settings	37
Sound Settings	38
Ringer Types	38
Selecting a Tone Length	40
Setting a Start-up/Power-off Tone	40
Using Voice Prompt	40
Setting Up Key Press Echo	41
Adjusting the Phone's Volume Settings	41
Alert Notification	43
Silence All	44
Display Settings	45
Changing the Text Greeting	45
Changing the Backlight Time Length	46
Changing the Display Screen Animation	47
Changing the Display for Incoming Calls	47
Changing the Display for Area Name	48
Changing the Display for Standby Mode	49
Changing the Screen Saver	50
Changing the Phone's Menu Style	50
Changing the Display for My Buddy	51
Changing the Background	51
Changing the Font Size	52
Location Settings	53
Airplane Mode	54
TTY Use	55
Phone Setup Options	56

Shortcut	56
Auto Answer Mode	57
Setting the Open/Close Flip Option	58
Setting Any Key Answer	59
Setting the Side Key Guard	59
Setting Abbreviated Dialing	60
Setting the Meeting Mode	61
Headset Mode	62
Setting Return to Standby Mode	63
Sleep Mode	63
Setting Message Notification	64
Editing Preset Messages	64
Setting a Callback Number	65
Setting Your Signature	65
Display Language	66
Using the Mini-Flashlight	66
2C. Setting Your Phone's Security	67
Accessing the Security Menu	68
Using Your Phone's Lock Features	68
Locking Your Phone	68
Unlocking Your Phone	69
Locking the Picture and Video Menu	69
Locking Voice Calls	69
Locking Ready Link Calls	70
Changing the Lock Code	70
Calling in Lock Mode	70
Restricting Calls	71
Using Special Numbers	72
Erasing the Contacts Directory	73
Erasing All Voice Tags	73
Erasing All Downloads	73
Resetting Your Pictures Account	74
Resetting Your Phone	74
Security Features for Sprint PCS Vision™	75
Enabling and Disabling Sprint PCS Vision Services	75

2D. Controlling Your Roaming Experience	76
Understanding Roaming	77
Setting Your Phone's Roam Mode	79
Using Call Guard	80
2E. Navigating Through Menus	81
Menu Navigation	82
Menu Structure	82
Viewing the Menus	83
2F. Managing Call History	86
Viewing History	87
Call History Options	88
Making a Call From Call History	88
Saving a Phone Number From Call History	89
Prepending a Phone Number From Call History	90
Erasing Call History	90
2G. Using the Contacts Directory	91
Displaying the Contacts List	92
Adding a New Contacts Entry	92
Finding Contacts List Entries	93
Contacts List Entry Options	94
Adding a Phone Number to a Contacts Entry	95
Editing a Contacts Entry's Phone Number	95
Erasing a Contacts Entry From the List	95
Assigning Speed Dial Numbers	96
Editing a Contacts Entry	97
Selecting a Ringer and Image Type for an Entry	98
Secret Contacts Entries	99
2H. Personal Organizer	100
Managing the Scheduler	101
Displaying Your Calendar	101
Setting Holidays	101
Using Your Phone's Scheduler	102
Adding an Event to the Scheduler	102
Event Alerts	103
Event Alert Menu	103

Using the Call Alarm Feature	104
Adding a Call Alarm to the Scheduler	104
Call Alarm Alerts	105
Call Alarm Menu	105
Editing an Event or Call Alarm	106
Viewing a Future or Past Day's Scheduled Events	106
Erasing a Day's Events or Call Alarms	106
Using the To Do List	107
Adding To Do List Items	107
Viewing the To Do List	107
Editing To Do List Items	107
Adding a To Do List Item to the Scheduler	108
Deleting Items From the To Do List	108
Viewing Memory in Your Scheduler	109
Purging All Events, Call Alarms, or To Do List Items	109
Personal Information Management	110
Displaying Your User Address	110
Finding Icon Definitions	110
Displaying the Version Information	110
Displaying Advanced Information	111
Using Your Phone's Tools	111
Using the Alarm Clock	111
Using the Calculator	113
Using the World Clock	113
Downloading Files	114
Confirming the Downloaded Data	117
Downloaded Data Options	118
Erasing the Downloaded Data	121

21. Using Your Phone's Voice Services122

Using Automatic Speech Recognition	123
Activating Automatic Speech Recognition	123
Making a Voice Call by Using ASR	124
Finding Contacts List Entries	125
Making a Call Using a Voice Tag	126
Programming a Voice Tag	126

Reviewing Voice Tags	127
Erasing a Voice Tag	127
Making a Ready Link Call by Using ASR	128
Using Digit Training	129
Phone Status Command	130
ASR Help Command	130
Managing Voice Memos	131
Recording Voice Memos	131
Reviewing Voice Memos	132
Erasing Voice Memos	133
Setting Up Screen Call	134
Activating Screen Call	134
Selecting an Announcement for Screen Call	135
Recording Your Name for a Pre-Recorded Announcement	135
Recording a Customized Announcement	136
Reviewing an Announcement	136
Erasing an Announcement	136
2J. Using Ready Link	137
Getting Started With Ready Link	138
Setting Ready Link Mode	138
Preparing Your Phone for Ready Link Service	138
Ready Link Call Alerts	139
Making and Receiving a Ready Link Call	140
Displaying the Ready Link List	140
Selecting a Contacts List	140
Making a Ready Link Call (1-to-1 Call)	141
Making a Ready Link Call (Group Call)	142
Making a Ready Link Call by Entering a Number	143
Missed Call Notification for Ready Link Calls	144
Receiving a Ready Link Call	145
Ready Link Options	146
Adding and Editing Ready Link Contacts	146
Copying an Entry to Personal List or Personal Group List	146
Saving a Ready Link Number	147
Finding an Entry in the Ready Link List	147

Adding a New Contact to Your Personal List	148
Adding a New Group to Your Personal Group List	149
Editing a Contact in Your Personal List	150
Editing a Group in Your Personal Group List	151
Erasing Ready Link List Entries	152
Erasing an Entry in Your Personal List or Personal Group List	152
Erasing a Ready Link List	153
Updating Your Ready Link Lists	153
Updating the Personal Lists	153
Managing Ready Link Settings	154
Assigning Speed Dialing for Ready Link Entries	154
Restarting the Ready Link Service	154
Setting Ready Link Guard	155
Setting Ringer Types for Ready Link Calls	155
Setting an Alert Notification for Ready Link Calls	156
Setting the Speakerphone for Ready Link Calls	156
Setting the Default View of the Ready Link List	157
Setting the Floor Display of the Ready Link Calls	157
2K. Using Your Phone's Built-in Camera	158
Taking Pictures	159
Creating Your Sprint PCS Picture Mail™ Password	160
Camera Mode Options	161
Selecting Camera Settings	165
Viewing Your Camera's Status Area Display	166
Storing Pictures in My Pictures	168
In Camera Folder	168
In Camera Folder Options	168
Saved to Phone Folder	171
Saved to Phone Folder Options	172
Taking Videos	173
Video Mode Options	174
Selecting Camcorder Settings	176
Viewing Your Video's Status Area Display	177
Storing Videos in My Videos	178
In Camcorder Folder	178

In Camcorder Folder Options	179
Saved to Phone Folder (Video)	181
Saved to Phone Folder Options (Video)	182
Sending Sprint PCS Picture Mail and Sprint PCS Video Mail	183
Sending Pictures From the In Camera Folder	183
Sending Videos From the In Camcorder Folder	185
Sending Sprint PCS Picture Mail From Messaging	185
Sending to Various Destinations	187
Managing Sprint PCS Picture Mail	188
Using the Sprint PCS Picture Mail Website	188
Managing Online Pictures From Your Phone	189
Uploading Your Pictures and Videos	190
Downloading Your Online Pictures	191
Sending Online Sprint PCS Picture Mail	192
Accessing Online Picture Options From Your Phone	193

2L. Using Your Phone's Built-in Media Player196

Your Multimedia Channel Options	197
Accessing Your Media Player's Channel Listings	198
Playing a Video or Audio Clip	199
Multimedia Options	201
Multimedia FAQs	202

Section 3: Qwest® Service Features205

3A. Qwest® Service Features: The Basics206

Using Voicemail	207
Setting Up Your Voicemail	207
Voicemail Notification	207
New Voicemail Message Alerts	208
Retrieving Your Voicemail Messages	208
Voicemail Options	210
Clearing the Message Icon	212
Displaying Your Voicemail Details	212
Voicemail Menu Key	213
Using Caller ID	214
Responding to Call Waiting	214

Making a Three-Way Call	215
Using Call Forwarding	216
3B. Sprint PCS VisionSM	217
Getting Started With Sprint PCS Vision	218
Your User Name	218
Launching a Sprint PCS Vision Connection	219
Net Guard	220
Sprint PCS Vision Connection Status and Indicators	220
Navigating the Web	221
Using the Sprint PCS Vision Multimedia Service	223
Purchasing Multimedia Channels	223
Playing an Audio or Video Clip	224
Understanding Messaging	225
Message Types	225
New Messages	225
Message Storage	226
Displaying Messages	226
Sending a Text Message	227
Sending a Message in the Drafts Folder	228
Sending a Message in the Outbox Folder	229
Message Options	229
Changing the Display Font Size of a Message	232
Prepending a Phone Number From a Message	232
Message Folders	233
Moving a Message Into Another Folder	234
Erasing Messages	234
Erasing a Folder	235
Accessing Email Providers	235
Using Email Providers	235
Using Instant Messaging	236
Accessing Instant Messaging	236
Experiencing Wireless Online Chat	237
Downloading Premium Services Content	238
Accessing Games	240
Accessing Ringers	242

Accessing Screen Savers244

Exploring the Web246

 Using the Browser Menu247

Sprint PCS Vision FAQs251

Section 4: Safety Guidelines252

4A. Safety253

 Getting the Most Out of Your Reception254

 Maintaining Safe Use of and Access to Your Phone255

 Caring for the Battery257

 Acknowledging Special Precautions and the FCC Notice258

 Consumer Information on Wireless Phones260

 Owner’s Record275

 User’s Guide Proprietary Notice275

Index276



Welcome to Qwest®

This guide will familiarize you with our technology and your new wireless phone through simple, easy-to-follow instructions. If you have already reviewed the **Start Here to Activate** guide that was packaged with your new phone, then you're ready to explore the advanced features outlined in this guide.

If you have not read your **Start Here to Activate** guide, go to Section One – Getting Started. This section provides all the information you need to unlock your phone, set up your voicemail, and use services such as directory assistance and operator services.

Welcome and thank you for choosing Qwest®.

Introduction

This **User's Guide** introduces you to wireless service and all the features of your new phone. It's divided into four sections:

- ◆ **Section 1:** Getting Started
- ◆ **Section 2:** Your Phone
- ◆ **Section 3:** Qwest Service Features
- ◆ **Section 4:** Safety Guidelines

Throughout this guide, you'll find tips that highlight special shortcuts and timely reminders to help you make the most of your new phone and service. The Table of Contents and Index will also help you quickly locate specific information.

You'll get the most out of your phone if you read each section. However, if you'd like to get right to a specific feature, simply locate that section in the Table of Contents and click on the page number to go directly to that page. Follow the instructions in that section, and you'll be ready to use your phone in no time.

Note: You can view this guide online or print it to keep it on hand. If you're viewing it online, simply click on a topic in the Table of Contents or Index or on any page reference. The PDF will automatically display the appropriate page.

Getting Started

Setting Up Service

In This Section

- ◆ **Getting Started**
 - ◆ **Setting Up Your Voicemail**
 - ◆ **Account Passwords**
 - ◆ **Getting Help**
-

Setting up service on your Sanyo SCP-7400 is quick and easy.

This section walks you through the necessary steps to unlock your phone, set up your voicemail, and contact Qwest for assistance with your service.

Getting Started

Unlocking Your Phone

To unlock your phone, follow these easy steps:

1. Press **END/⓪** to turn the phone on.
2. Press **Unlock** (left softkey).

Note: To select a softkey, press the softkey button directly below the softkey text that appears at the bottom left and bottom right of your phone's display screen. Softkey actions change according to the screen you're viewing and will not appear if there is no corresponding action available.



3. Enter your four-digit lock code. (For security purposes, the code is not visible as you type.)

Tip: If you can't recall your lock code, try using the last four digits of either your Social Security number or phone number or try 0000. If none of these work, call Qwest Wireless™ Repair at 1-877-879-0611.

Setting Up Your Voicemail

All unanswered calls to your wireless phone are automatically transferred to your voicemail, even if your phone is in use or turned off. Therefore, you will want to set up your voicemail and personal greeting as soon as your phone is activated.

To set up your voicemail:

1. Press and hold .
2. Follow the system prompts to:
 - Create your passcode
 - Record your greeting
 - Record your name announcement
 - Choose whether or not to activate One-Touch Message Access (a feature that lets you access messages simply by pressing and holding , bypassing the need for you to enter your passcode)

Note: The voicemail setup process may vary in certain Affiliate areas.

For more information about using your voicemail, see “Using Voicemail” on page 207.

Account Passwords

As a Qwest customer, you enjoy unlimited access to your personal account information, your voicemail account, and your Sprint PCS Vision account. To ensure that no one else has access to your information, you will need to create passwords to protect your privacy.

Account Password

If you are the account owner, you'll have an account password to sign on to www.qwestwireless.com and to use when calling Qwest Wireless Customer Service. Your default account password is the last four digits of your Social Security number.

Voicemail Password

You'll create your voicemail password (or passcode) when you set up your voicemail. See "Setting Up Your Voicemail" on page 4 for more information on your voicemail password.

Sprint PCS Vision Password

If your service plan includes Sprint PCS VisionSM, you can set up a Sprint PCS Vision Password. This optional password may be used to authorize purchase of Premium Services content and to protect personal information on multi-phone accounts.

For more information or to change your passwords, sign on to www.qwestwireless.com or call Qwest WirelessTM Repair at 1-877-879-0611.

Getting Help

Visit Our Website

You can get up-to-date information on your wireless service and options by signing onto our Website at www.qwestwireless.com.

When you visit us online, you can

- Review coverage maps
- Learn how to use voicemail
- Access your account information
- Check out frequently asked questions
- And more

Reaching Qwest Wireless Customer Service

You can reach Qwest online or by phone:

- Sign on to your account at www.qwestwireless.com
- Call us toll-free at 1-877-879-0611

Directory Assistance

You have access to a variety of services and information through Directory Assistance, including residential, business, and government listings. There is a per-call charge and you will be billed for airtime.

To call Directory Assistance:

▶ Press **4 1 1 TALK**.

Operator Services

Operator Services provides assistance when placing collect calls or when placing calls billed to a local telephone calling card or third party.

To access Operator Services:

▶ Press **0 TALK**.

For more information or to see the latest in products and services, visit us online at www.qwestwireless.com.

Note: Operator Services may not be available in all Affiliate areas.

Your Phone

Your Phone: The Basics

In This Section

- ◆ **Front View of Your Phone**
 - ◆ **Viewing the Display Screen**
 - ◆ **Features of Your Wireless Phone**
 - ◆ **Turning Your Phone On and Off**
 - ◆ **Using Your Phone's Battery and Charger**
 - ◆ **Displaying Your Phone Number**
 - ◆ **Making and Answering Calls**
 - ◆ **Entering Text**
-






Your Sanyo SCP-7400 Phone is packed with features that simplify your life and expand your ability to stay connected to the people and information that are important to you. This section will guide you through the basic functions and calling features of your new phone.

Front View of Your Phone
























Key Features

















1. **Earpiece:** Lets you hear the caller's voice.
2. **Main LCD (display):** Displays the phone's main menu, features, modes, etc.
3. **Softkey (left):** Lets you select the menu corresponding to the bottom left line on the Main LCD.
4. **Navigation Key:** Lets you navigate quickly and easily through the menu options. You can access the menu shortcuts by pressing **Right:** Contacts, **Left:** Shortcut, **Up:** Messaging, and **Down:** Downloads.
5. **MENU/OK:** Lets you access the phone's menus and select menu options.
6. **Camera Key:** Lets you access the Picture & Video menu and take pictures and videos.
7. **TALK:** Lets you place or receive calls, answer Call Waiting, or use Three-Way Calling and Automatic Speech Recognition.
8. **Microphone:** Allows the other caller to hear you when you speak to them and allows you to record voice memos.
9. **Accessories Connector:** Connects optional accessories, such as a USB cable.
10. **Charger Jack:** Connects the travel charger (included).
11. **Keypad:** Lets you enter numbers, letters, and characters, and navigate within menus. Press and hold keys 2-9 for speed dialing.
12. **SPEAKER Key:** Lets you place or receive calls in speakerphone mode. You can also use it to activate Automatic Speech Recognition.
13. **END/POWER:** Lets you turn the phone on and off, end a call, or return to standby mode.
14. **Side Camera Key:** Lets you access the Picture & Video menu and take pictures and videos.
15. **BACK:** Lets you display the previous page or clear characters from the screen.

16. **Side Voice/Call Key:** Lets you place calls by using Automatic Speech Recognition.
17. **Softkey (right):** Lets you select the menu corresponding to the bottom right line on the Main LCD.
18. **Faceplate Release Latch:** Lets you remove the faceplate.
19. **Camera Lens:** The built-in camera lens lets you take pictures and videos.
20. **Flash:** The built-in flash lets you take pictures and videos in low light. You can also use it as a mini-flashlight.
21. **LED Indicator:** Shows your connection status at a glance.
22. **Speaker:** Lets you hear the different ringers and sounds. You can mute the ringer when receiving incoming calls by pressing , , , , , or the Side Camera key.
23. **Sub LCD:** Lets you monitor the phone's status and see who's calling without opening the phone.
24. **Antenna:** Fully extend the antenna for the best reception.
25. **Headset Jack:** Lets you insert the plug of a headset (sold separately) for hands-free phone use.
26. **Ready Link/Memo Button:** Allows you to access the Ready Link List or Voice Memo menu. (See "Using Ready Link" on page 137 or "Managing Voice Memos" on page 131.)
27. **Side Volume Key:** Lets you adjust the receiver volume during a call or ringer volume in standby mode.



Viewing the Display Screen

Your phone's display screen provides a wealth of information about your phone's status and options. This list identifies the symbols you'll see on your phone's display screen:

-  shows your current signal strength. The more lines you have, the stronger your signal.
-  means your phone cannot find a signal.
-  tells you a call is in progress.
-  indicates the Ready Link service is enabled.
-  indicates the Ready Link service is enabled and the speakerphone mode is set to on.
-  indicates the Ready Link service is disabled.
-  indicates Sprint PCS Vision/Ready Link access is dormant.
-  indicates Sprint PCS Vision/Ready Link access is active.
-  indicates Sprint PCS Vision/Ready Link access is disabled.
-  indicates you are "roaming" off the network provided to you.
-  indicates you have new picture messages waiting.
-  indicates you have new voicemail messages waiting. Press and hold  to call your voicemail box.
-  indicates you have new text messages waiting.
-  indicates you have picture messages, voicemail messages, and text messages waiting.
-  indicates you have urgent messages waiting.
-  indicates you have alarm clock notifications waiting.
-  indicates you have schedule events or call alarms waiting.
-  indicates you have missed voice calls.
-  indicates you have missed Ready Link calls.
-  indicates you have two or more types of notifications. However, message icons will appear if there are message notifications, since message notifications have priority.

-  shows the level of your battery charge. The more black you see, the more power you have left.
-  shows your battery is charging.
-  indicates you have menus to scroll (in four directions).
-  indicates volume level 4 or 1 and vibrate feature are set.
-  indicates a beep sound is set at level 1.
-  indicates the vibrate feature is set.
-  indicates the voice call ringer setting is off.
-  indicates all the sound settings are off.
-  indicates the Location Service of your phone is enabled.
-  indicates the Location Service of your phone is disabled.
-  indicates you have a new caller's message waiting.
-  indicates the Screen Call Auto setting is on.
-  indicates your phone is in TTY mode.
-  indicates Headset mode is set to Ready Link and a headset is connected.
-  indicates the Alarm Clock setting is on.
-  indicates the speakerphone mode is set to on.

Note: Display indicators help you manage your roaming charges by letting you know when you're off the network provided to you and whether you're operating in digital or analog mode. (For more information, see Section 2D: Controlling Your Roaming Experience on page 76.)

Tip: You can access display screen icon descriptions in your phone's menu. Press , select **Settings**, select **Phone Info**, and select **Help**. To display an icon's description, highlight it and press .

Features of Your Wireless Phone


Congratulations on the purchase of your Sanyo SCP-7400 Phone. This phone is lightweight, easy-to-use and reliable, and it also offers many significant features and service options. The following list previews some of those features and options and provides page numbers where you can find out more:

- Dual-band/tri-mode capability allows you to make and receive calls while on the network provided to you and to roam on other analog and 800 and 1900 MHz digital networks where roaming agreements have been implemented (page 76).
- Sprint PCS Vision provides access to the wireless Internet in digital mode (page 217).
- Email provides quick and convenient text messaging capabilities (page 235).
- Games, ringtones, screen savers, and other applications can be downloaded to your phone to make your wireless phone as unique as you are (page 238).
- The built-in organizer lets you schedule alerts to remind you of important events (page 101).
- The Contacts directory (page 91) can store up to 500 numbers and 300 email and Web addresses in 300 entries (entries can store up to seven numbers each). A separate Ready Link Contacts List (page 140) provides easy access to up to 200 personal contacts.
- The built-in camera allows you to take full-color digital pictures and videos, view your pictures and videos using the phone's display, and instantly send them to a family and friends using Sprint PCS Picture Mail™ service (page 158).
- Ready Link allows you to enjoy quick, two-way, “walkie-talkie-style” communication with one or several Ready Link users (page 137).
- The changeable faceplate makes you enjoy various appearance of your phone (page 15).
- The Automatic Speech Recognition (ASR) lets you place and receive calls by speaking to your phone (page 123).
- The Media Player allows you to enjoy the streaming video and audio with your phone (page 196).

Changing the Faceplate

Removing and Installing the Faceplate

- ▶ To remove, press the faceplate release latch up and remove the faceplate from the phone at a 45-degree angle.



Note: Be careful not to damage your fingernail when you remove the faceplate.

- ▶ To install, insert the faceplate into the opening on the front of the phone and press down firmly until the latch snaps into place.



Turning Your Phone On and Off

Turning Your Phone On

To turn your phone on:

- ▶ Press **END/⓪**.

Once your phone is on, it displays “Looking for service...” which indicates that your phone is searching for a signal. When your phone finds a signal, it automatically enters standby mode – the phone’s idle state. At this point, you are ready to begin making and receiving calls.

If your phone is unable to find a signal after 15 minutes of searching, a Power Save feature is automatically activated. When a signal is found, your phone automatically returns to standby mode.

In Power Save mode, your phone searches for a signal periodically without your intervention. You can also initiate a search for service by pressing any key (when your phone is turned on).

Tip: The Power Save feature helps to conserve your battery power when you are in an area where there is no signal.

Turning Your Phone Off

To turn your phone off:

- ▶ Press and hold **END/⓪** until you see the powering down animation on the display screen.

Your screen remains blank while your phone is off (unless the battery is charging).

Using Your Phone's Battery and Charger

Battery Capacity

Your wireless phone is equipped with a Lithium Ion (LiIon) battery. It allows you to recharge your battery before it is fully drained. The battery provides up to 3.5 hours of continuous digital talk time (1.7 hours in analog) or up to 288 hours of continuous digital standby time (22 hours in analog).

When the battery reaches 5% of its capacity, the low battery icon appears. When there are approximately two minutes of talk time left, the phone sounds an audible alert and then powers down.


Note: Long backlight settings, searching for service, vibrate mode, Ready Link mode, and browser use affect the battery's talk and standby times.

Tip: Be sure to watch your phone's battery level indicator and charge the battery before it runs out of power.

Installing the Battery

To install the LiIon battery:


1. Place the battery into the space beneath the antenna with the metal contacts at the bottom, facing downward.
2. Gently press down until it's in place and the battery release latch snaps.



Removing the Battery


To remove your battery:

1. Make sure the power is off so that you don't lose any stored numbers or messages.
2. Push the battery release latch up and hold the battery.
3. Pull the battery up and out at a 45-degree angle.



Charging the Battery

Your phone's LiIon battery is rechargeable and should be charged as soon as possible so you can begin using your phone.





Keeping track of your battery's charge is important. If your battery level becomes too low, your phone automatically turns off and you will lose all the information you were just working on. For a quick check of your phone's battery level, glance at the battery charge indicator located in the upper-right corner of your phone's display screen. If the battery charge is getting too low, the low battery icon () appears and the phone sounds a warning tone.

Always use a Qwest-approved travel charger or vehicle power adapter to charge your battery.

Warning! Using the wrong battery charger could cause damage to your phone and void the warranty.

Using the Travel Charger

To use the travel charger provided with your phone:




1. Plug the travel charger into a wall outlet.
2. Plug the other end of the travel charger into the bottom of your phone (with the battery installed).
 - **Charging when your phone is turned on:**
The battery icon  appears on the display while charging. The battery icon turns to  when charging is completed.
 - **Charging when your phone is turned off:**
The battery icon  appears, and the message "BATTERY CHARGING-Power Off-" is shown on the display while charging. When the battery is completely discharged, it may take several minutes until the message is shown on the display. The battery icon turns to , and the message changes to "CHARGING COMPLETE-Power Off-" when charging is completed.



It takes approximately 4 hours to fully recharge a completely rundown battery. With the Qwest-approved LiIon battery, you can recharge the battery before it becomes completely run down.

Displaying Your Phone Number

Just in case you forget your phone number, your wireless phone can remind you.

To display your phone number:

1. Press  to access the main menu.
2. Select **Contacts** and press .
3. Select **My Phone#** and press .

Note: To access the phone's main menu, press  from standby mode. Menu items may be selected by highlighting them with the navigation key and pressing , or you can press the number corresponding to the menu item on your keypad.

Tip: You can also display your phone number from the Phone Info menu. Press , select **Settings**, select **Phone Info**, and select **Phone#/User ID**.

Making and Answering Calls

Making Calls

Placing a call from your wireless phone is as easy as making a call from any land line phone. Just enter the number and press **TALK** and you're on your way to clear calls.


To place a call using your keypad:

1. Make sure your phone is on.
2. Enter a phone number. (If you make a mistake while dialing, press **BACK** to erase one digit at a time. Press and hold **BACK** to erase the entire number.)
3. Press **TALK** or **SPEAKER**. (To place a call when you are roaming and Call Guard is enabled, see "Using Call Guard" on page 80.)
4. When you're finished, press **END/()** to end the call.

Tip: When making calls off the network provided to you, always dial using 11 digits (1 + area code + phone number).

You can also place calls from your phone by Speed Dialing (page 31) and using your Call History listings (page 88).



Important: To maximize performance when using your wireless phone, extend the antenna before a call and do not touch the antenna during a call.



Dialing Options

Dialing options are displayed when you press **Options** (right softkey) after entering numbers in the phone's standby mode.

To select an option, highlight it and press .

- **Abbrev. Dial** to dial the phone number in your Contacts list that ends with the appropriate digits you entered. (See “Using Abbreviated Dialing” on page 31.)
- **Call** to dial the phone number.
- **Call:Speaker On** to dial the phone number in speakerphone mode.
- **Send Message** to send a text message, picture, or video (mobile numbers only). (See page 227 or 183 for details.)
- **Save Phone#** to save the phone number in your Contacts list. (See “Saving a Phone Number” on page 28.)
- **Find** to display Contacts list entries that end with the digits you entered. (See “Finding a Phone Number” on page 29.)
-  **Hard Pause** to insert a hard pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 29.)
-  **2-Sec. Pause** to insert a 2-second pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 29.)
- **Hyphen** to insert a hyphen. (Hyphens are generally for visual appeal only; they are not necessary when entering numbers.)

Tip: To speed dial a phone number, press and hold the appropriate speed dial key (locations 2-9). See “Assigning Speed Dial Numbers” on page 96.


Answering Calls

To answer an incoming call with the flip open:

1. Make sure your phone is on. (If your phone is off, incoming calls go to voicemail.)
2. Press **TALK** or **SPEAKER** to answer an incoming call. (Depending on your phone's settings, you may also answer incoming calls by opening the phone or by pressing any number key. See "Setting Any Key Answer" on page 59 for more information.)

Tip: Press **Ignore** (left softkey) when you do not want to answer the call.

To answer an incoming call with the flip closed:

1. Make sure your phone is on. (If your phone is off, incoming calls go to voicemail.)
2. When your phone rings or vibrates, press and hold the Side Voice/Call key () on the right side of the phone. (The call will be answered in speakerphone mode.)
- or -
Open the phone to use the earpiece.

Note: If the setting for Open Flip is set to "No Action," opening the phone will not answer the call. (See "Setting the Open/Close Flip Option" on page 58.)

Your phone notifies you of incoming calls in the following ways:

- The phone rings and/or vibrates.
- The LED flashes.
- The backlight illuminates.
- The screen displays an incoming call message.
- If available, the phone number of the caller is displayed.
- If the phone number is in your Contacts list, the contact's name is displayed.

The following options are also displayed by pressing **Options** (right softkey). To select an option, highlight it and press .

- **Call Guard** to answer the call when you are in roaming mode. See page 80 for setting Call Guard.
- **Answer** to answer the call.
- **Answer:Speaker** to answer the call in speakerphone mode.
- **Screen Call** to answer the call by using a pre-recorded announcement. (Appears when you are in a network service area or digital roaming area. See page 134 for the setting.)
- **Quiet Ringer** to mute the ringer. (Appears when the ringer is set.)

Tip: Your wireless phone offers additional ways to answer calls. (See page 57 for Auto Answer and see page 59 for Any Key Answer.)

Answering a Roam Call With Call Guard Enabled

Call Guard is an option that helps you manage your roaming charges when making or receiving calls while outside the network provided to you. Please see Section 2D: Controlling Your Roaming Experience for more information about roaming.

To answer a call when you are roaming and Call Guard is enabled:

1. Press  or .
2. Press  to proceed while the pop-up message is displayed.

Note: When your phone is off, in an active Sprint PCS Vision Connection, or on a Ready Link call, incoming calls go directly to voicemail.

Ending a Call

To disconnect a call when you are finished:

With the Flip open:

- ▶ Close the phone or press **END/⓪**.

With the Flip closed:

- ▶ Press and hold **⓪||**.

Note: If the setting for Close Flip is not set to “End,” closing the phone will not end the call. (See “Setting the Open/Close Flip Option” on page 58.)

Tip: Time/Date is displayed when you press **BACK** while the phone is in use.

Using the Speakerphone

The speakerphone feature lets you hear audio through the speaker and talk without holding the phone. When the speakerphone is activated, use the volume control keys on the side of the phone to adjust the volume.

To turn the speakerphone on during a call:

- ▶ Press **SPEAKER**.

– or –

Press **Options** (right softkey), highlight **Speaker On**, and press **MENU OK**.

To turn the speakerphone off during a call:

- ▶ Press **SPEAKER**.

– or –

Press **Options** (right softkey), highlight **Speaker Off**, and press **MENU OK**.

Warning! Due to higher volume levels, do not place the phone near your ear during speakerphone use.

Changing the Ringer Volume

To change the ringer volume, press the Side Volume key when the phone is open and in standby mode.

Note: To change the ringer volume from the main menu, see “Adjusting the Phone’s Volume Settings” on page 41.


Adjusting Volume During a Conversation

When you need to adjust the receiver volume during a conversation, use the side volume key, or press the navigation key up or down while a call is in progress.


Muting a Call

There are times when it’s necessary to mute a call so that your caller does not hear you or certain background noise.

To mute a call with the flip open:

- ▶ Press **Options** (right softkey), highlight **Mute**, and press . (When the phone is muted, “**Mute**” appears on the display.)


To unmute a call with the flip open:

- ▶ Press **Options** (right softkey), highlight **Unmute**, and press .


To mute a call with the flip closed:

- ▶ Simply press  (located on the side of your phone).

To unmute a call with the flip closed:

- ▶ Press  once again during a call.

Missed Call Notification

When an incoming call is not answered, the Missed Call log and the  icon are displayed on your screen.

To call the Missed Call entry:

- ▶ Press **TALK** or **SPEAKER**.

Tip: If you have two or more notifications, the event list will appear.

To erase the Missed Call log:

- ▶ Press **Dismiss** (right softkey).

Tip: If you press **END/⓪** before checking your notification, **Events** (right softkey) appears in standby mode. Press **Events** (right softkey) to display the notification list.

Calling Emergency Numbers

You can place calls to 911 (dial **9** **1** **1** and press **TALK**), even if your phone is locked or your account is restricted. Once you dial the numbers, your phone will enter Emergency mode.

Press **Options** (right softkey) to display the options. To select an option, highlight it and press **MENU OK**.

- **Speaker On** to activate speakerphone mode. (If you are in speakerphone mode, the option will appear as **Speaker Off** to deactivate.)
- **Unlock Phone** to unlock your phone (appears only if the phone is locked).
- **Close Menu** to close the pop-up menu (appears only if the phone is unlocked).

Tip: Press **My Phone** (left softkey) to display your phone number during an Emergency call.

To exit Emergency mode:

1. Press **END/⓪**.
2. Press **Options** (right softkey) to display the options.
3. Highlight **Exit Emergency** and press **MENU OK**.

To display Emergency mode options:

1. Press **END/⓪** during a 911 call.
2. Press **Options** (right softkey).
 - **Call 911** to call 911.
 - **Call 911:Speaker** to call 911 in speakerphone mode.
 - **Exit Emergency** to exit Emergency mode.
3. Select an option and press **MENU OK**.

In-Call Options

During a call, your phone displays menu options when you press **Options** (right softkey).

To select an option, highlight it and press **MENU OK**.

- **Flash** to answer an incoming Call Waiting call or to connect a third party during Three-Way Calling.
- **Mute** or **Unmute** to mute or reactivate your phone's microphone.
- **Speaker On** or **Speaker Off** to activate or deactivate speakerphone mode. You can adjust the speakerphone volume using the Side Volume key.

Warning! Due to higher volume levels, do not place the phone near your ear during speakerphone use.

- **Three-Way Call** to call a third party.
- **Call History** to access the Call History menu. (See “Managing Call History” on page 86.)
- **Contacts** to access the Contacts menu. (See “Using the Contacts Directory” on page 91.)
- **Messaging** to access the Messaging menu. (See “Messaging” on page 225.)
- **Settings** to access the Settings menu. (See “Controlling Your Phone's Settings” on page 37.)
- **Tools/Extras** to access the Tools/Extras menu. (See “Personal Organizer” on page 100.)

Note: The Flash menu appears only for Call Waiting and Three-Way Calling. The Mute menu does not appear during a 911 call. The Three-Way Call menu does not appear in Roaming areas.

End-of-Call Options

To display the following options, press **Options** (right softkey) within 10 seconds after disconnecting a call.

To select an option, highlight it and press .




- **Call Again** to dial the phone number.
- **Call:Speaker On** to dial the phone number in speakerphone mode.
- **Save Phone#** to save the phone number in your Contacts list.
 - **Go to Phone Book** appears when the number is already in your Contacts list. (See “Saving a Phone Number” below.)

Note: The End-of-Call options are not displayed for calls identified as No ID or Restricted.

Saving a Phone Number

Your SCP-7400 can store up to 500 phone numbers in up to 300 Contacts entries (an entry may contain up to seven numbers). Each entry's name can contain 16 characters. Your phone automatically sorts the Contacts entries alphabetically. (For more information, see Section 2G: Using the Contacts Directory on page 91.)





To save a number from standby mode:

1. Enter a phone number.
2. Press **Options** (right softkey).
3. Highlight **Save Phone#** and press .
4. Select a label by highlighting **Mobile**, **Home**, **Work**, **Pager**, **Fax**, **Other**, or **No Label** and press .
5. Enter a name and press . If you have already stored entries in the Contacts list, you are prompted to select the following entry modes:
 - **New Name** to enter a new name.
 - **From Ph. Book** to select a name from the Contacts entry list.
6. Press **Save** (left softkey).

Finding a Phone Number

You can search Contacts list entries for phone numbers that contain a specific string of numbers.


To find a phone number:

1. Enter the last four or more digits of the number and press **Options** (right softkey). (The more numbers you enter, the more specific the search becomes.)
2. Highlight **Find** and press . (The Contacts entry that ends with the digits you entered appears.)
3. Scroll to your desired entry.
 - Press  to display the entry details.
 - Press  or  to dial.

Dialing and Saving Phone Numbers With Pauses






You can dial or save phone numbers with pauses for use with automated systems, such as voicemail or credit card billing numbers.

There are two types of pauses available on your phone:

- **Hard Pause** sends the next set of numbers when you press .
- **2-Sec. Pause** automatically sends the next set of numbers after two seconds.

Note: You can have multiple pauses in a phone number and combine 2-second and hard pauses.

To dial or save phone numbers with pauses:

1. Enter the phone number and press **Options** (right softkey).
2. Highlight either **Hard Pause** or **2-Sec. Pause** and press . (Hard pauses are displayed as a “H” and 2-second pauses as a “T”.)
3. Enter additional numbers (for example, a passcode or an extension).
4. To dial the number, press  or . (When dialing a number with a hard pause, press  to send the next set of numbers.)
– or –
To save the number in your Contacts list, press **Options** (right softkey), highlight **Save Phone#**, and press .

Making International Calls With Plus Code Dialing

Your phone's Plus Code Dialing feature can automatically dial the international access code when you are traveling outside of the United States.

To make a call using Plus Code Dialing:

1. From standby mode, press and hold **Shift** until a "+" sign appears on the phone display.
2. Enter the country code and phone number and press **TALK** or **SPEAKER**.

To remove the plus sign from your phone's display:

- ▶ Press and hold **Shift** while the plus sign is displayed or press **END/O** to cancel the call.

Dialing From the Contacts Directory

To dial directly from a Contacts entry:

1. Press **MENU OK** to access the main menu.
2. Select **Contacts** and press **MENU OK**.
3. Select **Find/Add Entry** and press **MENU OK**.

Shortcut: Press the navigation key right to list entries.

4. Scroll to the desired entry in the Contacts list and press **MENU OK**.
5. Select the number you want to call.
6. Press **Options** (right softkey) for the menu options.
7. Highlight **Call** or **Call:Speaker On** and press **MENU OK** to place a call.

Tip: You can also place a call by pressing **TALK**, **SPEAKER**, or **Call** (left softkey) during step 5 above.

Note: The icons next to each entry represent the Contacts labels (for example, Mobile, Home, Work, etc.). A triangle next to an icon means there is another label for the entry. Press the navigation key right or left to select the desired label.

Using Speed Dialing

With this feature, you can dial your favorite entries using one key press for locations 2-9. (See “Assigning Speed Dial Numbers” on page 96.)

To use speed dial for voice calls:

- ▶ From standby mode, press and hold the appropriate key for approximately two seconds.
– or –
- ▶ From standby mode, press the appropriate key and press **TALK** or **SPEAKER**.

The display confirms that the number has been dialed when it shows “Connecting...”.

To use speed dial for Ready Link calls:

- ▶ From standby mode, press the appropriate key then press and hold **---**. (See “Assigning Speed Dialing for Ready Link Entries” on page 154.)

The display confirms that the number has been dialed when it shows “R-Link calling...”.

Note: Speed dialing is not available when you are roaming; when you are roaming off the network provided to you, you must always dial using eleven digits (1 + area code + number).

Using Abbreviated Dialing

Abbreviated Dialing is another form of speed dialing. It allows you to dial a number by entering the last 3-6 digits of any number in your Contacts directory. This feature becomes available when you set the abbreviated dialing enable and enter the appropriate digits of a phone number. See page 60 for the setting.

To place a call using Abbreviated Dialing:

1. Dial the last 3-6 digits of a contact’s phone number.
2. Press **Options** (right softkey) to display the dialing options.
3. Highlight **Abbrev. Dial** and press **MENU OK**, **TALK**, or **SPEAKER**.

Tip: You can also place a call by pressing **TALK** or **SPEAKER** during step 2 above.

Note: If there is no matched number, your phone dials the number you set for abbreviated dial with the last four or five digits you entered. If there are matched numbers in your Contacts list, the abbreviated dial list will be displayed. To place a call, select a number and press **TALK**.

Entering Text

Selecting a Character Input Mode

Your phone provides convenient ways to enter words, letters, punctuation, and numbers whenever you are prompted to enter text (for example, when adding a Contacts entry or when sending email messages).

To change the character input mode:

1. When you display a screen where you can enter text, press **Mode** (right softkey).
2. Select a character input mode:
 - **T9 Word** to enter characters using predictive T9 Text Input (see page 33).
 - **Alphabet** to enter characters by tapping the keypad (see page 34).
 - **SYMBOL** to enter symbols (see page 35).
 - **NUMBER** to enter numbers (see page 35).
 - **PRESET SUFFIX** to enter a preset suffix (see page 35).
 - **SMILEYS** to enter smile pictures (see page 36).
 - **Emoticons** to enter pictorial symbols (see page 36).

Entering Characters Using T9 Text Input

T9 Text Input lets you enter text in your SCP-7400 by pressing keys just once per letter. (To select the **T9 Word** mode when entering text, see “Selecting a Character Input Mode” on page 32.)

T9 Text Input analyzes the letters you enter using an intuitive word database and creates a suitable word. (The word may change as you enter more letters.) If the word you want does not display after you have entered all the letters, press **Next O** to scroll through additional word selections. To accept a word and insert a space, press **Space #**.

If you make a mistake, press **BACK** to erase a single character. Press and hold **BACK** to delete an entire entry.

Adding a Word to the T9 Database

If a word you want to enter does not display as an option when you are using T9 Text Input, you can add it to the database.

To add a word to the T9 Text Input database:

1. Select the **Alphabet** input mode. (See “Selecting a Character Input Mode” on page 32.)
2. Enter the word using multi-tap text entry. (See “Entering Characters by Tapping the Keypad” on page 34.)
3. Press **Mode** (right softkey), highlight **T9 Word**, and press **MENU OK**. (The word will appear as an option the next time you scroll through options during T9 Text Input.)

For more information about T9 Text Input, visit the Tegic Website at www.T9.com.

Entering Characters by Tapping the Keypad

To enter characters by tapping the keypad, select the **Alphabet** mode (see “Selecting a Character Input Mode” on page 32). Press the corresponding key repeatedly until the desired character appears. By default, the first letter of an entry is capitalized and following letters are lowercase.

Characters scroll in the following order:

Key	English Sequence	
	Upper Case	Lower Case
1	., @ 1 ? ! * # /	
2	A B C 2	a b c 2
3	D E F 3	d e f 3
4	G H I 4	g h i 4
5	J K L 5	j k l 5
6	M N O 6	m n o 6
7	P Q R S 7	p q r s 7
8	T U V 8	t u v 8
9	W X Y Z 9	w x y z 9
Next 0	0	
Space #	Space	
Shift ✕	Unshifted One-character- shifted Caps Lock	

In Spanish mode, characters scroll in the following order:

Key	Spanish Sequence	
	Upper Case	Lower Case
1	., @ 1 ¿ ? ¡ ! * # /	
2	A Á B C 2	a á b c 2
3	D E É F 3	d e é f 3
4	G H I Í 4	g h i í 4
5	J K L 5	j k l 5
6	M N Ñ O Ó 6	m n ñ o ó 6
7	P Q R S 7	p q r s 7
8	T U Ú Ü V 8	t u ú ü v 8
9	W X Y Z 9	w x y z 9
Next 0	0	
Space #	Space	
Shift ✕	Unshifted One-character- shifted Caps Lock	



(See page 66 for changing to Spanish language mode.)

After a character is entered, the cursor automatically advances to the next space after two seconds or when you enter a character on a different key.


Tip: The beginning of the word after the space is changed to upper/lower case depending on shift mode. You can change the shift mode by pressing **Shift ✕**.

Entering Symbols, Numbers, Preset Suffixes, Smileys, and Emoticons

To enter symbols:

1. In a text entry field, press **Mode** (right softkey).
2. Highlight **SYMBOL** and press .
3. Highlight the line that includes your desired symbol.
4. Press the corresponding key (1-8) with each symbol.
– or –
Highlight your desired symbol by using the navigation key and press .



To enter numbers:

1. In a text entry field, press **Mode** (right softkey).
2. Highlight **NUMBER** and press .
3. Press the corresponding number key to enter the number.



Shortcut: Press and hold the corresponding number key to enter the number directly in alphabet mode or T9 mode.

To enter preset suffixes:

The Preset Suffix menu is a preprogrammed list of common prefixes, suffixes, and punctuation strings (for example, “www.”, “.com”, and “//”) designed to make text entry easier and more efficient.



1. In a text entry field, press **Mode** (right softkey).
2. Highlight **PRESET SUFFIX** and press .
3. Highlight your desired word by using the navigation key and press .

To enter smileys:

1. In a text entry field, press **Mode** (right softkey).
2. Highlight **SMILEYS** and press .
3. Highlight the line that includes your desired smiley.
4. Press the corresponding key (1-4) with each smiley.
– or –
Highlight your desired smiley by using the navigation key and press .

Note: Preset Suffix and Smileys do not apply in Ready Link mode.

To enter emoticons:

1. In a text message entry field, press **Mode** (right softkey).
2. Highlight **Emoticons** and press .
3. Highlight the line that includes your desired emoticon.
4. Press the corresponding key (1-4) with each emoticon.
– or –
Highlight your desired emoticon by using the navigation key and press .

Note: Emoticons are only available when composing text messages.

Controlling Your Phone's Settings

In This Section

- ◆ Sound Settings
 - ◆ Display Settings
 - ◆ Location Settings
 - ◆ Airplane Mode
 - ◆ TTY Use
 - ◆ Phone Setup Options
-

Using the menu options available on your wireless phone, you can customize your phone to sound, look, and operate just the way you want it to.

This section describes how you can change your phone's settings to best suit your needs. Take a few moments to review these options and to adjust or add settings that are right for you.

Sound Settings

Ringer Types








Ringer types help you identify incoming calls and messages. You can assign ringer types to individual Contacts entries, types of calls, and types of messages.

- **Preprogrammed Ringers** include a variety of standard ringer types and familiar music.
- **Vibrating Ringer** alerts you to calls or messages without disturbing others.
- **Downloaded Ringers** can be downloaded right to your phone. (See “Downloading Premium Services Content” on page 238 and “Ringers” on page 242.)



Selecting Ringer Types for Voice Calls

Your Sanyo SCP-7400 provides a variety of ringer options that allow you to customize your ringer and volume settings. These options allow you to identify incoming calls by the ringer.

To select a ringer type for voice calls:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Ringer Type** and press .
5. Select **Voice Calls** and press .
6. Select **With Caller ID** or **No Caller ID** and press .
7. Scroll to your desired ringer type and press .








To select a distinctive ringer for voice calls while roaming:

1. Follow steps 1-5 above.
2. Select **Roaming** and press .
3. Select **Distinctive** and press 
 - To confirm the ringer, press **Play** (right softkey).
 - If you want to deactivate this feature, select **Normal** during step 3 above.

Note: When you are in analog area, the Distinctive ringer will be played even if your voice call setting of roaming is Normal.








Selecting Ringer Types for Ready Link Calls

To select a ringer type for Ready Link calls:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Ringer Type** and press .
5. Select **Ready Link** and press .
6. Select **Ready Link Calls**, **R-Link Missed**, or **R-Link Floor Tone**, and press .
7. Scroll to your desired ringer type and press .

Selecting Ringer Types for Voicemail, Messages, or Calendar/Alarm







To select a ringer type for voicemail, messages, or calendar/alarm:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Ringer Type** and press .
5. Select **Voicemail**, **Messages**, or **Calendar/Alarm**, and press .
6. Press , scroll to your desired ringer type, and press .



Selecting a Tone Length

Longer tone lengths may be better for tone recognition when dialing voicemail or other automated systems.

To select a tone length:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Others** and press .
5. Select **Tone Length** and press .
6. Select **Short** or **Long** and press .

Setting a Start-up/Power-off Tone







1. Follow steps 1-4 in “Selecting a Tone Length.”
2. Select **Start-up Tone** or **Power-off Tone** and press .
3. Scroll to your desired tone and press .

Tip: You can set the volume of Start-up Tone and Power-off Tone. See next page.

Using Voice Prompt

This feature allows you to hear voice prompts at Automatic Speech Recognition (ASR), Voice Memo, Screen Call setting, etc. (default setting is On).

To deactivate this feature:







1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Others** and press .
5. Select **Voice Prompt** and press .
6. Select **Off** and press .

Tip: When ringer volume is set to “Silence All,” voice prompts cannot be heard.

Setting Up Key Press Echo

With this feature, your phone echoes the number when you press the keypad. This feature is available when you are in standby mode.







To activate Key Press Echo:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Others** and press .
5. Select **Key Press Echo** and press .
6. Select **On** and press .
 - To deactivate this feature, select **Off** during step 6 above.







Adjusting the Phone's Volume Settings

You can adjust your phone's volume settings to suit your needs and your environment.

To adjust the ringer and key volume:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Ringer/Key Vol.** and press .
5. Select **Ringer Volume**, **Calendar/Alarm**, **Start-up/Pw-off**, or **Key Beep** and press .
6. Adjust a volume level by pressing the navigation key up or down and press .




To adjust the earpiece or speaker volume:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Receiver Vol.** and press .
5. Select either **Earpiece** or **Speaker** and press .
6. Adjust a volume level by pressing the navigation key up or down and press .

Tip: You can adjust the ringer volume in standby mode (or the earpiece volume during a call) by using the Side Volume key.

To adjust the application volume:






This setting is available for the volume of video, Media Player, downloaded data, and browser.

1. Follow steps 1-3 above.
2. Select **Application Vol.** and press .
3. Press , adjust a volume level by pressing the navigation key up or down, and press .

Alert Notification

Your phone can alert you with an audible tone when you change service areas, once a minute during a voice call, for incoming or missed Ready Link calls, or when a call has been connected.

To set alerts:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Alerts** and press .
5. Select your desired option and press .
 - **Service** sets an alert to notify you of network services parameter changes.
 - **Ready Link** sets an alert to notify you of Ready Link calls. Select **Ready Link Calls** for incoming Ready Link calls, or **R-Link Missed** for missed Ready Link calls.
 - **Voicemail** sets an alert to notify you of voice messages.
 - **Messaging** sets an alert to notify you of text messages.
 - **Minute Beep** sets a minute reminder that beeps ten seconds before the end of each minute during a call.
 - **Signal Fade** sets an alert to notify you when your phone loses a signal during a call.







Tip: You can select **Once** or **Repeat Alert** if you select Ready Link Calls, R-Link Missed, Voicemail, or Messaging. **Repeat Alert** sounds an alert every two minutes for twenty minutes.

Tip: To set alerts for Ready Link calls, see “Setting an Alert Notification for Ready Link Calls” on page 156 for details.

Silence All

There may be times when you need to silence your phone entirely. The phone's Silence All option allows you to mute all sounds without turning your phone off.

To activate Silence All:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Ringer/Key Vol.** and press .
5. Select **Ringer Volume** and press .
6. Press the navigation key down until **Silence All** appears on the display and press .

Tip: When Ringer Volume is set as Silence All, other items are changed to Off and cannot be highlighted.

To deactivate Silence All:







- ▶ Press the volume key up repeatedly to select a desired volume level.

Display Settings


Changing the Text Greeting

The text greeting can be up to fifteen characters and is displayed on your phone's screen in standby mode. You may choose to display a custom greeting or you may display the phone's default greeting on the screen.

To display or change your custom greeting:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Greeting** and press .
5. Select **Custom** and press 
 - You can customize the greeting by entering a personalized greeting. (See “Entering Text” on page 32.)
6. Press .







To display the default greeting:

1. Follow steps 1-4 above.
2. Select **Default** and press 
 - When you are in Ready Link mode, “Ready Link” appears on the display instead of the default greeting.

Changing the Backlight Time Length



The backlight setting lets you select how long the display screen and keypad are backlit after any key press is made.

To change the Main LCD or Sub LCD backlight setting:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Backlight** and press .
5. Select **Main LCD** or **Sub LCD** and press .
6. Select **Always On**, **Always Off**, or your defined time length and press .
 - **Always Off** always turns the backlight off.
 - **Always On** keeps the backlight on indefinitely.

Note: The **Always On** setting returns to the previous value the next time you turn on the phone.

To change the Keypad backlight setting:










1. Select **Key** during step 5 above, and press .
2. Select **Always Off** or your defined time length and press .

Note: Long backlight settings affect the battery's talk and standby times.

Changing the Display Screen Animation

Your new wireless phone offers options for what you see on the display screen during various phone functions.







To change the animation display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Animation** and press .
5. Select **Standby**, **Outgoing Calls**, or **Service Search**, and press .
6. Press , scroll to your desired option and press .
 - Press **Preview** (right softkey) to see a sample display.
 - For standby, you can also set the animation starting time. Select **after** and press , then highlight your desired setting time and press .
 - To deactivate this feature, select **Off** during step 6 above.

Changing the Display for Incoming Calls

You can set the color or downloaded image to be shown on the Incoming Calls display.






To set your incoming calls display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Incoming Calls** and press .
5. Press , scroll to your desired color or image, and press .

Changing the Display for Area Name

This feature enables you to show the area of the phone number you are calling or are called from when the number is not registered in your Contacts list. For example, a call to or from 213-555-5555 will display “California.”








To set your area name display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Match Area Code** and press .
5. Select **On** or **Off** and press .
 - This feature is available only when the phone number is 10 digits, or 11 digits beginning with 1 and matches an area code.
 - The area name will not be displayed when the number of an incoming call is saved in your Contacts list.


Changing the Display for Standby Mode

This feature enables you to select a variety of items to display in standby mode.

To set your standby display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Standby Display** and press .
5. Select **Main LCD** or **Sub LCD** and press .
6. Select your desired item and press .
 - **Screen Saver** selects the screen saver to display.
 - **Calendar** displays the Calendar. (Main LCD only.)
 - **Digital Clock** displays the local time in digital view.
 - **Analog Clock** displays the local time in analog view.
 - **World Clock** displays the time of the selected city or country along with the local time. Press the navigation key right or left to change the city or country. Press **Summer** (left softkey) or **Standard** (right softkey) to change between Daylight Savings and standard time if applicable. (The  icon indicates Daylight Savings time.)

Tip: You can also display the World Clock from Tools/Extras menu. (See “Using the World Clock” on page 113.)









- **Default** returns the standby display to its default setting.
7. Press  to save the setting to follow each system prompt or when confirming the preview display.

Tip: In an area without service, the signal search display appears instead of the display for standby mode.

Changing the Screen Saver

Your new phone offers you the option of displaying a screen saver while in standby mode.






To assign a screen saver:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Standby Display** and press .
5. Select **Main LCD** or **Sub LCD** and press .
6. Select **Screen Saver** and press .
7. Press , scroll to your desired screen saver and press .
8. Press **Save** (left softkey) to save the screen saver.
 - To see a display preview of an image, press **Preview** (right softkey) during step 7 above.

Changing the Phone's Menu Style

Your phone allows you to choose how the main menu appears on your display screen.







To select the main menu style:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Main Menu** and press .
5. Select either **Graphic** or **Text** and press .

Changing the Display for My Buddy

This feature enables you to see a funny animation on the Main LCD and Sub LCD by opening and closing the flip.







To activate or deactivate My Buddy:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **My Buddy** and press .
5. Select **Main LCD** or **Sub LCD** and press .
6. Select **On** or **Off** and press .
 - Press **Preview** (right softkey) during step 6 above to see a display preview.

Changing the Background

You can customize your phone display's appearance by selecting a color scheme to reflect your personality.







To change the display's background:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Background** and press .
5. Select **Main LCD** or **Sub LCD** and press .
6. Select your desired color and press .

Changing the Font Size

You can change the font size settings for the message notification and browser.

To change the font size:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Font Size** and press .
5. Select either **Message** or **Browser** and press .
6. Select your desired font size.
 - Press **Preview** (right softkey) to display a font size example.
7. Press  to set the selected font.

Tip: From the font example display, select your desired font size by pressing the navigation key right or left.






Location Settings



Your Sanyo SCP-7400 Phone is equipped with a Location feature for use in connection with location-based services that may be available in the future.

The Location feature allows the network to detect your position. Turning Location off will hide your location from everyone except 911.

Note: Even if the Location feature is enabled, no service may use your location without your express permission.

To enable your phone's Location feature:







1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Location** and press . (You will see a message on the display.)
4. Press  or **OK** (left softkey) to continue.
 - Press the navigation key down to read the whole message.
5. Select **On** and press .
 - To deactivate this feature, select **Off** during step 5 above.

When the Location feature is on, your phone's standby screen will display the  icon. When Location is turned off, the  icon will display.

Airplane Mode

Airplane Mode allows you to use many of your phone's features, such as Games, Voice Memos, etc., when you are in an airplane or in any other area where making or receiving calls or data is prohibited. When your phone is in Airplane Mode, it cannot send or receive any calls or access online information.

To set your phone to Airplane Mode:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Airplane Mode** and press . (You will see a message on the display.)
5. Press  or **OK** (left softkey) to continue.
 - Press **Cancel** (right softkey) to return to previous menu.
6. Select **On** and press .
 - To deactivate this feature, select **Off** during step 6 above.

While in Airplane Mode, your phone's standby screen will display "Phone off."



TTY Use

A TTY (also known as a TDD or Text Telephone) is a telecommunications device that allows people who are deaf or hard of hearing, or who have speech or language disabilities, to communicate by telephone.

Your phone is compatible with select TTY devices. Please check with the manufacturer of your TTY device to ensure that it supports digital wireless transmission. Your phone and TTY device will connect via a special cable that plugs into your phone's headset jack. If this cable was not provided with your TTY device, contact your TTY device manufacturer to purchase the connector cable.

When establishing your wireless service, please call Qwest via the state Telecommunications Relay Service (TRS) by first dialing **7 1 1 TALK**. Then provide the state TRS with this number: 866-727-4889.

To turn TTY mode on or off:

1. Press to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **TTY** and press . (You will see a message on the display.)
5. Press or **OK** (left softkey) to continue.
6. Select **Enable** or **Disable** and press .

Note: When you connect TTY devices, your phone will display the icon in TTY mode. If TTY mode is enabled, the audio quality of non-TTY devices connected to the headset jack may be impaired.

IMPORTANT NOTICE: 911 Emergency Calling

Qwest recommends that TTY users make Emergency calls by other means, including Telecommunications Relay Services (TRS), analog cellular, and landline communications. Wireless TTY calls to 911 may be corrupted when received by public safety answering points (PSAPs) rendering some communications unintelligible. The problem encountered appears related to TTY equipment or software used by PSAPs. This matter has been brought to the attention of the FCC, and the wireless industry and PSAP community are currently working to resolve this.

Phone Setup Options


Shortcut

Your phone offers you the option of assigning a shortcut key to a favorite or often-used function. Pressing the navigation key to the left in standby mode will launch your personally designated shortcut.


To assign your shortcut key:

1. Press the navigation key left.
2. Select an unassigned number and press **Add** (right softkey).
3. Select your desired menu and press **Assign** (right softkey).



To use the shortcut menu:

1. Press the navigation key left.
2. Select the menu you want to use and press .

To edit the shortcut name:

1. Press the navigation key left.
2. Select your desired menu and press **Options** (right softkey).
3. Highlight **Edit Name** and press .
4. Edit the name and press **OK** (left softkey).
5. Press **Save** (left softkey) to save the name.







To unassign the shortcut:

1. Press the navigation key left.
2. Select your desired menu and press **Options** (right softkey).
3. Highlight **Unassign** and press .
4. Select **Yes** and press 
 - To unassign all shortcuts, select **Unassign All** during step 3 above.

Auto Answer Mode

You may set your phone to automatically pick up incoming calls in speakerphone mode or when connected to an optional hands-free car kit and headset (sold separately).







To set **Auto Answer mode**:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Auto Answer** and press .
5. Select **Car Kit/Headset** or **Speakerphone** and press .
6. Select either **5 Seconds** or **15 Seconds** and press .
 - To deactivate this feature, select **Off** during step 6 above.



Setting the Open/Close Flip Option

This feature enables you to answer an incoming call by opening the flip or to end a call by closing the flip.

To activate the Open Flip feature:


1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Open/Close Flip** and press .
5. Select **Open** and press .
6. Select **Answer Call** and press .
 - To deactivate this feature, select **No Action** during step 6 above.

To activate the Close Flip feature:






1. Follow steps 1-4 above.
2. Select **Close** and press . (You will see a message on the display.)
3. Press **OK** (left softkey) to continue.
4. Select an option from the following and press .
 - **End** to end the call.
 - **Continue(Mute)** to continue the call. Your voice is muted, however you can hear the caller's voice from the speaker.
 - **Contin(Unmute)** to continue the call. You can hear the caller's voice and speak to the phone to answer.

Note: The Close Flip feature does not apply during Ready Link calls or when you are using the speakerphone, a headset, or a car kit.


Setting Any Key Answer

This feature allows you to answer incoming calls by pressing any number keys and  in addition to **TALK** and **SPEAKER**.






To activate this feature:

1. Press  to access the main menu.
 2. Select **Settings** and press .
 3. Select **Others** and press .
 4. Select **Any Key Answer** and press .
 5. Select **On** and press .
- To deactivate this feature, select **Off** during step 5 above.

Setting the Side Key Guard

This feature enables you to lock your side keys (, , , and the Side Camera key) while the flip is closed.

To activate this feature:

1. Press  to access the main menu.
 2. Select **Settings** and press .
 3. Select **Others** and press .
 4. Select **Side Key Guard** and press .
 5. Select **On** and press .
- **Key Guard** appears on the Sub LCD while the flip is closed.
 - To deactivate this feature, select **Off** during step 5 above.







Note: This feature does not apply when the flip is open.

Tip: You can deactivate this feature temporarily to use side keys by pressing and holding  while the clamshell is closed.

Setting Abbreviated Dialing




Abbreviated Dialing is another form of speed dialing. It allows you to dial a number by entering 3-6 digits of any number in your Contacts Directory. If the digits you enter do not match any stored Contacts entry, your phone will automatically prepend the digits you specify.

To activate this feature:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Abbrev. Dial** and press .
5. Select **Ph. Book Match** and press .
6. Select **Enable** and press .

Tip: With the Phone Book match feature, your phone displays the Contact's name and phone number if the incoming call or outgoing call is in your Contacts list.

To set your prepend number:

1. Follow steps 1-4 above.
2. Select **Prepend** and press .
3. Select **Enable** and press .
4. Select **Prepend#** and press .
5. Enter a five- or six-digit number and press  or **OK** (left softkey).
 - To deactivate this feature, highlight **Disable** during step 3 above.






Tip: If you enter fewer than 5 digits, the display shows a warning message.

Tip: To dial the prepend number, see "Using Abbreviated Dialing" on page 31.

Setting the Meeting Mode



This feature allows you to hold an incoming call when you cannot answer immediately.

To set the Meeting mode:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Meeting Mode** and press .
5. Select **On** and press .
 - **Meeting** appears above the softkeys in Meeting mode.
 - To deactivate this feature, select **Off** during step 5 above.

Tip: Press and hold  to set this feature in standby mode.






To use the Meeting mode:

1. Press  when you receive an incoming call.
2. The caller hears a message to wait your answer.
3. Press  to answer the call.

Headset Mode

This feature allows you hands-free phone use. Set the headset mode to Voice Call or Ready Link and press the Turbo Button (the operation button) on the headset to activate useful functions.

To set headset mode:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Headset Mode** and press .
5. Select **Voice Call** or **Ready Link** and press .
 - To deactivate this feature, select **Off** during step 5 above.

Using the phone with headset mode activated:







- **Voice Call:** Press the Turbo Button to activate ASR (Automatic Speech Recognition). Press twice to redial the last call. Press and hold the button to record a Voice Memo. (See page 123 for ASR.)
- **Ready Link:** Press the Turbo Button to make a Ready Link call by using ASR (Automatic Speech Recognition). Press twice to redial the last Ready Link call. (See page 123 for ASR.)

Note: If your headset doesn't have a Turbo Button, set headset mode to Off.

Setting Return to Standby Mode

This feature allows you to select the way to return to standby mode.

To set this feature:







1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Return to Idle** and press .
5. A message appears. Press **OK** (left softkey) to continue.
6. Select **Automatically** or **End Key** and press .
 - **Automatically** to return to standby mode automatically in 30 seconds.
 - **End Key** to return to standby mode by pressing .

Note: **End Key** setting affects the battery's talk and standby times.

Sleep Mode

This feature helps conserve your battery power by restricting the display.






To set sleep mode:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Sleep Mode** and press .
5. Select **Main LCD** or **Sub LCD** and press .
6. Select your desired option and press .
 - To deactivate this feature, select **Off** during step 6 above.

Setting Message Notification

You can see an icon and/or a pop-up message notification when you receive a text message or voicemail while you are in Sprint PCS Vision applications, browser mode, or voice calls.








To set message notification:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Messaging** and press .
4. Select **Notification** and press .
5. Select **Msgs and Icon** or **Icon Only** and press .
6. Press **Save** (left softkey).

Editing Preset Messages

Your phone can store pre-set messages for use with text messaging and email. You can edit your phone's default preset messages through the Settings menu.

To edit your phone's preset messages:







1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Messaging** and press .
4. Select **Preset Msgs** and press .
5. Select the message you want to edit and press .
6. Use your keypad to edit the message and press **OK** (left softkey) or  to save your changes. ("Preset Msgs Saved" will display.)
 - To reset all messages, press **Options** (right softkey), select **Reset All Msgs**, and press  during step 5 above.

Note: For information on editing text, see "Entering Text" on page 32.

Setting a Callback Number

With this feature, you can notify your recipients of your callback number with the text message.








To set the callback number:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Messaging** and press .
4. Select **Send Callback#** and press .
5. Select an option from the following and press .
 - **None** to send no callback number.
 - **My Phone#** to send your phone number.
 - **Other** to send a specific callback number. To set a number, enter a phone number and press .

Setting Your Signature

This feature allows you to send a message with your signature.

To set your signature:






1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Messaging** and press .
4. Select **Signature** and press .
5. Press , select **On**, and press .
6. Select **Text** and press .
7. Enter your signature and press **OK** (left softkey).
8. Press **Save** (left softkey) to save your signature.

Note: You can put your set signature even when your signature setting is off. To put the signature, press **Mode** (right softkey) and select **Signature** while composing your message.

Display Language

You can choose to display your phone's onscreen menus in English or in Spanish.



To assign a language for the phone's display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Others** and press .
4. Select **Language** and press .
5. Select **English** or **Español** and press .

Using the Mini-Flashlight

This function allows you to use the phone's camera flash as a miniature flashlight. To use this function, your phone must be in standby mode with the Side Key Guard unlocked. (See page 59 for the Side Key Guard.)

To use the mini flashlight:

- ▶ With the flip closed and in standby mode, press and hold the Side Volume key ( ). (The light flashes for 8 seconds.)

Note: This function doesn't apply when a Missed Call or Notification is displayed.

Setting Your Phone's Security

In This Section




- ◆ **Accessing the Security Menu**
 - ◆ **Using Your Phone's Lock Feature**
 - ◆ **Restricting Calls**
 - ◆ **Using Special Numbers**
 - ◆ **Erasing the Contacts Directory**
 - ◆ **Erasing All Voice Tags**
 - ◆ **Erasing All Downloads**
 - ◆ **Resetting Your Pictures Account**
 - ◆ **Resetting Your Phone**
 - ◆ **Resetting and Locking Your Phone Through SMS**
 - ◆ **Security Features for Sprint PCS Vision™**
-

By using the security settings on your wireless phone, you receive peace of mind without sacrificing flexibility. This section will familiarize you with your phone's security settings. With several options available, you can customize your phone to meet your personal needs.

Accessing the Security Menu

All of your phone's security settings are available through the Security menu. You must enter your lock code to view the Security menu.

To access the Security menu:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Security** and press .
4. Enter your lock code. (The Security menu is displayed.)




Tip: If you can't recall your lock code, try using the last four digits of either your Social Security number or phone number or try 0000. If none of these work, call Qwest Wireless™ Repair at 1-877-879-0611.

Using Your Phone's Lock Features

Locking Your Phone

When your phone is locked, you can only receive incoming calls or make calls to 911 or special numbers.

To lock your phone:

1. From the Security menu (see "Accessing the Security Menu" above), select **Lock Phone** and press .
2. Select **Lock Now** or **On Power-up** and press .
3. Depending on your preference, highlight either **Full Lock** or **Excp. Incom.Calls** and press 
 - **Full Lock:** No phone calls can be made and only special numbers can be received. (You can still make a call to an Emergency number and special numbers.)
 - **Excp. Incom.Calls:** No phone calls can be made, however all incoming calls can be received. (You can still make a call to an Emergency number and special numbers.)

Tip: If you want to cancel the "On Power-up" setting before turning the phone off, select **Unlocked** during step 2 above.

Unlocking Your Phone



To unlock your phone:

1. Press **Unlock** (left softkey).
2. Enter your lock code.

Locking the Picture and Video Menu

With this feature, you must enter your lock code when you access the Picture and Video menu.





To lock the Pictures menu:

1. From the Security Menu (see “Accessing the Security Menu” on page 68), select **Lock Pic&Video** and press .
2. Select **Lock Now** and press 
 - To deactivate this feature, select **Unlocked** during step 2 above.

Locking Voice Calls

With this feature, you will not be able to make or receive voice calls except 911.





To lock voice calls:

1. From the Security Menu (see “Accessing the Security Menu” on page 68), select **Others** and press .
2. Select **Lock Services** and press .
3. Select **Voice Calls** and press .
4. Select **Locked** and press 
 - To deactivate this feature, select **Unlocked** during step 4 above.

Locking Ready Link Calls

With this feature, you will not be able to make or receive Ready Link calls.



To lock the Ready Link calls:

1. From the Security Menu (see “Accessing the Security Menu” on page 68), select **Others** and press .
2. Select **Lock Services** and press .
3. Select **Ready Link** and press .
4. Select **Locked** and press 
 - To deactivate this feature, select **Unlocked** during step 4 above.

Tip: The Ready Link/Memo button () will be used as a memo button in Ready Link locked state.

Changing the Lock Code

To change your lock code:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Others** and press .
2. Select **Change Lock** and press .
3. Enter a new lock code (“1234” for example).
4. Reenter the new code.

Calling in Lock Mode

You can place calls to 911 and to your special numbers when in lock mode. (For information on special numbers, see “Using Special Numbers” on page 72.)





To place an outgoing call in lock mode:

- ▶ To call an Emergency number or special number, enter the phone number and press .

Restricting Calls

There may be occasions when you want to limit the numbers your phone can call or from which it can receive calls. You can use the Restrict Calls setting to do just that. (The Restrict Calls setting does not apply to 911.)

To restrict calls:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Others** and press .
2. Select **Limit Use** and press .
3. Select **Outgoing Calls** or **Incoming Calls** and press .
4. Select your desired option and press .
 - **Allow All** lets you make or receive all calls.
 - **PhoneBook Only** lets you make or receive calls to or from Contacts entries, voicemail, or special numbers only.
 - **Special #s Only** lets you make or receive calls to or from three special numbers only. (See “Using Special Numbers” on page 72.)






Note: Restricted incoming calls are forwarded to voicemail.

Using Special Numbers



Special numbers are important numbers that you have designated as being “always available.” You can call and receive calls from special numbers even if your phone is locked.

You can save three special numbers in addition to your Contacts entries (the same number may be in both directories).

To add or replace a special number:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Others** and press .
 2. Select **Special #s** and press .
 3. Select an entry number and press .
 4. Enter your desired phone number and press .
- or –
- Press **Options** (right softkey), select **From Phone Book** or **Voicemail**, and press .

To insert pauses into a special number:



1. From step 4 above, enter a phone number and press **Options** (right softkey) for the options.
2. Highlight **Hard Pause**, **2-Sec. Pause**, or **Hyphen** and press .
3. Finish entering the rest of the numbers and press .

Note: Special Numbers cannot make or receive calls in voice call locked state.

Erasing the Contacts Directory

You can quickly and easily erase all of the contents of your Contacts Directory.



To erase all the names and phone numbers in your Contacts Directory:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Erase Ph. Book** and press .
2. If you're sure you want to erase your Contacts, select **Yes** and press .

Erasing All Voice Tags



You can quickly and easily erase all voice tags you have recorded.

To erase the voice tags:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Erase VoiceTag** and press .
2. If you're sure you want to erase the voice tags, select **Yes** and press .

Erasing All Downloads



To erase all data downloaded from the Web:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Erase Download** and press .
2. If you're sure you want to erase all data downloaded from the Web, select **Yes** and press 
 - If you have assigned downloaded data, the function returns to its default setting.

Resetting Your Pictures Account

This option resets your authentication ID for your Sprint PCS Picture Mail account.

To reset your pictures account:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Reset Pictures** and press .
2. If you're sure you want to reset your pictures account, select **Yes** and press .



After resetting, you are prompted to reenter the password when you use Online Pictures.

Note: Your account will be locked if you enter wrong password 10 times after resetting your account. In this case, please contact Qwest Wireless™ Repair.

Resetting Your Phone

Resetting the phone restores all the factory defaults, including the ringer types and display settings. The Contacts, Call History, Scheduler, and Messaging are not affected.





To reset your phone:

1. From the Security Menu display (see “Accessing the Security Menu” on page 68), select **Reset Phone** and press .
2. If you're sure you want to reset your phone, select **Yes** and press .





Enabling and Disabling Sprint PCS Vision Services

You can disable Sprint PCS Vision services without turning off your phone; however, you will not have access to all Sprint PCS Vision services, including Web and Email. Disabling Sprint PCS Vision will avoid any charges associated with Sprint PCS Vision services. While signed out, you can still place or receive phone calls, check voicemail, and use other voice services. You may enable Sprint PCS Vision services again at any time.

To disable Sprint PCS Vision services:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **PCS Vision** and press .
4. Select **Disable Vision** and press . (A message will appear.)
5. Press **Disable** (right softkey) to confirm that you want to sign out.

To enable Sprint PCS Vision services:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **PCS Vision** and press .
4. Select **Enable Vision** and press .
5. Press **OK** (left softkey) to sign in.

Controlling Your Roaming Experience

In This Section

- ◆ Understanding Roaming
 - ◆ Setting Your Phone's Roam Mode
 - ◆ Using Call Guard
-



Roaming is the ability to make or receive calls when you're off the network provided to you. Your new dual-band/tri-mode wireless phone works anywhere on the network provided to you and allows you to roam on other analog and 1900 and 800 MHz digital networks where roaming agreements have been implemented with other carriers.

This section explains how roaming works as well as special features that let you manage your roaming experience.

Understanding Roaming

Recognizing Icons on the Display Screen

Your phone's display screen always lets you know when you're off the network provided to you and whether your phone is operating in analog or digital mode. The following chart indicates what you'll see depending on where you're using your phone.

Main LCD/Sub LCD	Roaming Indicator	Analog Indicator
Provided Network		
Other Digital Networks		
	Digital Roam	
Analog Networks		
		Analog Roam

Tip: Remember, when you are using your phone off the network provided to you, always dial numbers using 11 digits (1 + area code + number).

Note: You will pay a higher per-minute rate for roaming calls.

Roaming on Other Digital Networks

When you're roaming on digital networks, your call quality and security will be similar to the quality you receive when making calls on the network provided to you. However, you may not be able to access certain features, such as Sprint PCS Vision.

Note: Ready Link Service is not available in roaming areas.

Roaming on Analog Networks

When you roam on analog networks, you will experience a similar quality provided by other analog carriers today. Although some features, such as Sprint PCS Vision and Ready Link, will be unavailable, you can still make and receive calls and access voicemail. If you are accustomed to network service, you may notice some of the following differences when using analog service:

- You are more likely to experience static, cross-talk, fade-out, and dropped calls.
- Some features which are standard on the network provided to you, such as call waiting, Sprint PCS Vision, Ready Link, and direct international dialing, may not be available.
- Though callers can leave voicemail messages while you are roaming, you may not receive notification until you return to the network provided to you. (See “Checking for Voicemail Messages While Roaming” on page 79.)
- There are security and privacy risks (eavesdropping and cloning) that exist with conventional analog services today.
- Your battery’s charge will deplete more quickly and you will need to recharge it more often when you use your phone for analog roaming.

Note: If you’re on a call when you leave the network provided to you and enter an area where roaming is available (whether digital or analog), your call is dropped. If your call is dropped in an area where you think network service is available, turn your phone off and on again to reconnect to the network provided to you.

Note: When using your phone in analog mode, the phone may feel warm. This is normal for analog operation.

Checking for Voicemail Messages While Roaming

When you are roaming off the network provided to you, you may not receive on-phone notification of new voicemail messages. Callers can still leave messages, but you will need to periodically check your voicemail for new messages if you are in a roaming service area for an extended period of time.

To check your voicemail while roaming:

- ▶ Dial 1+area code+your wireless phone number.

When you return to the network provided to you, voicemail notification will resume as normal.






Setting Your Phone's Roam Mode

Your phone allows you to control your roaming capabilities. By using the **Roaming** menu option, you can determine which signals your phone accepts.

Set Mode

Choose from three different settings on your dual-band/tri-mode phone to control your roaming experience.






To set your phone's roam mode:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Roaming** and press .
4. Select **Set Mode** and press .
5. Select an option from the following and press .
 - **Digital** allows you to access the network provided to you only and prevents roaming on other networks.
 - **Automatic** seeks network service. When network service is unavailable, the phone searches for an alternate system.
 - **Analog** forces the phone to seek an analog roaming system. The previous setting (Digital or Automatic) is restored the next time the phone is turned on.






Using Call Guard

Your phone has two ways of alerting you when you are roaming off the network provided to you: the onscreen roaming icon and Call Guard. Call Guard makes it easy to manage your roaming charges by requiring an extra step before you can place or answer a roaming call. (This additional step is not required when you make or receive calls while on the network provided to you.)





To turn Call Guard on or off:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Roaming** and press .
4. Select **Call Guard** and press .
5. Select **On** or **Off** and press .

To place roaming calls with Call Guard on:

1. From standby mode, dial 1 + area code + the seven-digit number. (You can also initiate a call from the Contacts directory, Call History, or Messaging.)
2. Press  or  (or press **Options** [right softkey] and highlight **Call** or **Call:Speaker On**) and press .
3. Press  to proceed while the pop-up message is displayed.
– or –
Press any key to erase the pop-up message, press **Options** (right softkey), highlight **Roam Call**, or **Roam:Speaker On**, and press .

To answer incoming roaming calls with Call Guard on:

- ▶ Press **Options** (right softkey), highlight **Answer** or **Answer:Speaker**, and press .
- or –
- 1. Press  or .
- 2. Press  to proceed while the pop-up message is displayed.

Reminder: If the Call Guard feature is set to **On**, you need to take extra steps to make and receive roaming calls, even if you have selected the **Analog** setting (see page 79).

Navigating Through Menus

In This Section

- ◆ **Menu Navigation**
 - ◆ **Menu Structure**
 - ◆ **Viewing the Menus**
-

Every function and feature of your Sanyo SCP-7400 can be accessed through an onscreen menu. This section is a road map to using your wireless phone. Please take a few moments to learn your way around and you'll find your phone easier to use.


Menu Navigation

The navigation key on your wireless phone allows you to scroll through menus quickly and easily. The scroll bar at the right of the menu keeps track of your position in the menu at all times.





To navigate through a menu, simply press the navigation key up or down.

Menu Structure

Selecting Menu Items

As you navigate through the menu, menu options are highlighted. Select any numbered option by simply pressing the corresponding number on the phone's keypad. You may also select any item by highlighting it and pressing .

For example, if you want to view your last incoming call:

1. Press  to access the main menu.
2. Select **Call History** by pressing . (It may already be highlighted.)
3. Select **Incoming** by pressing  or by highlighting it and pressing . (If you have received any calls, they are displayed on the screen.)

Backing Up Within a Menu

To go to the previous menu:

- ▶ Press .

To return to standby mode:

- ▶ Press .

Shortcuts

Use your navigation key to quickly access your phone's menus.

- **Right** to take a shortcut to the **Contacts** menu.
- **Left** to take a shortcut to the **My Shortcut** menu. (See page 56 for setting.)
- **Up** to take a shortcut to the **Messaging** menu.
- **Down** to take a shortcut to the **Downloads** menu.

Viewing the Menus

Menu Diagram

The following list outlines your phone's menu structure.

1. Call History

1. Outgoing
2. Incoming
3. Missed
4. Erase History

2. Contacts

1. Find/Add Entry
2. Speed Dial #s
3. My Phone#
4. Services

3. Messaging

1. Send Message
2. PictureMail
3. Text Msgs
4. Instant Msg.
5. Voicemail

4. Web

5. Picture&Video

1. Camera
2. Camcorder
3. My Pictures
4. My Videos
5. Online Albums
6. Account Info
7. Wap Link 1-3 (if applicable)

6. Downloads

1. Games
2. Ringers
3. Screen Savers
4. Applications
5. Dynamic 1-10 (If applicable)
6. Others (If applicable)

7. Media Player

8. Settings

1. Sounds
 1. Ringer/Key Vol.
 2. Ringer Type
 3. Alerts
 4. Receiver Vol.
 5. Application Vol.
 6. Others
2. Display
 1. Backlight
 2. Greeting
 3. Font Size
 4. Background
 5. Animation
 6. Incoming Calls
 7. Match Area Code
 8. Standby Display
 9. Main Menu
 10. My Buddy
 11. Return to Idle
 12. Sleep Mode
3. PCS Vision
 1. Enable (or Disable) Vision
 2. Net Guard
 3. Update Profile
4. Ready Link
 1. Enable/Disable
 2. List Update
 3. Sounds
 4. Speakerphone
 5. Default View
 6. Floor Display
 7. R-Link Guard
 8. Restart
 9. Help
5. Location
6. Roaming
 1. Set Mode
 2. Call Guard
7. Messaging
 1. Notification
 2. Preset Msgs
 3. Send Callback#
 4. Signature

- 8. Security
 - 1. Lock Phone
 - 2. Lock Pic&Video
 - 3. Erase Ph. Book
 - 4. Erase VoiceTag
 - 5. Erase Download
 - 6. Reset Pictures
 - 7. Reset Phone
 - 8. Others
- 9. Others
 - 1. Any Key Answer
 - 2. Auto Answer
 - 3. Open/Close Flip
 - 4. Abbrev. Dial
 - 5. Headset Mode
 - 6. TTY
 - 7. Side Key Guard
 - 8. Meeting Mode
 - 9. Airplane Mode
 - 10. Language
- 0. Phone Info
 - 1. Phone#/User ID
 - 2. Help
 - 3. Version
 - 4. Advanced

9. Tools/Extras

- 1. Voice Services
 - 1. Voice Memo
 - 2. Screen Call
- 2. Calendar
- 3. Alarm Clock
- 4. Calculator
- 5. World Clock
- 6. PC Sync
 - 1. Ringers
 - 2. Images
 - 3. Erase Data

Managing Call History

In This Section

- ◆ Viewing History
 - ◆ Call History Options
 - ◆ Making a Call From Call History
 - ◆ Saving a Phone Number From Call History
 - ◆ Prepending a Phone Number From Call History
 - ◆ Erasing Call History
-




The Call History keeps track of incoming calls, calls made from your wireless phone, and missed calls. This section guides you through accessing and making the most of your Call History.

Viewing History

You'll find the Call History feature very helpful. They are lists of the last 20 voice calls and the last 10 Ready Link calls that you placed, accepted, or missed. Call History makes redialing a number fast and easy. It is continually updated as new numbers are added to the beginning of the list and the oldest entries are removed from the bottom of the list.

Each entry contains the phone number (if it is available) and contact's name (if the phone number is in your Contacts List). Duplicate calls (same number and type of call) may only appear once on the list.

To view a Call History entry:

1. Press  to access the main menu.
2. Select **Call History** and press .
3. Select **Outgoing**, **Incoming**, or **Missed** and press . (The selected Call History list will display.)

Tip: You can switch the voice call history to the Ready Link call history by pressing **R-Link** (left softkey). To return to the voice call history, press **Voice Call** (left softkey). This option is not available when Ready Link mode is set to **Disable** (see page 138), or Ready Link is locked (see page 70).







Call History Options

For additional information and options on a particular call, highlight a Call History entry and press **Options** (right softkey).

- **Call** to dial the phone number.
- **Call:Speaker On** to dial the phone number in speakerphone mode.
- **Send Message** to send a text message, picture, or video.
(See page 227 or 183 for details.)
- **Save Phone#** to save the phone number (if applicable).
 - **Go to Phone Book** appears when the number is already in your Contacts list. (See “Saving a Phone Number From Call History” on page 89.)
- **Prepend** to add numbers to the beginning of the phone number.
(See “Prepending a Phone Number From Call History” on page 90.)
- **Copy to Personal** to copy the phone number to the Ready Link Personal List. (Only appears when Ready Link mode is set to Enable and the number does not match any stored entry in your Personal List.)
- **Erase** to erase the entry.

Making a Call From Call History

To place a call from Call History:




1. Press  to access the main menu.
 2. Select **Call History** and press .
 3. Select **Outgoing**, **Incoming** or **Missed** and press .
 4. Scroll to the entry you want to call.
 5. Press  or .
- or –
- Press **Options** (right softkey), highlight **Call** or **Call:Speaker On**, and press .

Note: You cannot make calls from Call History to entries identified as **No ID** or **Restricted**.

Saving a Phone Number From Call History

Your phone can store up to 500 phone numbers in up to 300 Contacts entries (an entry may contain up to seven numbers). Each entry's name can contain sixteen characters.

To save a phone number from Call History:




1. Scroll to the call history entry you want to save.
2. Press **Options** (right softkey) to display the options.
3. Highlight **Save Phone#** and press .
4. Select the appropriate label (Mobile, Home, Work, Pager, Fax, Other, or No Label) and press .
5. Enter a name and press . If you have already stored entries in the Contacts list, you are prompted to select the following entry mode:
 - **New Name** to enter a name directly.
 - **From Ph. Book** to select a name from the Contacts list.
6. Press **Save** (left softkey).

Note: You cannot save phone numbers already in your Contacts list or from calls identified as **No ID** or **Restricted**. If the selected entry has already been stored in the Contacts list, **Go to Phone Book** appears during step 3 above.



Prepending a Phone Number From Call History

If you need to place a call from Call History and you happen to be outside your local area code, you can add the appropriate prefix by prepending the number.

To prepend a phone number from Call History:

1. Scroll to a call history entry and press **Options** (right softkey).
2. Highlight **Prepend** and press .
3. Enter the digits you want to add to the number.
4. Press  or  to place a call.







To select another option, press **Options** (right softkey), highlight it and press .

- **Call** to dial the phone number.
- **Call:Speaker On** to dial the phone number in speakerphone mode.
- **Save Phone#** to store the phone number in your Contacts directory.
-  **Hard Pause** to insert a hard pause.
-  **2-Sec. Pause** to insert a 2-second pause.

Erasing Call History

To erase individual Call History entries, see “Call History Options” on page 88.

To erase Call History:

1. Press  to access the main menu.
2. Select **Call History** and press .
3. Select **Erase History** and press .
4. Select **Outgoing**, **Incoming**, **Missed**, or **All** and press .
5. Select **Voice Calls** or **Ready Link** and press 
 - **Voice Calls** to erase call history for voice calls.
 - **Ready Link** to erase call history for Ready Link calls.
6. Select **Yes** and press .

Using the Contacts Directory




In This Section

- ◆ **Displaying the Contacts List**
 - ◆ **Adding a New Contacts Entry**
 - ◆ **Finding Contacts List Entries**
 - ◆ **Contacts List Entry Options**
 - ◆ **Adding a Phone Number to a Contacts Entry**
 - ◆ **Editing a Contacts Entry's Phone Number**
 - ◆ **Erasing a Contacts Entry From the List**
 - ◆ **Assigning Speed Dial Numbers**
 - ◆ **Editing a Contacts Entry**
 - ◆ **Selecting a Ringer and Image Type for an Entry**
 - ◆ **Secret Contacts Entries**
-

Now that you know the basics that make it easier to stay in touch with people and information, you're ready to explore your phone's more advanced features. This section explains how to use your phone's Contacts Directory and helps you make the most of your contacts and time when you are trying to connect with the important people in your life.

Displaying the Contacts List









To display your contacts list:

- ▶ Press the navigation key right.
 - or -
- 1. Press  to access the main menu.
- 2. Select **Contacts** and press .
- 3. Select **Find/Add Entry** and press .

Adding a New Contacts Entry

Your phone can store up to 500 phone numbers in up to 300 Contacts entries (an entry may contain up to seven numbers). Each entry's name can contain sixteen characters.

To add a new entry:

1. Press  to access the main menu.
2. Select **Contacts** and press .
3. Select **Find/Add Entry** and press 
 - Press the navigation key right for the shortcut (steps 1 to 3).
4. Highlight **<Add Contact>** and press .
5. Enter a name and press .
6. Select a label by using your navigation key and press .
7. Enter the phone number or address and press .
8. Press **Save** (left softkey).
 - or -
1. Press the navigation key right to display the Contacts list.
2. Highlight an entry and press **Options** (right softkey).
3. Highlight **Add Contact** and press .
4. Follow steps 5-8 above.


Tip: You can also add a new Contacts entry by entering a number from standby mode. See "Saving a Phone Number" on page 28.

Finding Contacts List Entries


There are several ways to display your Contacts entries: by name, by speed dial number, by group, and by voice tags. Follow the steps outlined in the sections below to display entries from the Contacts list menu.

Finding Names

To find Contacts list entries by name:

1. Press the navigation key right to display the Contacts list.
2. Scroll to the desired entry in the Contacts list.
– or –
Enter the first letter of the name or part of the name. (The display shows the entries beginning with the letter entered.)
3. Press  to display the entry's details.




To find Ready Link List entries:

1. Press the navigation key right to display your Contacts list.
2. Press **Go to** (left softkey). Highlight your desired list and press .
 - **Phone Book** to display the Contacts list.
 - **Personal List** to display the Personal List.
 - **Personal Grps.** to display the Personal Group List.
3. Scroll through the list to select your desired entry.

Note: The **Go to** (left softkey) option does not appear when Ready Link mode is set to **Disable** (see page 138), or Ready Link is locked (see page 70).



Finding Speed Dial Numbers

To find phone numbers you have stored in speed dial locations:

1. Press  to access the main menu.
2. Select **Contacts** and press .
3. Select **Speed Dial #s** and press . (The Speed Dial numbers list appears.)

Finding Voice Tags

To find Voice Tags in your phone:

1. Press and hold  or .
2. You'll hear a tone followed by the prompt. Say "Edit Voice Tag."
3. After the prompt, say "Review List." (The list of Voice tags appears.)





Contacts List Entry Options

To access a contact's options, display the Contacts list, highlight an entry and press . Then select a phone number and press **Options** (right softkey). To select an option, highlight it and press .

- **Edit** to edit the selected entry.
- **Call** to dial the selected number.
- **Call:Speaker On** to dial the phone number in speakerphone mode.
- **Send Message** to send a text message, picture, or video (mobile numbers only). (See page 227 and 183 for details.)
- **Call Alarm** to set a call alarm for the entry. (See page 104 for Call Alarm.)
- **Set Speed Dial** to assign speed dial numbers to your favorite entries. (See "Assigning Speed Dial Numbers" on page 96.)
- **Prepend** to alter a phone number by adding numbers to the beginning of the entry. (See "Prepending a Phone Number From Call History" on page 90.)
- **Copy to Personal** to copy the phone number to your Ready Link Personal List. (Only appears when Ready Link mode is set to Enable and the number does not match any stored entry in your Personal List.)





Adding a Phone Number to a Contacts Entry

To add a phone number to an entry:

1. Press the navigation key right to display the Contacts list.
2. Scroll to the entry you wish to add and press .
3. Select a phone number, press **Options** (right softkey), highlight **Edit**, and press .
4. Select the label field you want to add and press .
5. Enter the number and press .
6. Press **Save** (left softkey).



Editing a Contacts Entry's Phone Number

To edit an entry's phone number:

1. Press the navigation key right.
2. Scroll to the entry you wish to edit and press .
3. Select a phone number, press **Options** (right softkey), highlight **Edit**, and press .
4. Select the number you want to edit and press .
5. Edit the entry by using your keypad and press .
6. Press **Save** (left softkey) to save your changes.

Erasing a Contacts Entry From the List










To erase the selected entry:


1. Press the navigation key right.
2. Scroll to the entry you wish to delete by using the navigation key and press **Options** (right softkey).
3. Highlight **Erase Contact** and press .
4. Select **Yes** and press .

Assigning Speed Dial Numbers






With this feature you can dial Contacts Directory entries with one key press for locations 2-9. Save your memory locations 2-9 for speed dialing your most commonly used phone numbers. Speed Dial numbers must be stored in your Contacts Directory to use this feature.

To assign Speed Dial:

1. Press  to access the main menu.
2. Select **Contacts** and press .
3. Select **Speed Dial #s** and press .
4. To select a corresponding speed dial number from 2-9, highlight an unassigned number and press .
5. Select an entry from the list and press .
6. Select the phone number you want to set as a speed dial and press .
- or -
1. Press the navigation key right.
2. Scroll to your desired entry in the Contacts list and press .
3. Select the phone number you want to set as a speed dial and press **Options** (right softkey).
4. Highlight **Set Speed Dial** and press .
5. Select an unassigned number and press .

Tip: When you highlight an assigned number and press , you'll be asked whether you want to overwrite the assigned number. Select **Yes** to overwrite or **No** to cancel.

To cancel a stored speed dial number:





1. Press  to access the main menu.
2. Select **Contacts** and press .
3. Select **Speed Dial #s** and press .
4. Select the stored speed dial number you want to cancel and press .
5. Select **Unassign** and press .

To use Speed Dial:

- From standby mode, just press and hold the appropriate key.

Editing a Contacts Entry





To make changes to an entry:

1. Press the navigation key right.
2. Scroll to the entry you wish to edit and press .
3. Select a phone number, press **Options** (right softkey), highlight **Edit**, and press .
– or –
Select an email address or Web address and press **Edit** (right softkey).
4. Select the field you want to edit and press .
5. Edit the entry by using your keypad and press .
6. Press **Save** (left softkey) to save your changes.



Selecting a Ringer and Image Type for an Entry


You can assign a ringer or an image type to a Contacts entry so you can identify the caller by the ringer or image type. (See “Ringer Types” on page 38.)

To select a ringer type for an entry:

1. Press the navigation key right.
2. Select the entry for which you want to set the incoming ringer and press .
3. Select a phone number, press **Options** (right softkey), highlight **Edit**, and press .
– or –
Select an email address or Web address and press **Edit** (right softkey).
4. Scroll to **Ringer** and press .
5. Scroll to your desired ringer and press . (When you highlight a ringer type, a sample ringer will sound.)
6. Press **Save** (left softkey) to save the ringer type.
 - To confirm the ringer, highlight **Ringer** and press **Play** (right softkey).

To select an image type for an entry:



1. Follow steps 1-3 above.
2. Scroll to **Picture ID** and press .
3. Scroll to your desired image and press .
4. Press **Save** (left softkey) to save the image type.
 - To see a display preview of an image, press **Preview** (right softkey) during step 4 above. Press the right softkey to switch between Main/Sub LCD's display preview.

Note: If you set an animation ringer (indicated with the  icon) and an image, your phone plays the ringer (audio) of the animation ringer and displays the image you selected.



Secret Contacts Entries

You can hide an entry's phone number(s) and require your lock code to edit the entry by making it secret. The entry name is still displayed, but the entry's phone numbers are replaced with "<Secret>".

To make an entry secret:

1. Press the navigation key right.
2. Scroll to the Contacts entry you want to tag as secret.
3. Press **Options** (right softkey) to display the menu options.
4. Highlight **Set Secret** and press .
5. Enter the 4-digit lock code.
6. Select **On** and press .

To make an entry public:

1. Press the navigation key right.
2. Scroll to the Contacts entry you want to tag as public.
3. Press **Options** (right softkey) to display the menu options.
4. Highlight **Set Secret** and press .
5. Enter the 4-digit lock code.
6. Select **Off** and press .

Tip: If you can't recall your lock code, try using the last four digits of either your Social Security number or phone number or try 0000. If none of these work, call Qwest Wireless™ Repair at 1-877-879-0611.

Personal Organizer

In This Section

- ◆ **Managing the Scheduler**
 - ◆ **Using Your Phone's Scheduler**
 - ◆ **Using the Call Alarm Feature**
 - ◆ **Using the To Do List**
 - ◆ **Purging All Events, Call Alarms, or To Do List Items**
 - ◆ **Personal Information Management**
 - ◆ **Using Your Phone's Tools**
 - ◆ **Downloading Files**
-




Your Sanyo SCP-7400 Phone is equipped with several personal information management features that help you manage your busy lifestyle. This section shows you how to use these features to turn your phone into a time management planner that helps you keep up with your contacts, schedules, and commitments. It takes productivity to a whole new level.

Managing the Scheduler

Use the Calendar to remind you of events or important calls you need to make. You can schedule up to 100 events, 15 Call Alarms, and 20 To-Do List items.

Displaying Your Calendar

To display your calendar:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Calendar** and press .



Note: In a no-service area or an analog service area, it's necessary to set the actual time and date to use the Calendar function after removing and installing your battery. Set the current Time/Date by using numeric keys and/or the navigation key (Right/Left: move cursor, Up/Down: change value). You can set any time from 12:00 AM, Jan 1, 2000 to 11:59 PM, Dec 31, 2099.

Setting Holidays

You can set your personal holidays by displaying the date in red on the Calendar display. The default holidays displayed in red are Sundays and national holidays.

Note: You can set holidays from Jan 1, 2000 to Dec 31, 2020.

To set personal holidays:

1. From the Calendar display, highlight the day you want to set to the holiday by using the navigation key.
2. Press **Options** (right softkey), highlight **Holiday**, and press .
3. Highlight **Set Date** or **Set Weekly** from the options and press 
 - **Set Date** sets the selected date for the holiday.
 - **Set Weekly** sets weekly holidays.
 - **Reset Date** resets the holiday setting for the selected date.
 - **Reset Weekly** resets the weekly holiday setting.
 - **Reset All** resets all the holiday settings and returns to the default settings.

Tip: If you selected **Set Weekly**, **Reset Weekly**, or **Reset All**, you'll be prompted to select **Yes** or **No**.




Tip: The current day is framed by a rectangle.

Using Your Phone's Scheduler


Adding an Event to the Scheduler

Your Scheduler helps organize your time and reminds you of important events (up to 100 events).

To add an event:

1. From the Calendar display (see page 101), select the day you want to add an event and press **Options** (right softkey).
2. Highlight **Add Event** and press .
3. Select **Schedule** and press .
4. Enter the description using your keypad and press  (or press **Mode** [right softkey] to select a description from "From To Do List").

Note: The "From To Do List" option will not appear if there are no items stored in the To Do List. See "Adding To Do List Items" on page 107 for details.

5. Select the following items and press .
 - **Description** to enter a description of your event (up to 14 characters).
 - **From** to schedule the start time.
 - **To** to schedule the end time.
 - **Location** to edit the location of your event (up to 14 characters).
 - **Alarm** to select your desired ringer.
 - **Alarm Time** to edit the alarm time (number of hours or minutes before the event starts). Default alarm time is 10 minutes before.
 - **Repeat** to set the event's repeating status. Select **None**, **Daily**, **Weekly**, **Monthly**, or **Yearly**.
6. Press **Save** (left softkey) to schedule the event.

Tip: The date you have scheduled events for is indicated by "►".

Tip: Press the navigation key up or down to scroll by week through the Scheduler calendar and the Side Volume key to scroll by month.

Event Alerts


There are several ways your phone alerts you of scheduled events:



- By playing the alert tone (depending on the Ringer Type and Ringer Volume setting).
- By blinking the LED.
- By displaying the event's description on the Main LCD when the flip is open.
- By displaying the event's description on the Sub LCD when the flip is closed.
- By lighting the LCD backlight (depending on the backlight setting).

Event Alert Menu

When you have an event alarm scheduled, your phone alerts you and displays the  icon, and the event summary.

To respond to an event alert:

- ▶ Press  to see the event details.
– or –
- ▶ Press **Snooze** (left softkey) to repeat the alarm in ten minutes.
– or –
- ▶ Press **Dismiss** (right softkey) to dismiss the event and back to standby mode.




Note: If you press  before checking your event, **Events** (right softkey) appears in standby mode. Press **Events** (right softkey) to display the event and press  to see the event details.

Using the Call Alarm Feature

Adding a Call Alarm to the Scheduler

You can set call alarms to notify you when you need to place a call. The call alarm will let you know when and to whom to place a scheduled call. You can set up to 15 call alarms.

To add a call alarm to the Scheduler:

1. From the Calendar display (see page 101), select the day you want to add an event and press **Options** (right softkey).
2. Select **Add Event** and press .
3. Select **Call Alarm** and press .
4. Enter the phone number directly or press **Options** (right softkey) for options.
 - **From Phone Book** to select the desired number from your Contacts list.
 - **Voicemail** to select the number for voicemail access.
5. Select the following items and press 
 - **Time/Date** to edit the start time and date.
 - **Alarm** to select the ringer alarm.
 - **Repeat** to set the Call Alarm's repeat status. Select **None**, **Daily**, **Weekly**, **Monthly**, or **Yearly**.
6. Press **Save** (left softkey).


Tip: You can also add a call alarm from the Contacts menu (see "Contacts List Entry Options" on page 94).

Call Alarm Alerts


There are several ways your phone alerts you of a scheduled call alarm:



- By playing the alert tone (depending on the Ringer Type and Ringer Volume setting).
- By blinking the LED.
- By displaying the call alarm notification on the Main LCD when the flip is open.
- By displaying the call alarm notification on the Sub LCD when the flip is closed.
- By lighting the LCD backlight (depending on the backlight setting).

Call Alarm Menu

When you have scheduled a call alarm, your phone alerts you and displays the  icon, the name, or phone number you wish to call.





To respond to a call alarm:

- ▶ Press **TALK** or **SPEAKER** to dial the phone number.
– or –
- ▶ Press **--** to make a Ready Link call (if applicable).
– or –
- ▶ Press  to see the event details.
– or –
- ▶ Press **Snooze** (left softkey) to repeat the alarm.
– or –
- ▶ Press **Dismiss** (right softkey) to dismiss the call alarm and back to standby mode.

Note: If you press  before checking your event, **Events** (right softkey) appears in standby mode. Press **Events** (right softkey) to display the event and press  to see the call alarm details.




Editing an Event or Call Alarm

To edit an event or call alarm:

1. From the Calendar display (see page 101), select the date for which you set events and press .
2. Select one of the events or call alarms and press . (The event or call alarm details appear.)
3. Select the box you want to edit and press .
4. Enter or select a new setting and press .
5. Press **Save** (left softkey).




Viewing a Future or Past Day's Scheduled Events

To view a future or past day's scheduled events:

1. From the Calendar display (see page 101), press **Options** (right softkey).
2. Highlight **Go To Date** and press .
3. Enter the date by using numeric keys and the navigation key and press  or **OK** (left softkey).
4. Press  once again to view the day's event list.

Erasing a Day's Events or Call Alarms

To erase a scheduled day's events or call alarms:







1. From the Calendar display (see page 101), select the date for which you set events and press .
2. Select one of the events or call alarms and press **Options** (right softkey).
3. Highlight **Erase Event** and press .
4. Select **Yes** and press .

Using the To Do List

Adding To Do List Items


Your phone can store and manage up to 20 To Do List items.

To add an item to your To Do List:

1. From the Calendar display (see page 101), press **Options** (right softkey).
2. Highlight **To Do List** and press .
3. Press **Options** (right softkey).
4. Highlight **Add Item** and press .
5. Enter the description (up to 14 characters) and press .
6. Select **Priority** and press  to edit the To Do's priority. You can select from **Normal**,  **Urgent**, or  **Done**.
7. Press **Save** (left softkey).




Viewing the To Do List

To view your To Do List:

1. From the Calendar display (see page 101), press **Options** (right softkey).
2. Highlight **To Do List** and press 
 - To see the details of each To Do List item, select an item and press .



Editing To Do List Items

To edit a To Do List item:

1. From the To Do List display, highlight the item you want to edit and press .
2. Select the box you want to edit and press .
3. Edit the description or change the priority and press .
4. Press **Save** (left softkey).





Adding a To Do List Item to the Scheduler

To add your To Do List item to the scheduler:

1. From the To Do List display (see page 107), select the item you want to add to the schedule and press **Options** (right softkey).
2. Highlight **Add To Schedule** and press .
 - **Add To Schedule** to extract the item from the To Do List and make it a scheduled event.
3. Enter the description using your keypad and press . (See “Adding an Event to the Scheduler” on page 102 for entering.)
4. Press **Save** (left softkey).



Deleting Items From the To Do List

To delete To Do List items:



1. From the To Do List display (see page 107), highlight the item you want to erase and press **Options** (right softkey).
2. Highlight your desired option and press .
 - **Erase Item** erases an item from the To Do List.
 - **Erase Selection** erases multiple selected To Do List items at one time. Press  to check the box(es) next to the To Do List item(s) you want to delete and press **Erase** (left softkey) to erase. To check all boxes, press **Options** (right softkey), highlight **Check All**, and press .
 - **Erase All** erases all To Do List items.
3. Select **Yes** and press .

Viewing Memory in Your Scheduler

To view available memory space and options:




1. From the Calendar display (see page 101), press **Options** (right softkey).
2. Highlight **View Memory** and press .
3. Select **Schedule**, **Call Alarm**, or **To Do List** and press . (The available memory space and options display.)

For further options:

4. Press **Options** (right softkey).
5. Highlight an option and press 
 - **Erase Old** deletes old events or call alarms.
 - **Erase Selection** deletes the To Do List items you selected. (See “Deleting Items From the To Do List ” on page 108.)
 - **Erase Done** deletes the To Do List items that have been completed.
 - **Erase All** deletes all events, call alarms, or To Do List items.
6. Select **Yes** or **No** and press .

Purging All Events, Call Alarms, or To Do List Items





To delete all scheduled events, call alarms, or To Do List items:

1. From the Calendar display (see page 101), press **Options** (right softkey).
2. Highlight **Erase Memory** and press .
3. Select one item from the options and press 
 - **Erase Old** deletes old events, call alarms, and To Do List items that are done.
 - **Erase All** deletes all events, call alarms, and To Do List items.
4. Select **Yes** and press .

Personal Information Management







Displaying Your User Address

To display the phone's current user address:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Phone Info** and press .
4. Select **Phone#/User ID** and press .
 - If you sign out, <PCS Vision Disabled> appears on the display.





Finding Icon Definitions

To view an explanation of icons that appear on the display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Phone Info** and press .
4. Select **Help** and press .
5. Select the item for which you want to see the explanation and press . (The icon's explanation appears.)
6. Press **Done** (left softkey) or  to end.





Displaying the Version Information

To display the version number of the software, hardware, PRL (Preferred Roaming List), PRI (Product Release Instructions), etc., installed on your phone:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Phone Info** and press .
4. Select **Version** and press .

Displaying Advanced Information

To display advanced information such as technology and frequency:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Phone Info** and press .
4. Select **Advanced** and press .









Using Your Phone's Tools

In addition to helping you be more efficient and organized, your phone offers useful and entertaining tools.

Using the Alarm Clock

Your phone comes with a built-in alarm clock with alarm capabilities. You can set up to 5 alarms. This feature is also available while your phone is turned off.

To use the alarm clock:


1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Alarm Clock** and press .
4. Select an unassigned number and press .
5. Select the following items and press .
 - **Alarm** to set the alarm On/Off. Select **On** and press .
 - **Time** to enter the alarm time. Enter the desired alarm time and press .
 - **Repeat** to select the alarm frequency. Select **Once**, **Daily**, **Weekday**, or your desired day of the week and press .
 - **Description** to enter a description of the alarm.
6. Press **Save** (left softkey) to save the alarm settings.

Note: In a no-service area or an analog service area, it's necessary to set the actual time and date to use the Alarm Clock function after removing and installing your battery.

To stop the alarm:







- ▶ Press any key to stop the alarm.

To respond the alarm:

- ▶ Press  to see the alarm details.
- or -
- ▶ Press **Snooze** (left softkey) to repeat the alarm.
- or -
- ▶ Press **Dismiss** (right softkey) to dismiss the alarm.

Note: If you press  before checking your event, **Events** (right softkey) appears in standby mode. Press **Events** (right softkey) to display the alarm.

To set the alarm clock settings:






1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Alarm Clock** and press .
4. Press **Settings** (right softkey) and press .
5. Select **Ringer Length** or **Snooze Interval** and press 
 - **Ringer Length** to set the ringer length of alarm clock.
 - **Snooze Interval** to set the interval time for snooze.
6. Set the time by using numeric keys or by pressing the navigation key up or down and press .

Note: You can adjust the ringer type and ringer volume in your Settings menu. To change the ringer type, see “Selecting Ringer Types for Voicemail, Messages, or Calendar/Alarm” on page 39. To change the ringer volume, see “Adjusting the Phone’s Volume Settings” on page 41.

Using the Calculator

Your phone comes with a built-in calculator.




To use the calculator:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Calculator** and press .
4. Enter numbers using your keypad. (Press the left softkey to insert a decimal point.)
5. Press the appropriate navigation key for an arithmetic option (**Up** for addition, **Down** for subtraction, **Left** for multiplication, **Right** for division).
6. Enter numbers and press  for the result.
 - To clear the numbers, press **CLR** (right softkey).
 - To exit the calculator, press .

Using the World Clock

This feature is available only in digital service areas.

To set the world clock display:






1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **World Clock** and press .
4. The world clock display appears.
 - Press the navigation key right or left to change countries.

Tip: Press **Summer** (left softkey) or **Standard** (right softkey) to select between daylight savings and standard time (if applicable). The  icon is shown in summer mode.





Downloading Files

Your phone allows you to download images (screen savers), ringers, games, etc., from a Sprint PCS Vision connection. It is also possible to download from certain menus (Contacts list, Ringer Setting, or Display Setting).








To download a file from the Downloads menu:

1. Press  to access the main menu.
2. Select **Downloads** and press .
 - Press the navigation key down for the shortcut (steps 1 and 2).
3. Press **Options** (right softkey) to display options.
4. Select **Get New** and press . (The browser will launch and display the Downloads main screen.)
5. Select your desired file and follow the system prompts.
– or –
1. Follow steps 1-2 above.
2. Select your desired data folder (for example, Games, Ringers, or Screen Savers) and press .
3. Select **Get New** and press . (The browser will launch and display the category's main screen.)
4. Select your desired file and follow the system prompts.




To download a file from a Contacts list entry:

1. Press the navigation key right.
2. Scroll to the entry for which you want to set the downloaded ringer or image and press .
3. Select a phone number and press **Options** (right softkey), highlight **Edit**, and press .
4. Scroll to **Ringer** or **Picture ID** and press .
5. Scroll to **Get New** and press . (The browser launches and displays the Download page.)
6. Select your desired image or ringer file and follow the system prompts.







To download a ringer file from the Ringer Setting menu:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Sounds** and press .
4. Select **Ringer Type** and press .
5. Select one item from **Voice Calls**, **Voicemail**, **Messaging**, or **Calendar/Alarm**, and press .
 - For **Voice Calls**, select **With Caller ID** or **No Caller ID**.
6. Press , scroll to **Get New**, and press . (The browser launches and displays the Download page.)
7. Select your desired ringer file and follow the system prompts.






To download a ringer file from the Start-up/Power-off Tone menu:

1. Select **Others** during step 4 on the previous page and press .
2. Select **Start-up Tone** or **Power-off Tone** and press .
3. Scroll to **Get New** and press . (The browser launches and displays the Download page.)
4. Select your desired ringer file and follow the system prompts.

To download an image file from the Display Setting menu (Animation and Incoming Calls):

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Display** and press .
4. Select **Animation** or **Incoming Calls** and press .
 - For **Animation**, select **Standby**, **Outgoing Calls**, or **Service Search**.
5. Press , scroll to **Get New**, and press . (The browser launches and displays the Download page.)
6. Select your desired image file and follow the system prompts.





To download an image file from the Screen Saver menu:

1. Select **Standby Display** during step 4 above and press .
2. Select **Main LCD** or **Sub LCD** and press .
3. Select **Screen Saver** and press .
4. Press , scroll to **Get New**, and press . (The browser launches and displays the Download page.)
5. Select your desired image file and follow the system prompts.

Confirming the Downloaded Data

The downloaded data will automatically be classified as games, ringers, images (screen savers), videos, or applications. However, if any data has a different category, it will be classified as dynamic (the folder name is variable). If data doesn't belong to any of the above, it will be classified as others.




To confirm the downloaded data:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select your desired data folder (for example, **Games**, **Ringers**, or **Screen Savers**) and press .
4. Select the downloaded data you want to confirm and press .

Tip: The names of dynamic folders are variable depending on data.
















You can manage your contents in the browser.

To confirm your Content Manager:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Press **Options** (right softkey), select **My Content Manager**, and press  to launch the browser.

Tip: You can also access your Content Manager from any folder in the Downloads menu. After selecting a folder, select **My Content Manager** and press  to launch the browser.

Icon Indication







Type	Item	Icon (appears at the left side of the downloaded data)
From Web	Ringers (~2048KB)	 (New Data)  (Assigned Data)
	Voice (~2048KB)	 (New Data)  (Assigned Data)
	Screen Savers/Images (~128KB)	 (New Data)  (Assigned Data)
	Animation (~2048KB)	 (New Data)  (Assigned Data)
	Animation Ringers (~2048KB)	 (New Data)  (Assigned Data)
	Videos (~2048KB)	 (New Data)  (Assigned Data)
	Games (~2048KB)	 (New Data)
	Applications (~2048KB)	 (New Data)
	Unknown types (~2048KB)	 (New Data)
		Note: Download icon subject to change

Downloaded Data Options

Selecting Download Settings






This feature is available when you select a Java application.

To select the settings for the downloaded data:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select **Games** or **Applications** and press .
4. Select the data for which you want to select settings and press **Options** (right softkey).
5. Highlight **Settings** and press .
6. Select **Network Access** or **Push Registry** and press .
 - **Network Access** to select the Network Access availability.
 - **Push Registry** to select the availability to communicate with other mobile phones such as chat or match-up games (if applicable).
7. Select **Always Allow**, **Ask**, or **Never Allow**, and press .

Assigning the Downloaded Data






To assign the downloaded data:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select **Ringers** or **Screen Savers** and press .
4. Select the data you want to assign and press **Options** (right softkey).
5. Highlight **Set as** and press .
6. Highlight the menu you want to assign and press .

Sorting the Downloaded Data

The files downloaded via the Web are stored in alphabetical order. You may also store the data in memory size order.





To sort downloaded files:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select a folder and press .
4. Press **Options** (right softkey).
5. Highlight **Sorting** from the options and press .
6. Highlight **Name** or **Size** and press .

Viewing the Downloaded Data Size

This feature allows you to confirm each downloaded file's size and the remaining download capacity.




To view the data size:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select a folder and press .
4. Press **Options** (right softkey).
5. Highlight **Icon/Size** and press . (Data size is displayed at the left of the downloaded data name.)

Viewing the Memory Space






This feature allows you to confirm how much memory is left and may be used for downloading files.

To view the available memory space:



1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Press **Options** (right softkey).
4. Highlight **View Memory** and press . (**Used** and **Free** memory size are displayed.)

Erasing the Downloaded Data

To erase the selected downloaded data:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select a folder and press .
4. Select the downloaded data you want to erase and press **Options** (right softkey).
5. Highlight **Erase** and press .
6. Press **Continue** (left softkey) to continue.
7. Highlight **Yes** and press  to erase the data.

To erase all downloaded data in a folder:

1. Follow steps 1-4 above.
2. Highlight **Erase All** and press .
3. Highlight **Yes** and press  to erase all data in the folder you select.

Note: It takes a while when you erase lots of downloaded data. Some data will remain if you answer an incoming call during erasing process.

Using Your Phone's Voice Services

In This Section

- ◆ **Using Automatic Speech Recognition**
 - ◆ **Managing Voice Memos**
 - ◆ **Setting Up Screen Call**
-

Your wireless phone's Voice Services let you place calls using your voice, store voice reminders, and record memos right on your phone.


This section includes easy-to-follow instructions on using voice-activated dialing and managing voice memos.

Using Automatic Speech Recognition

Your Sanyo SCP-7400 Phone is equipped with an Automatic Speech Recognition (ASR) feature. This feature allows you to make calls or use the phone's functions by simply using your voice. All you have to do is to talk into the phone, and the phone will recognize your voice and complete tasks by itself. You can activate Automatic Speech Recognition whether the phone is open or closed.

Activating Automatic Speech Recognition


To activate Automatic Speech Recognition:

- ▶ From standby mode, press and hold **TALK** or **SPEAKER**.
– or –
- ▶ From standby mode, press .

The phone displays the Command menu and prompts you to say the name of the command you want to use. To complete your task, simply follow the voice prompts. You can speak the name of the command when your phone displays the .

The following is a list of available ASR commands:

- **Contact** to call an entry in your Contacts list. (See page 124 for details.)
- **Dial Number** to dial a phone number by speaking the number. (See page 125 for details.)
- **Call Voice Tag** to find the name or phone number stored in the Voice Tag List. (See page 126 for details.)
- **Find Contact** to find an entry stored in your Contacts list. (See page 125 for details.)
- **Digit Training** to adapt the system to your voice. (See page 129 for details.)
- **Phone Status** to notify you of your phone number, the current signal strength, and the battery level.
- **Edit Voice Tag** to add, review, or erase a Voice Tag entry. (See page 126 for details.)
- **Help** to get instructions for Automatic Speech Recognition of voice call.
- **Ready Link** to place a Ready Link call from the Ready Link List. (See page 128 for details.)

Tip: You can also activate Automatic Speech Recognition with the flip closed. Press  to activate the Command menu and simply follow the voice prompts.

Note: The speech recognition system will wait 7.5 seconds for you to respond to a prompt. After 7.5 seconds, the phone will display an error message and your command will be cancelled.

Note: If your phone is unable to recognize an ASR command after three attempts, an error message will appear on the display and the phone will return to standby mode.

Making a Voice Call by Using ASR

With ASR, you can make a voice call by speaking a name, phone number, or using a voice tag.

To make a voice call by speaking a name:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Contact” to your phone.
3. Say the full name of a contact in your Contacts list (e.g. “John Jones”).
4. Say the label you’d like to call (e.g. “Mobile”).

Shortcut: To execute several commands at a time, you can also say several commands continuously (e.g. “Contact, John Jones, Mobile”).

5. The phone will automatically place a call if it recognizes your voice.
6. When you are finished, press **END/⓪**.

Note: If the phone does not recognize the name, the phone will find the closest match in your Contacts list and display a list of up to three names. You will hear the voice prompt “Did you say...” followed by the matched name. You can confirm the name by saying “Yes,” or change the selection by saying “No.”

Tip: During ASR operation, you can also select your desired items by using the navigation key or pressing available softkeys on the display.

To make a call by speaking a phone number:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Dial Number” to your phone.
3. Say the digits of the phone number using a natural voice.

Shortcut: You can also say “Dial Number” followed by the number you want to call.

4. The phone automatically places the call if it recognizes your voice.
5. When you are finished, press **END/⓪**.

Note: If the phone does not recognize the number, the phone will find the most likely match number and display a list of up to three numbers. You will hear the voice prompt “Did you say...” followed by the matched number. You can confirm the number by saying “Yes,” or say “No” to change the selection.

Finding Contacts List Entries

This feature allows you to find the entry in your Contacts list by saying the name.

To find a contact in the Contacts list:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Find Contact” to your phone.
3. Say the full name of a contact in your Contacts list (e.g. “John Jones”).
4. The phone will display the contact details for the recognized name.
5. To make a call, select the desired number from the list by using your navigation key and press **TALK** or **SPEAKER**.

Making a Call Using a Voice Tag

With a voice tag you record, your phone will automatically dial a phone number. Your phone can store up to 20 voice tags. (To create a voice tag, see “Programming a Voice Tag” below.)

To make a call by using a voice tag:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Call Voice Tag” to your phone.
3. Say your recorded voice tag.
4. The phone automatically places the call if it recognizes your voice.
5. When you are finished, press **END/⓪**.

Tip: To redial your last outgoing call by using ASR, press **TALK** or **SPEAKER** twice.

Programming a Voice Tag

To program a voice tag:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Edit Voice Tag.”
3. Say “New Entry.”
4. Say the digits of the phone number. (The phone number will be repeated and you will be asked to verify.)
5. Say “Yes” to confirm or “No” to cancel.
6. Say the name of the person you want to add to this voice tag.
7. Respond to the prompt by repeating the name after the beep. (You will hear a confirmation that voice tag has been successfully saved.)

Tip: Record voice tags in a quiet environment.

Reviewing Voice Tags

To review voice tags:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Edit Voice Tag.”
3. Say “Review List.” (A review list will display and you will hear all of the names and phone numbers saved in the voice tag list.)

Tip: During step 3 above, you can make a call to the highlighted number by pressing **TALK** or **SPEAKER**.

Erasing a Voice Tag

To erase a voice tag:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Edit Voice Tag.”
3. Say “Erase Entry.”
4. Say the name you want to erase from your voice tag list. (The name will be repeated and you will be asked to verify it.)
5. Say “Yes” to confirm or “No” to cancel. (You will hear a confirmation that the voice tag has been successfully erased.)

Tip: You can erase all voice tags through your phone’s Settings menu (see “Erasing All Voice Tags” on page 73).

Making a Ready Link Call by Using ASR

You can place a Ready Link call by using automatic speech recognition from your Ready Link List. To make a Ready Link Call, your phone's Ready Link mode must be set to Enable (see "Setting Ready Link Mode" on page 138 for details).

To make a Ready Link Call:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say "Ready Link." (Your Ready Link List will display.)
3. Choose from one of the following options:
 - **Contact** to place a Ready Link call from the Personal List.
 - **Group** to place a Ready Link call from the Personal Group List.
 - **Dial Number** to place a Ready Link call by entering a number.
 - **Phone Status** to notify you of your phone number and the current signal strength.
 - **Help** to activate the Automatic Speech Recognition instruction of Ready Link call.
4. Say "Contact," "Group," or "Dial Number."
5. Say the contacts name in your Ready Link List or digits of the phone number. (Wait for the prompt.)

6. Respond to the prompt by saying the name or group name.
 - To place the call, press and hold **---**. (See “Making and Receiving a Ready Link Call” on page 140 for details.)
 - To display other Contacts list, press **Go to** (left softkey), highlight your desired list, and press **MENU OK**. (See “Selecting a Contacts List” on page 140.)
 - To display the Ready Link options, press **Options** (right softkey) highlight your desired option, and press **MENU OK**. (See “Ready Link Options” on page 146.)

Tip: If you say “Contact” or “Dial Number” during step 3 on the previous page, you can say following commands continuously (e.g. “Contact, John Jones” or “Dial Number, 999-999-9999”).

Tip: To redial the last Ready Link call by using ASR with the flip open, press and hold **---** on the side of your phone and follow the voice prompts.

Tip: You can also make a Ready Link call to Contact, Group, and dialed number by using ASR with the flip closed. Press and hold **---**, and follow the voice prompts.

Using Digit Training

This feature allows you to train the phone to recognize your voice. You can get better recognition accuracy by programming your intonation pattern into your phone.

To program Digit Training:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Digit Training.”
3. Say “Start” to start programming.
4. Follow the voice prompts and recite the digits into your phone’s microphone. (A voice prompt will indicate the current rate of adaptation.)
5. Respond to the voice prompt repeatedly until adaptation is complete. (When you are finished training, you will hear a confirmation that the adaptation has been successfully completed.)

Note: Try digit training in a quiet environment for the best results. When you train, make sure you speak clearly and distinctly in your natural voice.

To activate Digit Training:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Digit Training.”
3. Say “On” or press **On** (right softkey) to activate the existing data. (A voice prompt will announce the activation of digit training.)

To deactivate Digit Training:

1. Follow steps 1-2 above.
2. Say “Off” or press **Off** (right softkey) to deactivate the existing data. (A voice prompt will announce the deactivation of digit training. The adaptation returns to its default setting.)

Phone Status Command

This feature uses a voice prompt to tell you your phone number and current signal strength.

To activate Phone Status Command:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Phone Status.” (You will hear your phone number and signal strength.)

ASR Help Command


This feature will help you learn the basics of using automatic speech recognition.

To activate Help Command:

1. Press and hold **TALK** or **SPEAKER** to activate the Command menu.
2. Say “Help.” (You will hear the voice prompts of helpful instructions for voice call.)






Managing Voice Memos

You can use your phone's Voice Services to record brief memos to remind you of important events, phone numbers, or grocery list items.

Tip: If you haven't signed up for the Ready Link service and Ready Link mode is set to **Disable**, or the Ready Link service is locked, you can use the Ready Link/Memo Button () as a Voice Memo button in standby mode. You can use it to record memos or display Memo options.

Recording Voice Memos

To record a voice memo:





1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Voice Memo** and press .
5. Select **Record** or **Rec:Speaker**, and press .
6. Start recording after the beep.

To end the recording of your memo:




- ▶ Press , **BACK**, or **END/⓪**.

Tip: Recording terminates automatically after 18 seconds.

To record the other party's voice during a phone call:

1. During a call, press **Options** (right softkey).
2. Highlight **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Voice Memo** and press .
5. Select **Record** and press .
6. Start recording after the beep.

To end the recording of your conversation:

- ▶ Press  or  while recording.
 - or -
- ▶ Press  to stop recording and disconnect the call.
 - or -
- ▶ Recording stops when the other party hangs up the call.










Note: Memo recording is disabled while you are roaming in analog service areas.

Note: Your phone can store up to 12 memos and the total available recording time is 72 seconds (maximum of 18 seconds per memo).

Tip: Voice Memos are stored with the date and time stamp in reverse chronological order.

Reviewing Voice Memos








To play the voice memos you have recorded:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Voice Memo** and press .
5. Select **Play** or **Play:Speaker** and press .
6. Select one memo from the list and press .
 - or -If you want to play all of the memos continuously, select **All** and press .
7. Press  to stop playing.
 - Press **Slow** (left softkey) or **Fast** (right softkey) to change the playing speed.
 - Press  to switch speakerphone mode.
 - To play a more recent or older memo, press the navigation key right or left.



Tip: You can also switch speakerphone mode by pressing **Options** (right softkey) and selecting **Speaker On/Off** during step 6 above.

Erasing Voice Memos








To erase all voice memos:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Voice Memo** and press .
5. Select **Play** or **Play:Speaker** and press .
6. Press **Options** (right softkey).
7. Highlight **Erase All** and press .
8. Select **Yes** and press .

- or -

1. Follow steps 1-4 above.
2. Select **Erase All** and press .
3. Select **Yes** and press .

To erase selected memos:


1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Voice Memo** and press .
5. Select **Play** or **Play:Speaker** and press .
6. Select the memo you want to erase and press **Options** (right softkey).
7. Highlight **Erase** and press .
8. Select **Yes** and press .

Setting Up Screen Call









This feature enables you to screen incoming calls by using a recorded announcement, either one that is pre-recorded or one that you record.






Activating Screen Call



To start Screen Call when you have incoming calls:

1. When the phone rings or vibrates, press **Options** (right softkey) to display the options.
2. Highlight **Screen Call** and press .

To set Auto Screen Call:







1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Screen Call** and press .
5. Select **Auto** and press .
6. Select **On** and press .
7. Set the answering time by using numeric keys or by pressing the navigation key up or down.
8. Press  or **OK** (left softkey). (The  icon is displayed on the standby display.)

Tip: If a new caller's message is waiting, the  icon appears on the display. The memos recorded while activating "Screen Call" are shown with the  or  icon in the Voice Memo list (: once played, : not played yet). To listen to the message, see "Reviewing Voice Memos" on page 132.

Tip: While the caller's message is being recorded, press  to answer the call, or press  to stop recording and disconnects the call.

Selecting an Announcement for Screen Call











To select a Screen Call announcement:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Screen Call** and press .
5. Select **Announcement** and press .
6. Depending on your preference, highlight **Pre-Recorded** or **Custom** and press .

Recording Your Name for a Pre-Recorded Announcement

You can use a pre-recorded announcement with or without your name. If you record your name, your phone uses your name to announce that you are not available to answer the call.






To record your name:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Screen Call** and press .
5. Select **Announcement** and press .
6. Select **Pre-Recorded** and press **Edit** (right softkey).
7. Highlight **Record Name** and press 
 - If your name has already been recorded, select **Yes** or **No** to overwrite the existing recording.
8. Press  to start the first recording.
9. Press  to stop recording.
10. After the first recording, press  again to start the second recording.
11. Press  to stop recording.

Tip: Recording terminates automatically in 12 seconds.

Recording a Customized Announcement







To record an announcement:

1. Follow steps 1-5 on the previous page.
2. Select **Custom** and press **Edit** (right softkey).
3. Highlight **Record** and press 
 - When an announcement has already been recorded, select **Yes** or **No** to overwrite the existing recording.
4. Press  to start the first recording.
5. Press  to stop recording.
6. After the first recording, press  again to start the second recording.
7. Press  to stop recording.

Tip: Recording terminates automatically in 12 seconds.




Reviewing an Announcement

To review an announcement:

1. Press  to access the main menu.
2. Select **Tools/Extras** and press .
3. Select **Voice Services** and press .
4. Select **Screen Call** and press .
5. Select **Announcement** and press .
6. Select **Pre-Recorded** or **Custom** and press **Edit** (right softkey).
7. Highlight **Play** or **Play:Speaker** and press .

Erasing an Announcement

To erase an announcement:

1. Follow steps 1-6 above.
2. Select **Erase Name** to erase the name for a Pre-Recorded announcement and press 
 - or –
 - Select **Erase** to erase the message for a Custom announcement and press .
3. Select **Yes** and press .

Using Ready Link



In This Section

- ◆ **Getting Started With Ready Link**
 - ◆ **Making and Receiving a Ready Link Call**
 - ◆ **Adding and Editing Ready Link Contacts**
 - ◆ **Erasing Ready Link List Entries**
 - ◆ **Updating Your Ready Link Lists**
 - ◆ **Managing Ready Link Settings**
-

Your Sanyo SCP-7400 Phone gives you the ability to quickly connect with other Ready Link users for walkie-talkie-style communication from anywhere, to anywhere on the network provided to you. It's ideal for quick two-way conversations with your friends, family, and co-workers.






This section explains the features and options of Ready Link.

Getting Started With Ready Link

Ready Link allows you to enjoy quick, two-way, “walkie-talkie-style” communication with your friends, family, and co-workers. You can make 1-to-1 or 1-to-many calls (up to 5 others on the same call) to any other Ready Link user, anywhere on the network provided to you. You can make and receive Ready Link calls when your phone displays the  or  icon.

Setting Ready Link Mode


To enable or disable Ready Link mode:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Enable/Disable** and press .
5. Select **Enable** and press . (The default setting is **Disable**.)
 - **Enable:** Lets you make or receive Ready Link calls any time your phone is not in use.
 - **Disable:** Disables your phone’s Ready Link service; you will not be able to make or receive Ready Link calls or access your Ready Link contacts.

Tip: If you haven’t signed up for the Ready Link service and Ready Link mode is set to **Disable**, or the Ready Link service is locked, you can use the Ready Link/Memo Button () as a Voice Memo button in standby mode.

Preparing Your Phone for Ready Link Service

Every time you turn on your phone, your phone will identify itself and make itself available to the Ready Link network.

- ▶ When you turn on your phone in an area where Ready Link service is available, your phone will display “Preparing...Please wait.” (The  icon appears on the display. Your phone is now ready to make and receive Ready Link calls.)


Ready Link Call Alerts

There are several ways your phone alerts you during Ready Link calls.


When you make or receive a Ready Link call:

- The phone sounds (depending on the Ringer Type and Ringer Volume setting).
- The backlight illuminates.
- The screen displays a Ready Link call message.
- The other party's Ready Link number and name (if available) are displayed.
- The screen displays who has the floor.


The status of a Ready Link call is displayed on your phone as follows:

- The Green LED On indicates you have the floor and may speak.
- The Red LED On indicates another contact has the floor.
- The LED Off indicates the floor is open. (You can take the floor and speak by pressing and holding .)


Main LCD Display during Ready Link Call



You have floor




Floor is open



Other has floor

Sub LCD Display during Ready Link Call



You have floor




Floor is open



Other has floor

Making and Receiving a Ready Link Call

Displaying the Ready Link List

- ▶ From standby mode, press **R-Link** (left softkey) or the Ready Link/Memo button on the side of your phone () to access the Ready Link List.

Tip: The first time you access the list, the Ready Link Help message will appear. Press **Yes** (left softkey) and **Next** (left softkey) to read a brief introduction of Ready Link.

Selecting a Contacts List

When your phone displays a Ready Link List, the left softkey is labeled **Go to**. To switch to another contacts list, press **Go to** (left softkey), highlight your desired list, and press .



- **Personal List/Personal Grps.** contain your personal Ready Link contact names and numbers, separately or in groups. You can create and edit your own Personal List. Your phone can store a total of 200 entries (you may include up to five contacts per group).
- **Outgoing** shows the last 10 different Ready Link calls you placed.
- **Incoming** shows the last 10 different Ready Link calls you accepted.
- **Missed** shows the last 10 Ready Link calls you missed.

Note: The  icon next to the group name indicates a group.




Making a Ready Link Call (1-to-1 Call)



You can place a 1-to-1 Ready Link call by entering a Ready Link number or by selecting a contact from the Ready Link List.




To place a Ready Link call by selecting a contact:

1. Press **R-Link** (left softkey) or press .
2. Press **Go to** (left softkey), highlight the list from which you want to place a call (**Personal List**, **Outgoing**, **Incoming**, or **Missed**), and press .



Tip: You can also select **Enter R-Link#** from the **Go to** option to enter a Ready Link number directly. (See page 143 for details.)

3. Scroll to the contact you want to call, and press and hold  to place the call and get the floor. (You will see **R-Link calling...** and **Connecting...** followed by “**You have floor.**” You can now begin speaking.)
– or –
Scroll to the contact you want to call and press and release  to place the call. (The call will connect as described above, but “**Floor is open.**” will appear on the screen and either you or your contact may press and hold  to take the floor and speak.)

Note: During a Ready Link call, the “**floor**” is the right to speak. When you see “**Floor is open.**,” the first person to press the Ready Link/Memo button () can speak (while holding the button). Only the person who has the floor can speak. The phone beeps if you press  when another contact has the floor.

4. Continue holding  as you speak. (When you are finished speaking, release  to allow the other contact to speak. When the other party takes the floor, you will see the speaker's name and phone number and the text “**has floor.**”)
5. When you are finished, press .






Note: When neither party has the floor during a Ready Link call, “**Floor is open.**” appears on the display. If no one takes the floor for 20 seconds, the Ready Link call ends automatically.

Tip: If you press  or  during step 3 above, you can make a standard voice call.



Making a Ready Link Call (Group Call)


You can make a Ready Link call to all members in a Group entry, which you have in your Ready Link List. You can communicate with up to five members at a time.

To place a Ready Link Group call:

1. Press **R-Link** (left softkey) or press .
2. Press **Go to** (left softkey), highlight **Personal Grps.** and press .
3. Scroll to the group you want to call, and press and hold  to place the call and take the floor. (You will see **R-Link calling...** and **Connecting...** followed by “**You have floor.**” Continue with the Ready Link call as described on page 141.)
 - To make a Ready Link call to a group member, select your desired group, highlight your desired group member, and press and hold .
 - If one of the group members takes the floor, you will see the member's name and Ready Link number on the display.
4. When the call is finished, press .

Tip: The phone beeps if you press  when another contact has the floor.

Tip: You can also make a Group Call after checking the group member. Press  to display group members, highlight **<Call Group>** and press and hold  during step 3 above.

Tip: To redial your last Ready Link call, highlight **Redial** and press and hold  from the Ready Link List.

Making a Ready Link Call by Entering a Number

To place a Ready Link call by entering a number:


1. From standby mode, enter the Ready Link number you want to dial.
2. Press **---** to place the Ready Link call. (Continue holding **---** to take the floor and speak.)
 - The contact's name appears on the display if there is a matched number in your Ready Link List.
3. Continue with the Ready Link call, pressing and holding **---** to speak and releasing it to allow others to reply.
4. When the call is finished, press **END/O**.
 - or -
 - 1. Press **R-Link** (left softkey) or press **---**.
 - 2. Press **Go to** (left softkey), highlight **Enter R-Link#** and press **MENU OK**.
 - 3. Enter the Ready Link number you want to dial.
 - 4. Follow steps 2-4 above.

Note: Ready Link numbers must contain ten digits (area code + phone number). Your Ready Link number is the same as your wireless phone number.

Missed Call Notification for Ready Link Calls

When an incoming Ready Link call is not answered, the Missed Call Notification and the  icon are displayed on your screen.

To call the last Missed Ready Link call:




- ▶ Simply press and hold  while the Missed Call Notification is displayed. (Continue with the Ready Link call as described previously.)

Tip: If you have two or more notifications, the event list will appear.

To erase the Missed Call log:




- ▶ Press **Dismiss** (right softkey).

Tip: If you press  before checking your notification, **Events** (right softkey) appears in standby mode. Press **Events** (right softkey) to display the notification list.



Note: When you display Missed Calls entries, you will see the  icon next to the name. The  icon will remain until you make or receive a Ready Link call to or from the entry. The  icon appears next to the new missed call entry.

Receiving a Ready Link Call


To receive a Ready Link call:

1. Make sure your phone's Ready Link mode is enabled (see "Setting Ready Link Mode" on page 138).
2. When you receive a Ready Link call from a contact, "R-Link Call," the contact's name, and the Ready Link number appear on the display. (You do not need to take any action to answer the call.)
 - When you receive a group call, "Group Call" and the Ready Link number appear.
 - If nobody takes the floor for 20 seconds, the call will be a missed Ready Link call.
3. If the person placing the call has kept the floor (held the Ready Link/Memo button), you will see the contact name and Ready Link number along with "**has floor.**" and you will hear the caller speaking.
4. When the caller finishes speaking and releases , you will see "**Floor is open.**" on the display screen. Press and hold  to take the floor and reply to the caller. (You will see "**You have floor.**" and hear a tone confirming that you may speak.)
5. When the conversation is finished, press .

Tip: You can also receive a Ready Link call with the flip closed. Press and hold  to take the floor when the floor is open.

Note: You can change the volume and the speakerphone setting while a Ready Link call is activated. **Volume:** Adjust the voice volume by using the Side Volume key or by pressing the navigation key up or down except when you are pressing and holding . **Speaker:** Switch the speakerphone on or off by pressing .

Ready Link Options

When you use Ready Link, several options are available by pressing **Options** (right softkey). To select an option, highlight it and press .




- **Copy to Personal** to copy a contact to the Personal List. (This option doesn't appear if the entry is already in the Personal List or when you select Personal List/Personal Groups.)
- **Edit** to edit a Ready Link number and/or name. (See page 150.)
- **Copy to Ph. Book** to copy a contact to the Contacts List.
- **Erase** to erase a contact. **Erase Group** appears when you highlight a group.
- **Add Contact** to add a new contact. **Add Group** appears when you highlight a group list. (See page 148 for details.)
- **Erase R-Link List** to erase entries saved in the Ready Link List.
- **Help** to see the Ready Link instruction page.

Adding and Editing Ready Link Contacts

Copying an Entry to Personal List or Personal Group List

You can copy an entry to your Personal Lists from several different sources. If the selected entry is already stored in the Personal Lists, the “copy” option does not appear.

To copy an entry from the Ready Link List:

1. Press **R-Link** (left softkey) or press .
2. Press **Go to** (left softkey), highlight the list from which you want to copy an entry (**Outgoing**, **Incoming**, or **Missed**), and press .
3. Select the entry you want to copy (or scroll to highlight the **Redial** entry at the top of your screen) and press **Options** (right softkey). To select an option, highlight it and press 
 - **Copy to Personal** to copy the contact to the Personal List.
 - **Copy to Ph. Book** to copy the contact to the Contacts list.
4. Press **Yes** (left softkey) to copy and save the entry to your Personal List.

Saving a Ready Link Number

When you have finished a Ready Link call, you will see the Ready Link number and the text “R-Link call ended.” on the display. You can save a Ready Link number from the ending display to your Personal Lists.

To save the number:




1. From the end display, press **Save** (right softkey).
2. Enter a name and press .
3. Press **Save** (left softkey).
4. Press **Yes** (left softkey).

Note: If the number is already stored in the Personal List or Personal Groups, the “Save” softkey does not appear.

Finding an Entry in the Ready Link List

You can find your desired entry by entering a few letters.






To find a Ready Link entry:

1. Press **R-Link** (left softkey) or press .
2. Press **Go to** (left softkey), highlight your desired list (**Personal List**, or **Personal Grps.**), and press .
3. Enter the first letter or the first few letters of the name.
 - The display shows the list beginning with the letter(s) you entered.
4. Scroll through the list and press  to select your desired entry.

Adding a New Contact to Your Personal List

You can store a total of 200 entries in the Personal Lists.

To add a new Ready Link contact:

1. Press **R-Link** (left softkey) or press .
2. Select **<Add Contact>** and press .
– or –
Select a contact and press **Options** (right softkey). Then highlight **Add Contact** and press .
3. Enter a name for the new contact and press . (This is the name you will see when calling or receiving a call from the contact.)
4. Select **R-Link Number**, enter the contact's 10-digit Ready Link number (their wireless phone number) and press .
5. Press **Save** (left softkey) to save the new contact to your Personal List.

Tip: You are not allowed to use the following symbols during step 4: ":", "@", ",", "/", "*", "(", and ")".

Adding a New Group to Your Personal Group List

You can add new groups to the Personal Group List. Each group can include up to five members. You can enter a group member directly, or select the member from the Personal List.




To add a new Ready Link group entry:

1. Press **R-Link** (left softkey) or press **---**.
2. Press **Go to** (left softkey), highlight **Personal Grps.**, and press **MENU OK**.
3. Select **<Add Group>** and press **MENU OK**.
– or –
Select an entry and press **Options** (right softkey). Then highlight **Add Group** and press **MENU OK**.
4. Enter a Group Name, press **MENU OK**, and press **Next** (left softkey).
5. To add contacts to the group, press **Add** (right softkey).
6. Highlight one item from the following and press **MENU OK**:
 - **New** to add a new contact. See page 148 for details.
 - **from Personal** to add a contact from your Personal List.
7. Scroll to the contacts you want to add and press **MENU OK** or **Pick** (right softkey) to include the entries.
8. Press **Done** (left softkey) when you are finished selecting contacts, then press **Update** (left softkey) to update your Personal Group List with the new group entry.

Tip: You can also add members directly. From step 5 above, highlight **<Add Members>** and press **MENU OK**. Enter the new member's name and R-Link number and press **Save** (left softkey) to save the entry.





Editing a Contact in Your Personal List

To edit a Personal List contact:



1. Press **R-Link** (left softkey) or .
2. Scroll to the entry you want to edit and press **Options** (right softkey).
 - **Edit** to edit the selected contact.
 - **Copy to Ph. Book** to copy the entry to the Contacts list.
 - **Erase** to erase the selected contact.
 - **Add Contact** to add a new contact.
 - **Erase R-Link List** to erase the Ready Link List.
(See page 153 for details.)
 - **Help** to view the Ready Link instruction page.
3. Highlight **Edit** and press .
4. Select the field you want to edit (**Name** or **R-Link Number**), and press .
5. Edit the entry, press **OK** (left softkey), and press **Save** (left softkey) to save your changes.

Editing a Group in Your Personal Group List

To edit a group name:

1. Press **R-Link** (left softkey) or .
2. Press **Go to** (left softkey), highlight **Personal Grps.**, and press .
3. Scroll to the group entry you want to edit and press **Options** (right softkey).
 - **Edit** to edit the selected group.
 - **Erase Group** to erase the selected group.
 - **Add Group** to add a new group.
 - **Erase R-Link List** to erase the Ready Link List.
(See page 153 for details.)
 - **Help** to view the Ready Link instruction page.
4. Highlight **Edit** and press .
5. Edit the group name and press  or **OK** (left softkey).




Tip: If you don't need to edit the group name, press **Next** (left softkey) during step 5 above and skip step 6.

6. Press **Save** (left softkey) to save your changes.
7. To edit a group member, scroll to the contact you want to edit and press **Options** (right softkey).
 - **Edit** to edit a group member's name and phone number.
 - **Erase** to erase the group member.
 - **Add New** to add a new group member.
 - **Add (Personal)** to add a new group member from the Personal List.
 - **Details** to display a group member's information.
8. Highlight **Edit** and press .
9. Select the field you want to edit (**Name** or **R-Link Number**) and press .
10. Edit the entry, press **OK** (left softkey), and press **Save** (left softkey) to save your changes.
11. Press **Update** (left softkey) to update your Personal Group List.





Erasing Ready Link List Entries

Erasing an Entry in Your Personal List or Personal Group List

To erase a contact or a group:

1. From the Ready Link List, press **Go to** (left softkey), highlight **Personal List** or **Personal Grps.**, and press .
2. Scroll to the entry you want to erase and press **Options** (right softkey).
3. Highlight **Erase** and press .
 - **Erase Group** appears when you select Personal Grps.
4. Select **Yes** and press .




To erase a group member:

1. From the Ready Link List, press **Go to** (left softkey), highlight **Personal Grps.**, and press .
2. Scroll to your desired group and press  to display the group members.
3. Select the contact you want to erase and press **Options** (right softkey).
4. Highlight **Erase** and press .
5. Select **Yes** and press .
6. Press **Update** (left softkey) to update your Personal Group List.

Erasing a Ready Link List

You can erase all entries saved in the Ready Link List.

To erase a Ready Link List:





1. From the Ready Link List, press **Options** (right softkey).
2. Highlight **Erase R-Link List** and press .
3. Select your desired option and press 
 - **Outgoing** to erase all outgoing Ready Link calls.
 - **Incoming** to erase all incoming Ready Link calls.
 - **Missed** to erase all missed Ready Link calls.
 - **All Calls** to erase all Ready Link call history, except redial.
 - **All Personal Ent** to erase all entries in Personal List and Personal Grps. You are prompted to enter your 4-digit lock code.
4. Select **Yes** and press .

Tip: The Redial number will not be erased.

Updating Your Ready Link Lists

Updating the Personal Lists










To update your Personal Lists manually through the Ready Link server:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **List Update** and press .

Managing Ready Link Settings

Assigning Speed Dialing for Ready Link Entries

To assign Speed Dialing for Ready Link entries:





1. Press  to access the main menu.
2. Select **Contacts** and press .
3. Select **Speed Dial #s** and press .
4. Select an unassigned number and press .
 - When you highlight an assigned number and press , you'll be asked whether you want to overwrite the assigned number. Select **Yes** or **No**, or you can also select **Unassign** to cancel the stored speed dial.
5. Press **Go to** (left softkey), highlight the list from which you want to set a speed dial (**Personal List**, or **Personal Grps.**) and press .
6. Select the contact and press .
 - or –
 - Select the group and press , select an option, and press .
 - **Assign** to assign the selected group as a speed dial.
 - **Details** to display the group details. You can select the group member from the group list.

To use Speed Dial for a Ready Link entry:

- ▶ From standby mode, press the appropriate key and press and hold .

Restarting the Ready Link Service






To restart the Ready Link service:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Restart** and press .

Setting Ready Link Guard

This feature enables you to display the warning message when you cannot receive Ready Link calls. The warning message will appear when you are launching Media Player, a Web or Java application, or sending/uploading your pictures and videos.








To set the Ready Link Guard:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **R-Link Guard** and press . (A message will appear.)
5. Press **OK** (left softkey) to continue.
6. Select **On** and press .
 - To deactivate this feature, select **Off** during step 6 above.

Setting Ringer Types for Ready Link Calls

Your phone provides a variety of ringer types that allow you to customize your ringer and volume settings.

To select a ringer type for Ready Link calls:








1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Sounds** and press .
5. Select **Ringer Type** and press .
6. Select **Ready Link Calls**, **R-Link Missed**, or **R-Link Floor Tone**, and press .
7. Scroll to your desired ringer type and press .
 - To confirm the ringer, press **Play** (right softkey) during step 6 above.

Tip: You can change the ringer type in another way (see “Selecting Ringer Types for Ready Link Calls” on page 39).

Setting an Alert Notification for Ready Link Calls

Your phone can alert you with an audible tone when you receive a Ready Link call.

To set alerts for Ready Link calls:






1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Sounds** and press .
5. Select **Alerts** and press .
6. Select **Ready Link Calls** or **R-Link Missed** and press .
7. Select **Once** or **Repeat Alert** and press 
 - To deactivate R-Link Missed alert, select **Off** during step 7 above.

Tip: You can set alerts in another way (see “Alert Notification” on page 43).

Setting the Speakerphone for Ready Link Calls

You can set the speakerphone on or off when Ready Link call is activated. By default, the speakerphone is set to on.

To set the speakerphone on or off:






1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Speakerphone** and press .
5. Select **On** or **Off** and press .

Note: If the phone's ringer volume is set to Vibrate, Ringer off, or Silence All, the speakerphone turns off. Press  to turn the speakerphone mode on.

Setting the Default View of the Ready Link List

You can select the default Ready Link List when Ready Link is launched.






To select the default view of the Ready Link List:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Default View** and press . (The available lists appear.)
5. Select your desired list and press .

Setting the Floor Display of the Ready Link Calls

With this feature, you can select the floor display during a Ready Link calls.

To select the floor display:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **Ready Link** and press .
4. Select **Floor Display** and press .
5. Select **Text Only** or **Text & Image** and press .
 - To see a display preview of the image, select **Text & Image** and press **Preview** (right softkey) during step 5 above (Main LCD only).

Using Your Phone's Built-in Camera

In This Section

- ◆ Taking Pictures
 - ◆ Storing Pictures in My Pictures
 - ◆ Taking Videos
 - ◆ Storing Videos in My Videos
 - ◆ Sending Sprint PCS Picture MailSM and Sprint PCS Video Mail
 - ◆ Managing Sprint PCS Picture MailSM
-




Your Sanyo SCP-7400 Phone's built-in camera gives you the ability to take full-color digital pictures, view your pictures using the phone's display, and instantly send them to your family and friends. It's fun and as easy to use as a traditional point-and-click camera: just take a picture, view it on your phone's display, and send it from your phone to up to ten people. In addition to taking pictures, you can also take, view, and send videos to your friends and family with your built-in camera.


This section explains the features and options of your phone's built-in camera.




Taking Pictures

Taking pictures with your phone's built-in camera is as simple as choosing a subject, pointing the lens, and pressing a button. You can activate camera mode and take pictures whether the phone is open or closed.

To take a picture with the flip open:

1. Press  to access the main menu.
2. Select **Picture&Video** and press .
3. Select **Camera** and press  to activate camera mode.
(Additional options are available through the camera mode **Options** menu. See "Camera Mode Options" on page 161 for more information.)

Shortcut: To activate camera mode, you can also press and hold  or the side camera key (see illustration on page 9).

4. Using the phone's main LCD as a viewfinder, aim the camera lens at your subject.
5. To take the picture, press , , **Capture** (left softkey), or the Side Camera key. (The picture will be saved automatically in your In Camera folder.)
 - To return to camera mode to take another picture, press .
6. Press **Next** (right softkey) for more options:
 - **Send Picture** to send the picture to up to 10 contacts at one time. (See page 183 for details.)
 - **Upload to Albums** to upload the picture you just took to the Sprint PCS Picture Mail Website. Depending on your settings, you may be prompted to accept a Sprint PCS Vision connection.
 - **Set as Picture ID** to assign the picture as a Picture ID.
 - **Set as Scrn Saver** to assign the picture as a Screen Saver.
 - **Go to Camera** to return to camera mode to take another picture.
 - **Pics In Camera** to go to the In Camera folder to review your saved pictures.
 - **Delete** to delete the picture you just took.

To take a picture with the flip closed:

1. Press and hold the side camera key to activate camera mode.
2. Point the camera lens at your subject. (You can check the picture framing through the Sub LCD.)

Note: When taking a picture with the flip closed, the subject image appears in reverse on the external display. The captured image will not be saved in reverse.

3. Press the side camera key to take the picture. (The picture will be saved automatically in your In Camera folder.)
 - Open the flip to review the picture and for more options.






Note: While you are taking a picture, the backlight turns on even if your backlight is set to **Always Off**.

Note: In some cases, the screen may flicker and the stripes may appear on the display under fluorescent lighting.

Creating Your Sprint PCS Picture MailSM Password

The first time you use any of the Sprint PCS Picture Mail management options involving the Sprint PCS Picture Mail Website, you will need to establish a Sprint PCS Picture Mail password through your wireless phone. This password will also allow you to sign in to the Sprint PCS Picture Mail Website at <http://pictures.qwest.com> to access and manage your uploaded pictures, videos, and albums.

To create your Sprint PCS Picture Mail password:

1. Press  to access the main menu.
2. Select **Picture&Video** and press .
3. Select **Online Albums** and press .
4. Select **View Albums** and press . (You will be prompted to create a pictures password.)
5. Enter a four- to eight-digit password and press  or **OK** (left softkey).
6. Please wait while the system creates your account.


Tip: Write down your Sprint PCS Picture Mail password in a secure place.

Once your account has been successfully registered, you may upload and send pictures and videos, and access the Sprint PCS Picture Mail Website.

Camera Mode Options

Several options are available from camera mode.

Press **Options** (right softkey) to display additional camera options:



- **Flash** to activate the flash. (See “Setting the Flash” on page 162 for details.)
- **Self-timer** to activate the camera’s timer. (See “Setting the Self-timer” on page 162 for details.)
- **Fun Tools** to select an option from the following:
 - **Fun Frames** to select your favorite fun picture frame to decorate your picture.
 - **Multiple Shots** to take multiple shots. (See “Taking Multiple Shots” on page 163 for details.)
 - **Color Tone** to select a wide variety of color tones for the picture (**Normal**, **Sepia**, **Black & White**, **Negative**, **Posterization**, **Emboss**, or **Drawing**).
- **Image Controls** to select an option from the following:
 - **Brightness** to select **Auto** or **Manual** brightness control. If you select **Manual**, use your navigation key to select a setting and press  to apply the desired setting.
 - **White Balance** to adjust white balance based on changing conditions. Select from **Auto**, **Sunny**, **Cloudy**, **Tungsten**, **Fluorescent**, or **Manual**.

Shortcut: To change the White Balance, press the navigation key up or down in camera mode.

- **Camera Settings** to select **Resolution**, **Quality**, **Shutter Sound**, **Night Mode**, **Full Screen**, or **Auto Delete**. (See “Selecting Camera Settings” on page 165 for details.)
- **Pics In Camera** to go to your phone’s In Camera folder. (See “In Camera Folder” on page 168 for details.)
- **Go to Camcorder** to switch to video mode. (See “Taking Videos” on page 173 for details.)
- **Key Guidance** to indicate the key functions in camera mode.

Setting the Flash





To activate the flash:

1. From camera mode, press **Options** (right softkey).
2. Highlight **Flash** and press .
3. Select an option from the following and press 
 - **On This Shot** to activate the flash for one shot.
 - **On Always** to activate the flash all the time.
 - **Auto** to activate the flash automatically.
4. Take a picture using the phone's main LCD as a viewfinder.
 - To deactivate this feature, select **Off** during step 3 above.

Tip: When the phone is open and in camera mode, press  to switch between flash modes.

Setting the Self-timer



To activate the Self-timer:

1. From camera mode, press **Options** (right softkey).
2. Highlight **Self-timer** and press .
3. Highlight the length of delay you want the timer to use (**10 seconds** or **5 seconds**) and press . (The  icon appears on the lower left portion of the main LCD.)
4. Press **Start** (left softkey) when you are ready to start the timer.
5. Get ready for the picture. (When the timer is down to three seconds, the Self-timer icon will turn red ) and the phone will begin to beep.)

Note: After taking a picture, Self-timer settings return to off.

To cancel the Self-timer after it has started:



- ▶ Press **Cancel** (right softkey).

Note: While the Self-timer is active, all keys are disabled except , , and **Cancel** (right softkey).




Taking Multiple Shots

This feature allows you to take up to 9 continuous shots of one moment. When you take multiple shots, the  icon will appear in the viewfinder.

To take multiple shots:

1. From camera mode, press **Options** (right softkey).
2. Highlight **Fun Tools** and press .
3. Highlight **Multiple Shots** and press .

Note: If your phone's memory is full, the "Multiple Shots" option will not appear.

4. Select your desired option from the following and press .
 - **3 Shots** to take series of 3 shots.
 - **6 Shots** to take series of 6 shots. (Only appears when the resolution setting is Low or Medium.)
 - **9 Shots** to take series of 9 shots. (Only appears when the resolution setting is Low.)
5. Select the duration of the interval between shots from **Normal** or **Fast** and press .
6. To take the pictures, press . (The Multiple Shots folder will display up to nine thumbnail pictures per screen.)
 - To deactivate this feature, select **Off** during step 4 above.

Tip: After taking multiple shots, the pictures are automatically saved in the In Camera folder. (See "In Camera Folder" on page 168 for details.)

When you are in the Multiple Shots folder, several options are available.

Press **Options** (right softkey) to display the following options:

- **Upload to Albums** to upload pictures saved in your phone to the Sprint PCS Picture Mail Website.
- **Set as Picture ID** to display the picture as a Picture ID.
- **Set as Scrn Saver** to display the picture as a screen saver.
- **Go to Camera** to activate camera mode.
- **Pics In Camera** to access the In Camera folder.
- **Delete** to delete pictures in the In Camera folder.
- **Slideshow** to display your pictures as a slideshow. (Only appears when you have two or more pictures in the folder.)
- **Info Bar** to display information on the currently highlighted picture. (Expanded picture only)
- **Thumbnail/Expand** to switch the display from full-screen to thumbnail view (up to nine pictures per screen).

Tip: You can also switch the thumbnail view to the expanded display by pressing and holding . To go back to thumbnail view, press .


- **Full Screen** to display the currently highlighted picture to the full screen view without any icons.

Tip: To switch the full screen view, press .

Using the Zoom

This feature allows you to zoom in on an object when you take a picture. Depending on your resolution settings, you can adjust the zoom from 1-step to 20-step.



To use the zoom:

1. From camera mode, press the navigation key right or left, or the side volume key up or down to adjust the zoom. (The gauge bar appears.)
2. Press  to take the picture. (The picture will be saved automatically in your In Camera folder.)

Note: The Zoom gauge will not appear when the Resolution setting is High.




Selecting Camera Settings

To select your camera settings:

1. From camera mode, press **Options** (right softkey).
2. Highlight **Camera Settings** and press .
3. Select an option from the following and press .
 - **Resolution** to select a file size (**High**, **Medium**, or **Low**) for a picture.
 - **Quality** to select **Economy**, **Normal**, or **Fine** picture quality.
 - **Shutter Sound** to select a shutter sound. (See “Setting the Shutter Sound” below for details.)
 - **Night Mode** to select **On** for taking pictures in low light.
 - **Full Screen** to expand the display to the full screen view without any icons (except the flash icon).
 - **Auto Delete** to set the auto delete function. (See “Setting Auto Delete” on page 166 for details.)

Setting the Shutter Sound




To select the Shutter Sound:

1. From camera mode, press **Options** (right softkey).
2. Select **Camera Settings** and press .
3. Select **Shutter Sound** and press .
4. Select an option from the following and press .
 - **Default** plays the default shutter sound.
 - **Say “Cheez”** plays a recording of the phrase “Say Cheez.”
 - **Off** makes no sound.

Setting Auto Delete


With this feature, pictures that have been uploaded to your online Sprint PCS Picture Mail account will be erased automatically from your phone.

To set Auto Delete:















1. From camera mode, press **Options** (right softkey).
2. Highlight **Camera Settings** and press .
3. Highlight **Auto Delete** and press .
4. Select **Yes** and press  to activate auto delete.
 - To deactivate this feature, select **No** during step 4 above.

Note: You can also set this function in video mode. From video mode, press **Options** (right softkey), select **Camcord.Settings**, and follow steps 3-4 above.

Viewing Your Camera's Status Area Display



Camera Icon Indication

No.	Function		Icons	Details
1	Flash	On This Shot		To use the flash for only one shot.
		On Always		To use a flash every time you take a picture.
		Auto		To use the auto flash function.
2	White Balance	Sunny		Use this setting for sunny weather.
		Cloudy		Use this setting for cloudy weather.
		Tungsten		Use this setting for standard household lighting.
		Fluorescent		Use this setting for fluorescent lighting.
		Manual		For the manual setting of white balance.
3	Brightness	Manual		For the manual setting of brightness.
4	Night Mode			Use this setting in low light.
5	Multiple Shots			Use this setting for Multiple Shots.
6	Resolution	High		For high picture resolution.
		Medium		For medium picture resolution.
		Low		For low picture resolution.
7	Memory Gauge			Shows the remaining memory.
8	Picture Number		100%	The number of stored pictures.
	Remaining Pictures		/100	The number of pictures you can take with the current resolution.
9	Self-timer			Numeric countdown will appear when the self timer has been activated.

Storing Pictures in My Pictures





My Pictures is your phone's picture storage area. There are two types of folders in My Pictures that can be used separately according to your needs. They are:

- **In Camera** (see below)
- **Saved to Phone** (see page 171)

In Camera Folder

Once a picture is taken, it is automatically saved to the folder called "In Camera." From the In Camera folder, you can view all the pictures you have taken, store selected images in your phone, send pictures to the Sprint PCS Picture Mail Website, delete images, and access additional picture options.


To review your stored pictures in the In Camera folder:

1. Press  to access the main menu.
2. Select **Picture&Video** and press .
3. Select **My Pictures** and press .
4. Select **In Camera** and press . (Thumbnail pictures will display, up to nine pictures at a time.)
5. Use your navigation key to view and scroll through pictures.



In Camera Folder Options

When you are in the In Camera folder, several options are available.

Press **Options** (right softkey) to display the following options:

- **Upload to Albums** to upload pictures saved in your phone to the Sprint PCS Picture Mail Website. Depending on your settings, you may be prompted to accept a Sprint PCS Vision connection. Choose one from the following options:
 - **This Picture** to upload the currently highlighted picture.
 - **Selected Pictures** to upload the selected pictures. Press  to select a picture (the check box on the lower right corner will be marked).
 - **All Pictures** to upload all the pictures in the In Camera folder.

Note: Erasing pictures will free up memory space in your phone to enable you to take more pictures. Once erased, pictures cannot be uploaded to your online Sprint PCS Picture Mail account or saved to the Saved to Phone folder.

- **Set as Picture ID** to display the currently highlighted picture for incoming calls from a specific Contacts List entry. Select your desired entry and press .
- **Set as Scrn Saver** to display the currently highlighted picture as a screen saver. Select **Main LCD** or **Sub LCD** and press .

Note: Assigned pictures will be copied automatically to the Saved to Phone folder with the .


- **Details/Edit** to select an option from the following:
 - **Text Caption** to edit the caption of a currently highlighted picture.
 - **Picture Info** to display information on the currently highlighted picture, such as caption, time/date, size, etc.
 - **Color Tone** to select a wide variety of color tones for the picture (**Sepia**, **Black & White**, **Negative**, **Posterization**, **Emboss**, **Painting**, or **Drawing**).
 - **Rotate Picture** to rotate the currently highlighted picture. To rotate, press the navigation key right or left, or **Rotate** (right softkey).
- **Delete** to delete pictures in the In Camera folder. Select **This Picture**, **Selected Pictures**, or **All Pictures**.
- **Save to Phone** to save the selected pictures in the Saved to Phone folder.
- **Sort by Date** to sort pictures by date. (Thumbnail pictures only.) Select **Taken-Descending**, **Taken-Ascending**, **Uploaded-Descend**, or **Uploaded-Ascend**.
- **Slideshow** to display your pictures as a slideshow. (Only appears when you have two or more pictures in the folder.)
- **Info Bar** to display information on the selected picture, such as folder name, picture number, caption, etc. Select **On** to display the caption of a picture; select **Off** to hide the information. (Expanded picture only.)

Tip: From expanded picture display, press the navigation key up or down to hide or display the Info Bar.

- **Thumbnail/Expand** to switch the display from full-screen to thumbnail view (up to nine pictures per screen).
- **Full Screen** to display the currently highlighted picture to the full screen view without any icons and info bar.
- **Go to Saved to Ph.** to access the Saved to Phone folder.
- **Go to Camera** to activate camera mode.

Note: **Save to Phone** and **Upload** copy pictures from your phone's In Camera folder to your Saved to Phone folder or your online Sprint PCS Picture Mail account. Pictures that have been stored to your Saved to Phone folder or uploaded to your online account will remain available in the In Camera folder until you erase them.

Note: If this is the first time you have accessed the Sprint PCS Picture Mail account, you will be prompted to create your Sprint PCS Picture Mail password. (See "Creating Your Sprint PCS Picture Mail Password" on page 160.)




Saved to Phone Folder

When you assign or download a picture, the picture will be saved automatically to the separate folder called “Saved to Phone.”

The Saved to Phone folder allows you to store copies of pictures on your phone and to assign pictures to various phone tasks.


To save a picture to the Saved to Phone folder:

1. From the In Camera folder (see “In Camera Folder” on page 168), select a picture you wish to save to the Saved to Phone folder and press . (You may select multiple pictures.)



Tip: If there is no selected picture, the currently highlighted picture will be selected.

2. Press **Options** (right softkey). (The In Camera folder options will display.)
3. Highlight **Save to Phone** and press . (A copy of the picture will be saved to the Saved to Phone folder.)

To view pictures stored in the Saved to Phone folder:

1. Press  to access the main menu.
2. Select **Picture&Video** and press .

Shortcut: Instead of steps 1 and 2 above, press .

3. Select **My Pictures** and press .
4. Select **Saved to Phone** and press . (Thumbnail pictures will display, up to nine pictures at a time.)
5. Use your navigation key to view and scroll through pictures.

Tip: To switch the thumbnail view and expanded view, press the left softkey.

Tip: From the expanded view, press and hold the navigation key right or left to display the stored picture continuously.


Saved to Phone Folder Options

From the Saved to Phone folder, press **Options** (right softkey) to display the following options. To select an option, highlight it and press **MENU OK**.

- **Set as Picture ID** to display the currently highlighted picture for incoming calls from a specific Contacts List entry.
- **Set as Scrn Saver** to display the currently highlighted picture as a screen saver. Select **Main LCD** or **Sub LCD** and press **MENU OK**.
- **Details/Edit** to display the currently highlighted picture's details or edit the pictures. You can select from **Text Caption**, **Picture Info**, **Color Tone**, or **Rotate Picture**.
- **Delete** to delete pictures stored in the Saved to Phone folder. Select **This Picture**, **Selected Pictures**, or **All Pictures**.
- **Sort by Date** to sort pictures by date. (Thumbnail picture only.) Select **Saved-Descending**, or **Saved-Ascending**.
- **Slideshow** to display your pictures as a slideshow. (Only appears when you have two or more pictures in the folder.)
- **Info Bar** to display information on the currently highlighted picture, such as folder name, picture number, caption, etc. (Expanded picture only.)
- **Full Screen** to display the currently highlighted picture to the full screen view without any icons and info bar.
- **Pics In Camera** to access the In Camera folder.
- **Go to Camera** to activate camera mode.

Note: Pictures may be assigned to more than one task.



Note: Assigned pictures will be identified with the  icon.







Taking Videos


In addition to taking pictures, you can also record, view, and send videos to your friends and family with your built-in camcorder.




To take a video with the flip open:

1. Press  to access the main menu.
2. Select **Picture&Video** and Press .

Shortcut: Instead of steps 1 and 2 above, press .

3. Select **Camcorder** and press  to activate video mode.
(Additional options are available through the video mode “Options” menu. See “Video Mode Options” on page 174 for more information.)
4. Using the phone’s main LCD as a viewfinder, aim the camera lens at your subject.
5. Press , , **Record** (left softkey), or the Side Camera key to start recording. (Maximum recording time is 30 seconds.)

Tip: To pause the recording, press  or **Pause** (left softkey).

6. Press , **Stop** (right softkey), or the Side Camera key to stop recording. (The picture will be saved automatically in your In Camcorder folder.)
 - To return to video mode to take another video, press .
7. Press **Next** (right softkey) for more options:
 - **Send Video** to send the video. (See page 185 for details.)
 - **Upload to Albums** to upload the video you just took to the Sprint PCS Picture Mail Website. Depending on your settings, you may be prompted to accept a Sprint PCS Vision connection.
 - **Set as Ringer** to display the video for incoming calls. Select **Voice Calls** or **Phone Book** and press .
 - **Go to Camcorder** to return to video mode to take another video.
 - **Videos In Camcord.** to go to the In Camcorder folder to review your saved videos.
 - **Playback** to play back the video you just took.
 - **Delete** to delete the video you just took.

To take a video with the flip closed:

1. Press and hold the side camera key to activate camera mode.
2. Press and hold the side camera key to activate video mode.
3. Point the camera lens at your subject. (You can check the video framing through the Sub LCD.)

Note: When taking a video with the phone closed, the subject image appears in reverse on the external display. The captured image will not be saved in reverse.

4. Press the side camera key to start recording. (Maximum recording time is 30 seconds.)
5. Press the Side Camera key to stop recording. (Your video will be saved automatically in the In Camcorder folder.)
 - Open the flip to review the video and for more options.

Note: While you are recording a video, the backlight turns on even if your backlight is set to **Always Off**.

Note: In some cases, the screen may flicker and the stripes may appear on the display under fluorescent lighting.

Video Mode Options

Several options are available from video mode.

Press **Options** (right softkey) to display additional options:



- **Video Light** to select a Video Light setting. Select **On** to light the Video Light while taking video.
- **Self-timer** to activate the camera's timer function. (See "Setting the Self-timer" on page 162 for details.)
- **Image Controls** to select an option from the following:
 - **Brightness** to select **Auto** or **Manual** brightness control. If you select **Manual**, press the navigation key right (increase) or left (decrease) to select a setting and press to apply the desired setting.
 - **White Balance** to adjust white balance based on changing conditions. Select from **Auto**, **Sunny**, **Cloudy**, **Tungsten**, **Fluorescent**, or **Manual**.

- **Camcord.Settings** to select **Resolution**, **Video Quality**, **Silent Movie**, **Cue Sound**, **Night Mode**, **Skin Frames**, or **Auto Delete**. (See “Selecting Camcorder Settings” on page 176 for details.)
- **Videos In Camcord.** to go to your phone’s In Camcorder folder. (See “In Camcorder Folder” on page 178 for details.)
- **Go to Camera** to switch to camera mode. (See “Taking Pictures” on page 159 for details.)
- **Key Guidance** to indicate the key functions in video mode.

Using the Zoom

This feature allows you to zoom in on an object when you record a video. Depending on your resolution settings, you can adjust the zoom from 1-step to 18-step.



To use the zoom:

1. From video mode, press the navigation key right or left, or the side volume key up or down to adjust the zoom. (The gauge bar appears.)
2. Press  to start recording.
3. Press  to stop recording. (The video will be saved automatically in your In Camcorder folder.)

Tip: The zoom function is also available while recording.

Selecting Camcorder Settings




To select your camcorder settings:

1. From video mode, press **Options** (right softkey).
2. Highlight **Camcord.Settings** and press .
3. Select an option from the following and press .
 - **Resolution** to select a file size (**Good**, or **Medium**) for a video.
 - **Video Quality** to select Video quality from **Economy**, **Normal**, or **Rich**.
 - **Silent Movie** to select **On** to record without sounds. Select **Off** to deactivate this feature.
 - **Cue Sound** to select a cue sound. (See “Setting the Cue Sound” below for details.)
 - **Night Mode** to take videos in low light.
 - **Skin Frames** to select your favorite frame from **Movie Border** or **Line Border**. (This option doesn’t appear when Resolution setting is Good.)
 - **Auto Delete** to set auto delete. (See “Setting Auto Delete” on page 166 for details.)


Note: Recording time varies depending on the Video Quality.
(**Economy:** 30 seconds, **Normal:** 20 seconds, **Rich:** 15 seconds.)

Setting the Cue Sound

To select the Cue Sound:

1. From video mode, press **Options** (right softkey).
2. Highlight **Camcord.Settings** and press .
3. Select **Cue Sound** and press .
4. Select an option from the following and press .
 - **Default** plays the default cue sound.
 - **“Action & Cut”** notifies you with the pre-recorded words.
 - **Off** makes no sound.

Viewing Your Video's Status Area Display



Video Icon Indication

No.	Function		Icons	Details
1	Video Light			Appears when the Video Light setting is On.
2	White Balance		Same as Camera Status Area. (See page 167 for details.)	
3	Brightness	Manual		For the manual setting of brightness.
4	Night Mode			Use this setting in low light.
5	Recording Gauge			For displaying the recording time.
6	Resolution	Good		For good picture resolution.
		Medium		For medium picture resolution.
7	Memory Gauge			Shows the remaining memory.
8	Picture Number		100%	The number of stored pictures.
	Remaining Pictures		/100	The amount of videos you can take with current resolution.
9	Self-timer		5s	Numeric countdown will appear during the self-timer countdown.
10	Elapsed Time Display			For displaying the elapsed time of recording.

Storing Videos in My Videos





My Videos is your phone's picture storage area. Same as My Pictures, there are two types of folders in My Videos that can be used separately according to your needs. They are:

- In Camcorder (see below)
- Saved to Phone (see page 181)

In Camcorder Folder

Once a video is taken, it is automatically saved to the folder called "In Camcorder." From the In Camcorder folder, you can view all the videos you have recorded, store selected images in your phone, send videos to the Sprint PCS Picture Mail Website, delete images, and access additional video options.

To review your stored videos in the In Camcorder folder:


1. Press  to access the main menu.
2. Select **Picture&Video** and Press .
3. Select **My Videos** and press .
4. Select **In Camcorder** and press . (Thumbnail videos will display, up to nine videos at a time.)
5. Use your navigation key to view and scroll through videos.
6. Press **Play** (left softkey) to play the video.

Tip: Press the Side Volume key up or down to adjust the video volume while playing or pausing a video.




In Camcorder Folder Options

When you are in the In Camcorder folder, several options are available.

Press **Options** (right softkey) to display the following options:

- **Send Video** to send video files. See page 185 for details.
- **Upload to Albums** to select an option from the following to upload videos saved in the In Camcorder folder to the Sprint PCS Picture Mail Website. Depending on your settings, you may be prompted to accept a Sprint PCS Vision connection.
 - **This Video** to upload the currently highlighted video.
 - **Selected Videos** to upload the selected videos. Press  to select a video (the check box on the lower right corner will be marked).
 - **All Videos** to upload all the videos in the In Camcorder folder.

Note: Erasing videos will free up memory space in your phone to enable you to take more videos. Once erased, videos cannot be uploaded to your online Sprint PCS Picture Mail account or saved to the Saved to Phone folder.

- **Set as Ringer** to display the currently highlighted video for incoming calls from a specific Contacts List entry. Select an option from the following and press .
- **Voice Calls** to display the video for incoming calls. Select **With Caller ID** or **No Caller ID** and press .
- **Phone Book** to display the video for incoming calls from a specific Contacts list entry. Select your desired entry and press .
- **Details/Edit** to select an option from the following:
 - **Text Caption** to edit the caption of a currently highlighted video.
 - **Video Info** to display information on the currently highlighted video, such as caption, time/date, size, etc.
- **Delete** to delete videos in the In Camcorder folder. Select **This Video**, **Selected Videos**, or **All Videos**.
- **Save to Phone** to save the selected videos in the Saved to Phone folder.
- **Sort by Date** to sort videos by date. (Thumbnail picture only.) Select **Taken-Descending**, **Taken-Ascending**, **Uploaded-Descend**, or **Uploaded-Ascend**.


- **Thumbnail/Expand** to switch the display from full-screen to thumbnail view (up to nine pictures per screen).

Tip: You can also switch the thumbnail view to the expanded display by pressing and holding **MENU OK**. To go back to thumbnail view, press **BACK**.

- **Go to Saved to Ph.** to access the Saved to Phone folder.
- **Go to Camcorder** to activate video mode.

Note: **Upload to Albums** and **Save to Phone** copy videos from your phone's In Camcorder folder to your Saved to Phone folder or your online Sprint PCS Picture Mail account. Pictures that have been stored to your Saved to Phone folder or uploaded to your online account will remain available in the In Camera folder until you erase them.

Note: If this is the first time you have accessed the Sprint PCS Picture Mail account, you will be prompted to create your Sprint PCS Picture Mail password. (See "Creating Your Sprint PCS Picture Mail Password" on page 160.)




Saved to Phone Folder (Video)


When you assign or download a video, the video will be saved automatically to the separate folder called “Saved to Phone.”

The Saved to Phone folder allows you to store copies of videos on your phone and to assign videos to various phone tasks.





To save a video to the Saved to Phone folder:

1. From the In Camcorder folder (see “In Camcorder Folder” on page 178), select a video you wish to save to the Saved to Phone folder and press . (You may select multiple videos.)


Tip: If there is no selected video, the currently highlighted video will be selected.

2. Press **Options** (right softkey). (The In Camcorder folder options will display.)
3. Highlight **Save to Phone** and press . (A copy of the video will be saved to the Saved to Phone folder.)

To play videos stored in the Saved to Phone folder:

1. Press  to access the main menu.
2. Select **Picture&Video** and press .
3. Select **My Videos** and press .
4. Select **Saved to Phone** and press . (Thumbnail pictures will display, up to nine videos at a time.)
5. Use your navigation key to view and scroll through videos.
6. Press **Play** (left softkey) to play the selected videos.


Saved to Phone Folder Options (Video)

From the Saved to Phone folder, press **Options** (right softkey) to display the following options. To select an option, highlight it and press .

- **Set as Ringer** to display the currently highlighted video for incoming calls from a specific Contacts List entry. Select **Voice Calls** or **Phone Book**.
- **Details/Edit** to display the currently highlighted video's details or edit the pictures. You can select from **Text Caption** or **Video Info**.
- **Delete** to delete videos stored in the Saved to Phone folder. Select **This Video**, **Selected Videos**, or **All Videos**.
- **Sort by Date** to sort videos by date. (Thumbnail picture only.) Select **Saved-Descending** or **Saved-Ascending**.
- **Thumbnail/Expand** to switch the display from full-screen to thumbnail view (up to nine pictures per screen).
- **Videos in Camcorder**. to access the In Camcorder folder.
- **Go to Camcorder** to activate video mode.

Note: Videos may be assigned to more than one task.

Note: Assigned videos will be identified with the  icon.







Sending Sprint PCS Picture Mail and Sprint PCS Video Mail

Once you've taken a picture or a video, you can use the messaging capabilities of your wireless phone to instantly send it to family and friends. You can send pictures and videos to up to ten people at a time using their email addresses or their wireless phone numbers.

Sending Pictures From the In Camera Folder


To send pictures from the In Camera folder:


1. Press  to access the Picture & Video menu.
2. Select **My Pictures** and press .
3. Select **In Camera** and press .
4. Highlight a picture you wish to send and press  to select a picture. (The check box on the lower right corner will be marked. You can select multiple pictures.)


Tip: If there is no selected picture, the currently highlighted picture will be selected.




5. Press **Send** (left softkey). (You will see messages on the display.)

Note: The first time you send Sprint PCS Picture Mail, you will be prompted to establish a Sprint PCS Picture Mail Website account and password. (See "Creating Your Sprint PCS Picture Mail Password" on page 160.)

6. Press the left softkey to continue.
7. Select **Recipients** and press .

8. Select an option from the following and press .

- **Phone Book Entry** to select recipients from your Contacts list. Highlight a recipient and press  to select.
- **Mobile Phone#** to enter a mobile phone number directly.
- **Email Address** to enter an email address directly.
- **From Recent List** to select from a list of recent Sprint PCS Picture Mail or messaging recipients.





Note: The  and  icons next to contact's names represent Mobile Phone and email. When entering a new contact, use your navigation key to select the correct icon for the entry. You can also select both the mobile phone number and email address at once by selecting  icon.

9. Press **Next** (left softkey) when you are finished selecting and entering recipients. (You may include up to ten recipients per message.)
10. Follow the onscreen instructions to add available options.
11. To send the picture, press the appropriate softkey.



Tip: When you send a picture from the In Camera folder, you can also attach videos from the In Camcorder folder. To attach videos, highlight the box next to **Videos** and press the appropriate softkey.

Sending Videos From the In Camcorder Folder

To send videos from the In Camcorder folder:

1. Press  to access the Picture & Video menu.
2. Select **My Videos** and press .
3. Select **In Camcorder** and press .
4. Press  to select a video. (The check box on the lower right corner will be marked. You can select multiple videos.)



Tip: If there is no selected video, the currently highlighted video will be selected.

5. Press **Options** (right softkey), select **Send Video**, and press .
6. To complete and send the Sprint PCS Video Mail, follow steps 6-11 in “Sending Pictures From the In Camera Folder” on page 183.
 - To change the attached videos, select the thumbnail video using your navigation key and press the appropriate softkey. Select **From My Videos** or **Take Video** and press . After selecting, press **Next** (left softkey).





Sending Sprint PCS Picture Mail From Messaging



You can also send your Sprint PCS Picture Mail from your phone's Messaging menu.

To send pictures from the Messaging menu:

1. Press  to access the main menu.
2. Select **Messaging** and press  to access the Messaging menu.

Shortcut: Press the navigation key up from standby mode to access the Messaging menu.

3. Select **Send Message** and press .
– or –
Select **PictureMail**, press , select **<Send Message>**, and press .
4. Select **Picture** and press .




5. Select **From My Pics.** and press . (The In Camera folder will display, up to nine thumbnail pictures per screen.)
6. Use the navigation key to display the picture you wish to send and press . (You can select multiple pictures.)

Tip: To expand a selected picture from thumbnail to full-screen, press and hold .

7. Press **Next** (left softkey). To complete and send the Sprint PCS Picture Mail, follow steps 6-11 in “Sending Pictures From the In Camera Folder” on page 183.

Tip: If you want to take a new picture and send it, select **Take Picture** during step 5 above. Take a new picture, press **Next** (right softkey) and follow steps 6-11 in “Sending Pictures From the In Camera Folder” on page 183.

To send videos from the Messaging menu:






1. Follow steps 1-3 on the previous page.
2. Select **Video** and press .
3. Select **From My Videos** and press . (The In Camcorder folder will display, up to nine thumbnail videos per screen.)
4. Use the navigation key to display the video you wish to send and press . (You can select multiple videos.)
5. Press **Next** (right softkey). (To complete and send the Sprint PCS Video Mail, follow steps 6-11 in “Sending Pictures From the In Camera Folder” on page 183.)

Tip: If you want to take a new video and send it, select **Take Video** during step 3 above. Take a new video, press **Next** (right softkey) and follow steps 6-11 in “Sending Pictures From the In Camera Folder” on page 183.

Sending to Various Destinations

With your SCP-7400, you can select various destinations such as picture printing service or photo sharing service. The destinations will be downloaded to your phone automatically the first time you access the Sprint PCS Picture Mail account.

To select the destination:

1. Press  to access the Picture & Video menu.
2. Select **My Pictures** and press .
3. Select **In Camera** and press .
4. Highlight a picture you wish to send and press  to select a picture.
5. Press **Send** (left softkey).
6. Select the destination you want to and press .
 - Select **Update** to update your destination list.
7. Follow the onscreen instructions to complete the process.

Note: Depending on the destination, the items you can send will vary. A caution will be displayed when you select the item you cannot send. Follow the caution to complete the process.

Tip: The destination list may also appear in the Picture & Video menu.

Managing Sprint PCS Picture Mail

Using the Sprint PCS Picture Mail Website

Once you have uploaded pictures and videos from your phone to your online Sprint PCS Picture Mail account (see “In Camera Folder” on page 168), you can use your personal computer to manage your uploaded data. From the Sprint PCS Picture Mail Website you can send pictures and videos, organize and move images, and do much more.

You will also have access to picture management tools to improve and customize your pictures. You’ll be able to lighten, darken, crop, add antique effects, add comic bubbles and cartoon effects, and use other features to transform your pictures.



To access the Sprint PCS Picture Mail Website:

1. From your computer’s Internet connection, go to <http://pictures.qwest.com>.
2. Enter your wireless phone number and Sprint PCS Picture Mail password to sign on. (See “Creating Your Sprint PCS Picture Mail Password” on page 160.)





Managing Online Pictures From Your Phone

You can use your phone to manage, edit, or send pictures and videos you have uploaded to the Sprint PCS Picture Mail Website. (See “In Camera Folder Options” on page 168 and “In Camcorder Folder Options” on page 179 for information about uploading.)

To view your online pictures from your phone:

1. Press  to access the main menu.
2. Select **Picture&Video** and press .

Shortcut: Instead of steps 1 and 2 above, press .








3. Select **Online Albums** and press .
4. Select **View Albums** and press . (Depending on your settings you may be prompted to accept a Sprint PCS Vision connection. The My Uploads folder and your albums appear.)
5. Select **My Uploads** or an album title and press .
6. Highlight **Picture** or **Video** and press . (Thumbnail pictures or videos, up to nine per screen are displayed.)

Tip: To expand a selected picture or video from thumbnail to full-screen, press and hold .






7. Use your navigation key to select a picture or video.

Uploading Your Pictures and Videos

To upload pictures:

1. Press  to access the Picture & Video menu.
2. Select **Online Albums** and press .
3. Select **Upload Pics** and press .
4. Select pictures and press **Upload** (left softkey).
5. Highlight **This Picture**, **Selected Pictures**, or **All Pictures** and press .
6. Highlight **My Uploads** and press 
– or –
Highlight **Other Albums**, press  and then select your desired album and press .



To upload videos:

1. Follow steps 1 and 2 above.
2. Select **Upload Videos** and press .
3. Select videos and press **Upload** (left softkey).
4. Highlight **This Video**, **Selected Videos**, or **All Videos** and press .
5. Highlight **My Uploads** and press 
– or –
Highlight **Other Albums**, press , and then select your desired album and press .

Downloading Your Online Pictures



From the Sprint PCS Picture Mail Website, you can download the selected picture or video to the Saved to Phone folder. In addition to downloading, you can assign the picture or video to several phone tasks.

To download pictures:

1. From the online picture display, select a picture you wish to download and press **Options** (right softkey). (See “Managing Online Pictures From Your Phone” on page 189.)
2. Highlight **Save to Phone** and press .
3. Select an option from the following and press .

 - **Set as Picture ID** to download and assign the currently highlighted picture to Picture ID.
 - **Set as Scrn Saver** to download and assign the currently highlighted picture to screen saver.
 - **Download Only** to only download the pictures to the Saved to Phone folder.




To download videos:

1. From the online video display, select a video you wish to download and press **Options** (right softkey). (See “Managing Online Pictures From Your Phone” on page 189.)
2. Highlight **Save to Phone** and press .
3. Select an option from the following and press .


 - **Set as Ringer** to download and assign the currently highlighted video to voice calls or a Contacts entry.
 - **Download Only** to only download the videos to the Saved to Phone folder.

Sending Online Sprint PCS Picture Mail

To send pictures from the online Address Book:

1. From the online picture display, select a picture you wish to send and press **Send** (left softkey). (See “Managing Online Pictures From Your Phone” on page 189.)
2. Highlight **Recipients** and press .
3. Highlight **Online Addr. Book** and press .
4. To select a recipient, highlight a recipient and press . (You may select up to 10 recipients.)
5. Press **Done** (left softkey) when you are finished selecting recipients.
6. Follow the onscreen instructions to add available options.
7. Confirm the recipients and attached data.
8. Press the appropriate softkey to send your Sprint PCS Picture Mail.

To send videos from the online Address Book:

1. From the online video display, select a video you wish to send and press **Options** (right softkey). (See “Managing Online Pictures From Your Phone” on page 189.)
2. Highlight **Send Video** and press .
3. To complete and send the Sprint PCS Video Mail, follow steps 2-8 above.


Tip: When you send pictures and videos from the Sprint PCS Picture Mail Website, you can also attach pictures and videos from the Website. To attach another picture or video file, highlight the box next to **Pictures** or **Videos** and press the appropriate softkey.

To send an album from online mode:

1. From the online Albums display, select an album you wish to send and press **Send** (left softkey). (See “Managing Online Pictures From Your Phone” on page 189.)
2. Follow steps 2-8 in “To send pictures from the online Address Book” on page 192 to complete and send your Sprint PCS Picture Mail.

Accessing Online Picture Options From Your Phone

To access your online pictures options from your phone:

1. Select a picture from your online display (see “Managing Online Pictures From Your Phone” on page 189).
2. Press **Options** (right softkey) to display options.
3. To select an option, highlight it and press .
 - **Copy/Move** to copy or move pictures to a selected album:
 - Move This** to move the currently highlighted picture to the album.
 - Move Selection** to move the selected pictures to the album.
 - Move All** to move all pictures in the current album (or My Uploads) to the target album.
 - Copy This** to copy the currently highlighted picture to the album.
 - Copy Selection** to copy the selected pictures to the album.
 - Copy All** to copy all pictures in the current album (or My Uploads) to the target album.

Tip: Press **New** (right softkey) to copy/move pictures to a new folder.

- **Details/Edit** to display the details of currently highlighted picture or edit the picture. Select from **Text Caption**, **Picture Info**, or **Rotate Picture**.
- **Delete** to erase pictures saved in the current album (or My Uploads). Select **This Picture**, **Selected Pictures**, or **All Pictures**.
- **Save to Phone** to download to the Saved to Phone folder to assign the pictures to the phone task. Select from **Set as Picture ID**, **Set as Scrn Saver**, or **Download Only**.

- **Info Bar** to display picture's information, such as folder name, picture number, caption, etc. Select **On** to display the information. (Expanded picture only.)

Tip: From expanded picture display, press the navigation key up or down to hide or display the Info Bar.

- **Thumbnail/Expand** to switch the display from thumbnail view (up to nine pictures per screen) to full-screen.


Tip: You can also switch the thumbnail view to the expanded display by pressing and holding . To go back to thumbnail view, press **BACK**.

- **Create Album** to create a new album (from My Uploads only). Enter the album name and select **Save** (left softkey).
- **Online Albums** to switch the display to the online album list.

To access your online videos options from your phone:

1. Select a video from your online display (see “Managing Online Pictures From Your Phone” on page 189).
2. Press **Options** (right softkey) to display options.
3. To select an option, highlight it and press .
 - **Send Video** to send videos. (See “Sending Videos From the In Camcorder Folder” on the page 185 for details.)
 - **Copy/Move** to copy or move videos to a selected album. Select from **Move This**, **Move Selection**, **Move All**, **Copy This**, **Copy Selection**, or **Copy All**.
 - **Details/Edit** to display the details of currently highlighted video or edit the video. Select from **Text Caption** or **Video Info**.
 - **Delete** to erase videos saved in the current album (or My Uploads). Select from **This Video**, **Selected Videos**, or **All Videos**.
 - **Save to Phone** to download to the Saved to Phone folder to assign videos to the phone task. Select from **Set as Ringer**, or **Download Only**.
 - **Thumbnail/Expand** to switch the display from thumbnail view (up to nine videos per screen) to full-screen.
 - **Create Album** to create a new album (from My Uploads only). Enter the album name and select **Save** (left softkey).
 - **Online Albums** to switch the display to the online album list.

To access your online albums options from your phone:

1. Display the album list in the online Sprint PCS Picture Mail menu (see “Managing Online Pictures From Your Phone” on page 189).
2. Use your navigation key to select an album (or My Uploads).
3. Press **Options** (right softkey) to display options.
4. To select an option, highlight it and press .
 - **Create Album** to create a new album. Enter a new album name and press **Save** (left softkey).
 - **Delete Album** to delete the selected album.
 - **Rename Album** to rename the selected album. Enter a new name and press **Save** (left softkey).

Note: My Uploads cannot be erased or renamed.

- **Album Info** to display album information: name, created time/date, and the number of stored pictures and videos.

Using Your Phone's Built-in Media Player

In This Section

- ◆ **Your Multimedia Channel Options**
 - ◆ **Accessing Your Media Player's Channel Listings**
 - ◆ **Playing a Video or Audio Clip**
 - ◆ **Multimedia FAQs**
-

Your wireless phone's built-in media player gives you the ability to listen to audio clips and view video clips right from your phone's display. It's a great way to stay up-to-date with news, weather, and sports information while also providing entertainment with the latest blockbuster movie trailers or music videos – anywhere, anytime on the network provided to you. Just access your media player from your phone's main menu, scroll to your choice of channel, and select one of the video or audio clips to play. It's like having a TV in the palm of your hand.

This section explains the features and options of your phone's built-in media player.

Your Multimedia Channel Options



Multimedia Service offers a variety of accessible audio or video channels, depending on your Service Plan and multimedia subscriptions. Your subscription options include a comprehensive basic service as well as a full menu of a variety of additional channel options.

- **Preview Channel:** This free channel lets you sample clips from all of the available channels before you make a decision to subscribe. It's like viewing the movie preview before deciding whether you want to spend the money to go see the full motion picture.
- **Sprint TV:** This comprehensive basic service gives you access to a variety of content from familiar brands. Think of it as "basic cable" for your phone. It allows you unlimited access to this content as long as you continue to pay the monthly subscription fee.
- **Available Individual Channel Options:** You also have the option of subscribing to individual channels from an extensive menu offering. These channels are available for a monthly subscription fee and allow you unlimited access as long as you continue to pay your monthly subscription fee.

Accessing Your Media Player's Channel Listings





It's easy to access and view the multimedia Channel Listings on your Sanyo SCP-7400 from the phone's main menu.

To access your media player and Channel Listings:

1. Press  from standby mode to display the phone's main menu.
2. Select **Media Player** and press . (Your **Channel Listing** will display, divided into the following two sections:)
 - **My Channels:** These include the complimentary Previews channel that Sprint provides, as well as any available individual channels for which you have purchased access. If you have purchased Sprint TV, either through a Sprint TV Vision Plan subscription or by purchasing it separately, it will be displayed here.
 - **Available Channels:** These are channels that have not yet been purchased but are available to access for a monthly subscription fee. Use your navigation key to scroll through and select a channel, and follow the onscreen instructions to purchase access to it. Upon purchasing access to one of these channels, the channel will be listed, along with its corresponding channel number, in the **My Channels** section of your media player's Channel Listings. You will see it displayed in this section the next time you access your phone's media player.

Playing a Video or Audio Clip

To access your media player and Channel Listings:


1. Press  from standby mode to display the phone's main menu.
2. Select **Media Player** and press  to display your Channel Listings.
3. Use your keypad to enter a channel number (or use your navigation key to scroll to a channel and press ).
 - **My Channels:** If you have selected a channel that you've already signed up for (or if it's a channel with no monthly fee), you will see a list of available clips.
 - **Available Channels:** If you have selected a channel you have not yet signed up for, you will be prompted to accept the corresponding monthly charge. Follow the onscreen prompts to subscribe to the selected channel. (A list of available clips will display.)
4. Scroll to the clip you would like to play and press **Select** (left softkey) or . (The clip will automatically load and begin playing.)
 - Press **Options** (right softkey) to display several options (see page 201 for details).

Tip: To change the volume of video or audio, press the Side Volume key up or down.

Tip: To play another clip, press the navigation key up or down, or press your desired channel number with your keypad while playing the clip.





To play a clip from the browser:

You can play a clip from a URL in the browser (if available).

1. Press **Web** (right softkey) to launch the browser.
2. Select the page that includes URLs.
3. Select your desired URL and press .


To play a clip in a text message:

You can play a clip in the text message that includes the URL (if available).

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Text Msgs** and press .
4. Select **Inbox** or your defined folder, and press .
5. Select the message that includes URLs.
6. Select your desired URL and press **Go** (left softkey) to play the video or audio clip.
7. Follow the onscreen prompt to play the clip.




Tip: To switch the speakerphone on or off, press  while playing a clip.

Multimedia Options

While using the Multimedia Player, several options are available. To select an option, press **Options** (right softkey), highlight it and press .

- **Channel Listing** to display the channel list.
- **Online Catalog** to display online catalogs (if available).
- **Info** to display channel information (if available).
- **Player Settings** to select frames to display while playing clips.
Select from **Audio Skins** or **Skin Frames** (only appears while you are in the channel list).
- **Help** to see the Multimedia instruction page.

Note: The first time you access one of your **Available Channels**, you will be prompted to accept the corresponding monthly fee (unless it's a channel that doesn't have an associated monthly fee). Accepting the charge gives you access to the channel for as long as you continue to pay the monthly fee. If you accept the fee, the next time you access your phone's media player, this channel will appear in the **My Channels** section of your Channel Listings.

Note: The icons next to channel numbers indicate types of channels. Press  to play an audio clip, or press  to play a video clip.  appears if the channel has two or more clips.

Tip: When entering the specific channel number, channels 01 - 09 do not require you to enter a "0." For example, to access channel "07," just press the "7" key.

Multimedia FAQs

1. How does my phone's Multimedia Service differ from Video Mail?

Multimedia Service lets you access high-quality video and audio clips provided by external sources. Video Mail lets you capture, upload and share videos that you personally create with your phone's built-in camcorder.

2. How am I charged for Multimedia Service?

Sprint PCS Vision Plan:

- With a Sprint PCS Vision Plan, you can play an unlimited number of video/audio clips on your phone's display as long as you've subscribed to a channel (see next bullet). You also receive access to the Previews channel as a courtesy from Sprint. It doesn't cost you anything to play the clips, but you will need to pay a monthly fee for any channel subscriptions (see the following bullet).
- In addition to complimentary access to the Previews channel, you can subscribe to any of the channels listed in the Available Channels section of your Channel Listings for an additional monthly fee. Clips within these channels will continue to be available to you as long as you continue to pay your monthly channel subscription fee.

3. Will I know if I'm receiving an incoming call while I'm viewing or listening to an audio clip?

Yes. Incoming calls will roll into voicemail while you are playing a clip. If the caller leaves a voicemail, the voicemail icon will appear on the screen.

4. How long are the clips? Will I know the estimated time it will take to play the clip prior to accessing it?

Once you have selected a channel, you will see a listing of the available clips, with the clip's length appearing after the clip's title (if available). In general, a clip's duration will depend on the story or content being provided, and can be fairly short or as long as a few minutes.

5. Can I access a multimedia clip wherever I am, as long as I have my phone?

As long as you are on the network provided to you, you will have access to the audio and video clips.

Note: Multimedia Service does not work while roaming off of the network provided to you or where service is unavailable.

6. Are the videos that I'm viewing "live" videos?

No. This service provides videos on demand. The video and audio clips are refreshed throughout the day, but they are not "live."

7. After purchasing access to an Available Channel for a monthly fee, do I receive any confirmation? That is, how do I know it has been purchased?

The next time you access your media player's Channel Listings, the purchased channel title and corresponding number will appear in the **My Channels** section.

8. Why are some channels already pre-loaded into the My Channels section?

Some channels, such as Previews, are offered free of charge as a customer courtesy. These channels automatically appear in the **My Channels** section of your Channel Listings.

9. If I don't subscribe to Sprint PCS Vision Plan, am I still able to view the multimedia clips?

No.

10. How can I easily access a channel without having to scroll through all the channels in my Channel Listings?

Each channel will have a number to the left of it. You can simply press this number to quickly access the clips located within that channel.

Tip: When entering the specific channel number, channels 01 - 09 do not require you to enter a "0." For example, to access channel "07," just press the "7" key.

11. What does it mean when the video pauses and I see the word “loading” at the bottom of the screen?

This happens when the media player is in the process of loading the data necessary to play the clip. It typically occurs when there is heavy traffic on the network.


12. How can I cancel service if I decide I don’t want it?

To cancel your Multimedia Service, contact your service provider.

13. If I place my stereo headphones on and insert them into the phone’s headset jack, can I close the flip while I am playing an audio (or video) clip without interrupting the clip?

Yes. When you insert your stereo headset into the phone’s headset jack, the phone automatically goes into “headset mode,” allowing you to close the flip and continue playing the clip (likewise, if your phone is in “headset mode,” a phone call will not become disconnected by closing the flip).

14. Can I surf to a different channel while I am playing a clip?

Yes; while you are playing a clip, you can use the up and down navigation keys to surf to a different channel. A small pop-up screen will appear that tells you which channel you are watching as well as other channels you have access to. Use the navigation keys to scroll through the different channels. Once you find a channel that you want to watch, scroll to it and press  (or simply wait approximately 3 seconds) and the channel will begin loading.

Qwest® Service Features

Qwest® Service Features: The Basics

In This Section

- ◆ Using Voicemail
 - ◆ Using Caller ID
 - ◆ Responding to Call Waiting
 - ◆ Making a Three-Way Call
 - ◆ Using Call Forwarding
-


Now that you've mastered your phone's fundamentals, it's time to explore the calling features that enhance your wireless service. This section outlines your basic Qwest Service features.

Using Voicemail

Setting Up Your Voicemail

All unanswered calls to your wireless phone are automatically transferred to your voicemail, even if your phone is in use or turned off. Therefore, you will want to set up your voicemail and personal greeting as soon as your phone is activated.


To set up your voicemail:

1. Press and hold .
2. Follow the system prompts to:
 - Create your passcode
 - Record your greeting
 - Record your name announcement
 - Choose whether or not to activate One-Touch Message Access (a feature that lets you access messages and bypassing the need for you to enter your passcode)

Note: The voicemail setup process may vary in certain Affiliate areas.

Voicemail Notification

There are several ways your phone alerts you of a new message:

- By displaying a message on the screen.
- By sounding the assigned ringer type.
- By the LED blinking red.
- By displaying the  icon at the top of your screen.

Tip: If you have two or more notifications, the event list will appear.

New Voicemail Message Alerts

When you receive a new voice message, your phone alerts you and prompts you to call your voicemail.

To call your voicemail:

- ▶ Press **TALK**.

To display your Missed Log:

- ▶ Press **Events** (right softkey).

Important: When you are roaming off the network provided to you, you may not receive notification of new voicemail messages. It is recommended that you periodically check your voicemail by dialing 1 + area code + your wireless phone number. When your voicemail answers, press **✖** and enter your passcode. You will be charged roaming rates when accessing voicemail while roaming off the network provided to you.

Note: Your phone accepts messages even when it is turned off. However, you are only notified of new messages when your phone is turned on. You may not receive new messages when roaming outside of the network provided to you.

Retrieving Your Voicemail Messages

You can review your messages directly from your wireless phone or from any other touch-tone phone. To dial from your wireless phone, you can either speed dial your voicemail or use the menu keys.

Using One-Touch Message Access

- ▶ Press and hold **1**. (Your phone will dial your voicemail box.)

Using the Menu Keys on Your Phone to Access Your Messages

1. Press **MENU OK** to access the main menu.
2. Select **Messaging** and press **MENU OK**.
3. Select **Voicemail** and press **MENU OK**.
4. Select **Call Voicemail** or **Call:Speaker On**, and press **MENU OK**.

Note: You are charged for airtime minutes when you are accessing your voicemail from your wireless phone.

Using a Phone Other Than Your Wireless Phone to Access Messages

1. Dial your wireless phone number.
2. When your voicemail answers, press **✕**.
3. Enter your passcode.

Tip: When you call into voicemail you first hear the header information (date, time, and sender information) for the message. To skip directly to the message, press **4** during the header.

Voicemail Button Guide

Here's a quick guide to your keypad functions while listening to voicemail messages. For further details and menu options, see "Voicemail Menu Key" on page 213.

1	2	3
Date/Time	Send Reply	Advance
4	5	6
Replay	Rewind	Forward
7	8	9
Erase	Call Back	Save
✕	0	#
Cancel	Help	Skip

Vicemail Options

Your phone offers several options for organizing and accessing your voicemail.

Using Expert Mode

Using the Expert Mode setting for your personal voicemail box helps you navigate through the voicemail system more quickly by shortening the voice prompts you hear at each level.

To turn Expert Mode on or off:

1. Press and hold **☒1** to access your voicemail. (If your voicemail box contains any new or saved messages, press **✕** to access the main voicemail menu.)
2. Press **3** to change your Personal Options, following the system prompts.
3. Press **4** for Expert Mode.
4. Press **1** to turn Expert Mode on or off.

Setting Up Group Distribution Lists

Create up to 20 separate group lists, each with up to 20 customers.

1. Press and hold **☒1** to access your voicemail. (If your voicemail box contains any new or saved messages, press **✕** to access the main voicemail menu.)
2. Press **3** to change your Personal Options, following the system prompts.
3. Press **2** for Administrative Options.
4. Press **5** for Group Distribution Lists.
5. Follow the voice prompts to create, edit, rename, or delete group lists.

Callback

Return a call after listening to a message without disconnecting from voicemail.

- ▶ Press **8** after listening to a message. (Once the call is complete, you're returned to the voicemail main menu.)

Voicemail-to-Voicemail Message

Record and send a voice message to other voicemail users.

1. From the main voicemail menu, press **2** to send a message.
2. Follow the voice prompts to enter the phone number.
3. Follow the voice prompts to record and send your voice message.

Voicemail-to-Voicemail Message Reply

Reply to a voice message received from any other voicemail user.

1. After listening to a voice message, press **2**.
2. Follow the voice prompts to record and send your reply.

Voicemail-to-Voicemail Message Forwarding

Forward a voice message, except those marked “Private,” to other voicemail users.

1. After listening to a message, press **6**.
2. Follow the voice prompts to enter the phone number.
3. Follow the voice prompts to record your introduction and forward the voice message.

Voicemail-to-Voicemail Receipt Request

Receive confirmation that your voice message has been listened to when you send, forward, or reply to other voicemail users.

1. After you have recorded a message, press **1** to indicate you are satisfied with the message you recorded.
2. Press **4** to mark receipt requested.
3. Press **1** to send your voicemail message.

Continue Recording

When leaving a voice message, you can choose to continue recording even after you've stopped.

- ▶ Before pressing **1** to indicate that you are satisfied with the message you recorded, press **4** to continue recording.

Extended Absence Greeting






When your phone is turned off or you are off the network provided to you for an extended period, this greeting can be played instead of your normal personal greeting.

1. From the main voicemail menu, press **3** for Personal Options.
2. Press **3** for Greetings.
3. Press **3** to record an Extended Absence Greeting.

Clearing the Message Icon

Your phone may temporarily continue to display the message icon after you have checked your voice and text messages.





To clear the icon from the display screen:

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Voicemail** and press .
4. Select **Clear Count** and press .
5. Select **Yes** and press .

Displaying Your Voicemail Details

This feature allows you to show the number of new voicemail messages and the time you received the voicemail notification.

To display your voicemail details:

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Voicemail** and press .
4. Select **Details** and press .

Vicemail Menu Key

Following the prompts on the voicemail system, you can use your keypad to navigate through the voicemail menu. The following list outlines your phone's voicemail menu structure.

- 1** Listen
 - 1** Envelope Information
 - 2** Reply
 - 3** Advance 8 Seconds
 - 4** Replay
 - 5** Rewind
 - 6** Forward Message
 - 7** Erase
 - 8** Callback
 - 9** Save
 - 0** Options
- 2** Send a Message
- 3** Personal Options
 - 1** Notification Options
 - 1** Phone Notification
 - 2** Numeric Paging to a Wireless Phone
 - ✕** Return to Personal Options Menu
 - 2** Administrative Options
 - 1** Skip Pass code
 - 2** Autoplay
 - 3** Message Date & Time On/Off
 - 4** Change Pass code
 - 5** Group Distribution List
 - ✕** Return to Personal Options Menu
 - 3** Greetings
 - 1** Personal Greetings
 - 2** Name Announcement
 - 3** Extended Absence Greeting
 - ✕** Return to Personal Options Menu
 - 4** Expert Mode (On/Off)
- 8** Place a Call
- ✕** Disconnect

Using Caller ID

Caller ID allows people to identify a caller before answering the phone by displaying the number of the incoming call. If you do not want your number displayed when you place a call, just follow these easy steps.

To block your phone number from being displayed for a specific outgoing call:

1. Press **✕** **6** **7**.
2. Enter the number you want to call.
3. Press **TALK**.

To permanently block your number, call Qwest Wireless™ Repair at 1-877-879-0611.

Responding to Call Waiting

When you're on a call, Call Waiting alerts you of incoming calls by sounding one beep. Your phone's screen informs you that another call is coming in and displays the caller's phone number. (This feature may not be available while you are in analog area.)

To respond to an incoming call while you're on a call:

- ▶ Press **TALK** (or press **Options** [right softkey], highlight **Flash**, and press **MENU OK**). (This puts the first caller on hold and answers the second call.)

Tip: Press **Ignore** (left softkey) when you do not want to answer the call.

To switch back to the first caller:

- ▶ Press **TALK** again (or press **Options** [right softkey], highlight **Flash**, and press **MENU OK**).

Tip: For those calls where you don't want to be interrupted, you can temporarily disable Call Waiting by pressing **✕** **7** **0** before placing your call. Call Waiting is automatically reactivated once you end the call.

Making a Three-Way Call

With Three-Way Calling, you can talk to two people at the same time. When using this feature, the normal airtime rates will be charged for each of the two calls.

To make a Three-Way Call:

1. Enter a number you wish to call and press **TALK** or **SPEAKER**.
2. Once you have established the connection, press **TALK** (or press **Options** [right softkey], highlight **Three-Way Call**, and press **MENU OK**). (This puts the first caller on hold.)
3. Dial the second number you wish to call and press **TALK** (or press **Options** [right softkey], highlight **Call** or **Call:Speaker On**, and press **MENU OK**).
4. When you're connected to the second party, press **TALK** again (or press **Options** [right softkey], highlight **Flash**, and press **MENU OK**) to begin your three-way call.

If one of the people you called hangs up during your call, you and the remaining caller stay connected. If you initiated the call and are the first to hang up, all three callers are disconnected.

Tip: You can also begin a Three-Way Call by displaying a phone number stored in your Contacts, Call History, or Messaging. To call the third party, press **MENU OK** during step 3 above.

Note: Call Waiting and Three-Way Calling may not be available while roaming off the network provided to you.

Using Call Forwarding

Call Forwarding lets you forward all your incoming calls to another phone number – even when your phone is turned off. You can continue to make calls from your phone when Call Forwarding is activated.

To activate Call Forwarding:

1. Press **✖ 7 2**.
2. Enter the area code and phone number to which your future calls should be forwarded.
3. Press **TALK**. (You will hear a tone to confirm the activation of Call Forwarding.)

To deactivate Call Forwarding:

1. Press **✖ 7 2 0**.
2. Press **TALK**. (You will hear a tone to confirm the deactivation.)

Note: You are charged a higher rate for calls you have forwarded.

Note: Ready Link calls cannot be forwarded.

Sprint PCS VisionSM

In This Section

- ◆ Getting Started With Vision
 - ◆ Downloading Content
 - ◆ Using Multimedia Services
 - ◆ Accessing Games
 - ◆ Understanding Messaging
 - ◆ Accessing Ringers
 - ◆ Accessing Email Providers
 - ◆ Accessing Screen Savers
 - ◆ Using Instant Messaging
 - ◆ Exploring the Web
 - ◆ Experiencing Wireless Online Chat
 - ◆ Sprint PCS Vision FAQs
-

Sprint PCS VisionSM brings you clarity you can see and hear with advanced multimedia services. These features, including messaging, games, downloadable ringers and screen savers, and Web access are easy to learn and use. The rich, colorful graphic experience is visually comparable to your home or office computer. Clearly, it's a whole new way to look at wireless.

This section introduces these advanced services and walks you through the necessary steps to start taking advantage of Sprint PCS Vision.

Getting Started With Sprint PCS Vision

With your Sanyo SCP-7400 and wireless service from Qwest®, you are ready to start enjoying the advantages of Sprint PCS Vision. This section will help you learn the basics of using your Sprint PCS Vision services, including managing your User Name, launching a Vision connection, and navigating the Web with your phone.

Your User Name

When you buy a compatible phone and sign up for a service plan that includes Sprint PCS Vision, you're automatically assigned a User Name. A User Name is typically your 10-digit wireless phone number followed by "@qwest.sprintpcs.com." For example, if your phone number is 555-123-4567, your User Name will be 5551234567@qwest.sprintpcs.com.

When you use Sprint PCS Vision services, your User Name is submitted to identify you to the network. The User Name is also useful as an address for Email, as a way to personalize Web services, and as an online virtual identity.

Your User Name will be automatically programmed into your phone. You don't have to enter it.

Finding Your User Name



If you aren't sure what your Sprint PCS Vision User Name is, you can easily find it on your phone.

To find your User Name:

- ▶ From standby mode, access your phone's main menu, then go to **Settings > Phone Info > Phone#/User ID**.

Launching a Sprint PCS Vision Connection

To launch a Sprint PCS Vision connection:

1. Press  to access the main menu.
2. Select **Web** and press . (Your Sprint PCS Vision connection will launch and the Sprint PCS Vision home page will display.)

The Sprint PCS Vision Home Page



Shortcut: You can also press **Web** (right softkey) in standby mode.

Note: If Net Guard is enabled and displayed (see next page), press **OK** (left softkey) to continue and launch the Web.

Tip: When Ready Link Guard is set to on, a warning message will appear. Press **Continue** (left softkey) to continue. (See page 155 for Ready Link Guard.)

While connecting, the following will appear on the screen:






Connecting...Please wait..

If you had a previous Sprint PCS Vision connection, the last page you visited (for example, Email or ESPN Top News) will display when you launch your browser. When this occurs, you may not see the “Connecting...” message when you launch the session. Though the browser is open, you are not currently in an active data session - that is, no data is being sent or received. As soon as you navigate to another page, the active session will launch and you will see the “Connecting...” message.

Net Guard

When you first connect to the Web, the Net Guard will appear to confirm that you want to connect. This feature helps you avoid accidental connections. You can disable the Net Guard in the future by selecting **Always Auto-Connect** when the Net Guard is displayed.




To change your Net Guard settings:

1. Press  to access the main menu.
2. Select **Settings** and press .
3. Select **PCS Vision** and press .
4. Select **Net Guard** and press .
5. Select **On** or **Off** and press .
 - **On** to activate the Net Guard.
 - **Off** to deactivate the Net Guard.

Note: When enabled, the Net Guard appears only once per session. The Net Guard does not appear if the phone is merely re-connecting due to a time-out.

Sprint PCS Vision Connection Status and Indicators

Your phone's display lets you know the current status of your Sprint PCS Vision connection through indicators which appear at the top of the screen. The following symbols are used:

-  Your Sprint PCS Vision connection is active (data is being transferred); the transmit/receive symbol will blink to indicate data transmission. Incoming voice calls go directly to voicemail; outgoing voice calls can be made, but the Sprint PCS Vision connection will terminate.
-  Your Sprint PCS Vision connection is dormant (no data is being sent or received). Though not currently active, when dormant the phone can restart an active connection quickly; voice calls can be made and received.
-  Your phone is not currently able to access Sprint PCS Vision service features.

If no indicator appears, your phone does not have a current Sprint PCS Vision connection. To launch a connection, see “Launching a Sprint PCS Vision Connection” on page 219.

Navigating the Web


Navigating through menus and Websites during a Sprint PCS Vision session is easy once you've learned a few basics. Here are some tips for getting around:


Softkeys

During a Sprint PCS Vision session, the bottom line of your phone's display contains one or more softkeys. These keys are shortcut controls for navigating around the Web, and they correspond to the softkey buttons directly below the phone's display screen.

Tip: Depending on which Websites you visit, the labels on the softkeys may change to indicate their function.

To use softkeys:

- ▶ Press the desired softkey button. (If an additional pop-up menu appears when you press the softkey button, select the menu items using your keypad [if they're numbered] or by highlighting the option and pressing )



Scrolling

As with other parts of your phone's menu, you'll have to scroll up and down to see everything on some Websites.

To scroll line by line through Websites:

- ▶ Press the navigation key up or down.


To scroll page by page through Websites:

- ▶ Press the volume buttons on the side of the phone.


Selecting

Once you've learned how to use softkeys and scroll, you can start navigating the Web.

To select on-screen items:

- ▶ Use the navigation key to highlight the desired item, then press the desired softkey button (or press ).

Tip: You'll find that the left softkey is used primarily for selecting items. This softkey is often labeled "Go."

Tip: If the items on a page are numbered, you can use your keypad (number keys) to select an item. (The tenth item in a numbered list may be selected by pressing the  key on your phone's keypad, even though the number 0 doesn't appear on the screen.)

Links allow you to jump to different Web pages, select special functions, or even place phone calls.

To select links:

- ▶ Highlight the link and select the appropriate softkey.

Going Back

To go back one page:

- ▶ Press the  key on your phone.

Note: The  key is also used for deleting text (like a BACKSPACE key) when you are entering text.

Going Home

To return to the Sprint PCS Vision home page from any other Web page:

- ▶ Press the right softkey, then highlight **Home** and press **OK** (left softkey).

Tip: You can also return to the Sprint PCS Vision home page by pressing and holding the  key.



Multimedia



Using the Sprint PCS Vision Multimedia Service

Your phone's built-in media player and Sprint PCS Vision Multimedia Service allow you to listen to audio clips and view video clips right from your phone's display. See and hear the latest news, sports, and weather information in video and sound on-the-go, anytime, anywhere on the network provided to you.

Note: For more information about your phone's multimedia capabilities, see Section 2L : Using Your Phone's Built-in Media Player on page 196.

Purchasing Multimedia Channels

To purchase a multimedia channel:

1. Press  to access the main menu.
2. Select **Media Player** and press .
3. Select a channel under **Available Channels** and press **Select** (left softkey).
4. Follow the onscreen instructions to purchase the channel.

Tip: You can also purchase the channel by pressing the channel number during step 3 above.


Playing an Audio or Video Clip

Enjoy your purchased channels from the channel list. In addition to the list, you can also enjoy the Multimedia Player from a URL in the browser or in the text message you have received (if available).

To play an audio or video clip:

1. Press  to access the main menu.
2. Select **Media Player** and press  (the channel list appears).

Note: When you select the Media Player menu, categories may appear before displaying the channel list (e.g. News, Sports, Entertainment, etc.) Select a category and press  to display your channel list.

3. Select a purchased channel under **My Channels** and press  or **Select** (left softkey).

Tip: The indicator **My Channels** will not appear if you have purchased all available channels.

4. Use your navigation key to browse through available clips and press **Select** (left softkey) to select and play an available clip.



Messaging

Understanding Messaging

Now you can send and receive emails, picture mails, and text messages and participate in Web-based chatrooms right from your phone.

Messaging allows you to stay connected to friends, family, and co-workers 24 hours a day anywhere on the network provided to you.

Note: In some instances, when you receive a text message, the accents with characters will be erased.

Message Types

There are many types of text messaging available on your phone. These appear on your screen as **New Message** and include text messages and picture mail messages.


New Messages

When you receive a new message, the message notification and icon (✉ for a text message and 📧 for a picture mail) will appear.

Press **View** (left softkey) to display the message details.

- Press **Call** (left softkey) to dial the callback number. (Appears when a callback number is highlighted.)
- Press **Reply** (left softkey) to reply to the sender. (Appears when a phone number or email address is highlighted.)
- Press **Go** (left softkey) to go to the Website. (Appears when a URL is highlighted.)
- Press **Forward** (left softkey) to forward the message. (Appears only if there are no phone numbers or URLs in the message.)
- Press **Options** (right softkey) to display options. (See page 231 for details.)

Tip: If you have two or more notifications, the event list will appear.

Tip: To make a Ready Link call from the message, press and hold  (if applicable).






Message Storage

Your phone can store up to 200 received and 180 sent messages. When the message memory is full, the oldest unlocked message will be deleted automatically. (See page 230 for locking messages.)






Displaying Messages

To display a message from the message notification alert, see “New Messages” on page 225.

To display a text message from the main menu:

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Text Msgs** and press . (The folder list appears.)
4. Select **Inbox**, **Sent**, **Outbox**, **Drafts**, or your defined folder and press . (The message list appears.)
5. Select the header of the message you want to see and press . (The message detail appears.)

To display a picture mail from the main menu:









1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **PictureMail** and press . (The Sprint PCS Picture Mail Inbox appears.)
4. Select **Inbox** and press . (The Sprint PCS Picture Mail list appears.)
5. Select your desired message and press . (The Sprint PCS Picture Mail detail appears.)
6. Select the URL in the message and press **Go** (left softkey). (The browser will launch and display the picture.)

Tip: Press the navigation key right to read the next message from the message detail display; press the navigation key left to read the previous message.



Sending a Text Message

With Messaging, you can use a person's wireless phone number to send and receive text messages from your wireless phone to their messaging-ready phone – and they can send messages to you. When you receive a new message, you'll automatically be notified with a two-way text message. To send a Sprint PCS Picture Mail, see “Sending Sprint PCS Picture Mail From Messaging” on page 185.

To send a text message:



1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Send Message** and press .
4. Select **Text** and press .
5. Select an option from the followings and press .
 - **Phone Book Entry** to select a recipient from your Contacts list. Highlight an entry and press  to select. Or select **<Add Entry>** to enter a new entry. Press **Done** (left softkey) when you are finished selecting/entering recipients.
 - **Mobile Phone#** to enter a mobile phone number directly.
 - **Email Address** to enter an email address directly.
 - **From Recent List** to select recipients from a list of recent message recipients.
6. To add a recipient, press **Options** (right softkey), highlight **Add Recipient**, and press .
 - **Edit** to edit the selected entry.
 - **Erase** to erase the selected entry.
 - **Erase All** to erase all entries you have selected and entered.
 - **Add Recipient** to add recipients.
7. Press **Next** (left softkey) when you are finished selecting and entering recipients (you may include up to 10 recipients).
8. To enter a message, select **Message** and press .
9. Use your keypad to enter a text message (or press **Mode** [right softkey] to select from **Preset Messages**, **Recent Messages** or **Signature**), and press **OK** (left softkey).

Tip: The Signature option appears only when you set your signature (see page 65).

10. To set the message priority, scroll to **Priority** and press .
11. Select **Ordinary** or **Urgent** and press .
12. To change the recipients or to save the message as a draft, press **Options** (right softkey) and select an option from the following.
 - **Chg Recipients** to change recipients.
 - **Send Callback#** to select from **None**, **My Phone#**, or **Other** to notify your recipients of your callback number. (See “Setting a Callback Number” on page 65.)
 - **Save to Drafts** to save the message to a Drafts folder. (See below to edit and send the draft message.)





Tip: The oldest message in the drafts folder will be erased automatically when you save more than 10 messages.

13. Press **Send** (left softkey) to send the message.

Note: If there is a failure when sending a message in no-service area, you are prompted to select to send the message automatically. Press **Yes** (left softkey), and the message goes to the Outbox folder with the  icon. If you press **No** (right softkey), the message goes to the folder with the  icon. (See page 229 to send the message.)

Sending a Message in the Drafts Folder





To edit and send a message in the drafts folder:

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Text Msgs** and press .
4. Select **Drafts** and press .
5. Select the message you wish to edit and press **Edit** (left softkey).
6. After editing the message, press **Send** (left softkey) to send the message.

Sending a Message in the Outbox Folder

If a failure occurs when you try to send a message, the message goes to the Outbox folder.

To send a message from the Outbox folder:

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Text Msgs** and press .
4. Select **Outbox** and press .
5. Select the message you wish to send and press **Send** (left softkey).

Message Options


Several options are available when you display a folder list, message list, or message details.


Folder List Options

From the folder list display, press **Options** (right softkey). (See “Displaying Messages” on page 226 for displaying the list.) To select an option, highlight it and press .



- **Edit Folder** to edit the folder (self-defined folder only).
- **Erase Folder** to erase the folder (self-defined folder only).
- **Create Folder** to create a new self-defined folder.
- **Compose New** to compose a new message.
- **Erase Messages** to erase messages (if applicable).

Message List Options


From the message list display or the Sprint PCS Picture Mail list display, press **Options** (right softkey). (See “Displaying Messages” on page 226 for displaying the list.) To select an option, highlight it and press .

- **Reply** to reply to the message. (Inbox and your defined folder only.)
- **Forward** to forward the message. (Inbox, your defined folder, and Sent only.)
- **Edit** to edit a message. (Outbox and Drafts only.)
- **Send** to send a message. (Outbox and Drafts only.)
- **Move** to move a message to another folder. (Inbox and your defined folder only.)
- **Lock** to lock a message. Locked messages will not be erased automatically. To unlock the message, select **Unlock** and press . (Sprint PCS Picture Mail Inbox, Inbox, your defined folder and Sent only.)
- **Compose New** to compose a new message.
- **Erase** to erase the selected message.
- **Erase Read Msgs** to erase read messages in the folder (except locked messages). (Sprint PCS Picture Mail Inbox, Inbox, and your defined folder only.)
- **Erase All** to erase all messages in the folder (except locked messages).


Tip: Locked messages will be displayed with the  icon.



Tip: To make a call from the list, highlight a message and press  or  (if applicable).

Message Details Options

From message details, press **Options** (right softkey) to display message options. (See page 226 for displaying.) Following options are available for messages in the Sprint PCS Picture Mail Inbox, Inbox, Send, and your defined folder. To select an option, highlight it and press .

- **Call (Go to List)** to display phone numbers in the message to make a call. Select a number and press **Call** (left softkey) to make a call.
- **Call:Speaker On** to display phone numbers in the message to make a call in speakerphone mode. Select a number and press **Call** (left softkey) to make a call.



Tip: To make a Ready Link call, select a number and press .

- **Prepend** to add numbers to the beginning of the phone number.
- **Go to URL List** to display URLs in the message to go to the site.
- **Send Message** to display phone numbers and email addresses to send a message. (Except Sprint PCS Picture Mail.)
- **Reply** to reply to the message. (Inbox and defined folder only.)
- **Forward** to forward the message. (Except Sprint PCS Picture Mail.)
- **Move** to move a message to another folder. (Inbox and defined folder only.)
- **Lock** to lock the message. Locked messages will not be erased automatically. To unlock the message, select **Unlock** and press .
- **Font Size** to change the font size from **Small** or **Normal**.
- **Save to Ph. Book** to save the phone number, email address, and URLs. Select a data category and press  to save.
- **Go to Phone Book** to go to the Contacts list.
- **Compose New** to compose a new message. (Except Sprint PCS Picture Mail.)
- **Erase** to erase the message.

Changing the Display Font Size of a Message

From a message details display (except in the Outbox and Drafts folder), press **Options** (right softkey) to display message options.





To adjust the display font size:

1. Highlight **Font Size** and press .
2. Highlight **Small** or **Normal** and press .

Prepending a Phone Number From a Message



From a message details display (except in the Outbox and Drafts folder), press **Options** (right softkey) to display message options.

To add a prefix to a phone number:

1. Highlight **Prepend** and press .
2. Select your desired phone number and press  or **OK** (left softkey).
3. Enter the digits or pauses (see below) you want to add to the number.
4. Press  or  to make a call.

– or –








To select another option, press **Options** (right softkey), highlight it and press .

- **Call** to dial the phone number.
- **Call:Speaker On** to dial the phone number in speakerphone mode.
- **Save Phone#** to store the phone number in your Contacts Directory.
-  **Hard Pause** to insert a hard pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 29.)
-  **2-Sec. Pause** to insert a 2-second pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 29.)




Message Folders

Incoming Updates and numeric pages are stored in folders in your phone's Messaging menu. You may add up to ten folders or use the phone's default folder. When ten self-defined folders exist, the "Create Folder" option will not appear.

To add a new folder:

1. Press  to access the main menu.
2. Select **Messaging** and press .
3. Select **Text Msgs** and press .
4. Press **Options** (right softkey).
5. Highlight **Create Folder** and press .
6. Enter a folder name and press  or **OK** (left softkey).
7. Choose from the following optional features for the added folder and press  to save each item. Scroll to each item and press .
 - **Auto Filing** to file the incoming messages automatically into the self-defined folder by keywords. Following options appear when this feature is set to on.
 - **Keyword** to enter a keyword for Auto Filing.
 - **Notify** to set the notification display and ringer on or off.
 - **Envelope Icon** to set the notification icon on or off.
8. Press **Save** (left softkey) to save the folder.



To edit a folder:

1. From the folder list display, highlight a defined folder.
2. Press **Options** (right softkey).
3. Highlight **Edit Folder** and press .
4. Select the box you wish to edit and press .
5. Enter or select a new folder name or setting.
6. Press  or **OK** (left softkey).
7. Press **Save** (left softkey).

Moving a Message Into Another Folder




You can move incoming messages to the Inbox or a self-defined folder.

To move a message into another folder:

1. From the message display in your Inbox or defined folder, press **Options** (right softkey) to display the message options.
2. Highlight **Move** and press .
3. Highlight your desired folder and press . (You must have at least one defined folder to move a message.)




Erasing Messages

To erase an individual message:

1. From the folder list display, select **Inbox**, **Sent**, **Outbox**, **Drafts**, or your defined folder and press .
2. Select the message you want to erase and press **Options** (right softkey).
3. Highlight **Erase** and press . (A confirmation will display.)
4. Select **Yes** and press .



Tip: To erase all messages, select **Erase All** during step 3 above.

To erase selected messages:

1. From the folder list display, press **Options** (right softkey).
2. Highlight **Erase Messages** and press .
3. Select **Read**, **Unread**, and/or **Sent**, and press  to check the appropriate box(es).
4. After selecting the box(es), press **Done** (left softkey).
5. Select **Erase** and press  to erase selected messages (except locked messages).

Erasing a Folder

To erase a text message folder:

1. From the folder list display, highlight the defined folder you want to erase.
2. Press **Options** (right softkey).
3. Highlight **Erase Folder** and press .
4. Select **Yes** and press .

Note: When you erase a folder, the messages within the folder are also erased. If the folder contains a new (unread) message or locked message, you are prompted to select **Erase** or **Don't Erase**.

Accessing Email Providers

With Sprint PCS Vision, you can use popular email services such as AOL® Mail, Yahoo!® Mail, MSN Hotmail, and EarthLink® to keep in touch even while you're on the go.

Using Email Providers

To access email providers from your wireless phone:

1. From the Sprint PCS Vision home page, select **Messaging**.
2. Select **Email**.
3. Select an email provider, such as **AOL Mail**, **Yahoo! Mail**, or **EarthLink**.
4. Use your keypad to enter the required sign in information for the selected provider, such as user name, email address, and/or password, and select **Sign In**. (Your mailbox for the selected provider will display.)

Note: The information required for sign in will vary depending on the email provider you are accessing.

5. Follow the onscreen instructions to read, reply to, compose, send, and manage your email account.

Using Instant Messaging

Sprint PCS Vision also provides you with access to popular instant messaging (IM) clients, including Yahoo!® Messenger and AOL® Instant Messenger™.

Accessing Instant Messaging

To access instant messaging clients from your wireless phone:

1. Press the navigation key up and select **Instant Msg.**
– or –
From the Sprint PCS Vision home page, select **Messaging** and select **Instant Messaging**.
2. Select an email provider, such as **AOL Instant Messenger** or **Yahoo! Messenger**.
3. Use your keypad to enter the required sign in information for the selected provider, such as user name and/or password, and select **Sign In**. (Your IM screen for the selected provider will display.)



Note: The information required for sign in will vary depending on the instant messaging provider you are accessing.

4. Follow the onscreen instructions to read, reply to, compose, send, and manage your IM account.

Experiencing Wireless Online Chat

Sprint PCS Vision gives you the ability to join wireless chatrooms from your wireless phone, to send text messages and icons to chatroom participants, or to launch a one-on-one (private) chatroom.

To access a chatroom from the browser:

1. Press  to access the main menu.
2. Highlight **Web** and press .
3. Select **Messaging**.
4. Select **Chat**.
5. Select **Enter**. (You will see a disclaimer for Wireless Chat.)
6. Select **I Agree** to enter the Chat menu.
7. Use your keypad to enter a nickname and select **Enter**.
8. Select a chatroom from the menu, for example, “Friends” or “Singles.” (Once in the chatroom, you may scroll through the postings to read messages from other chatroom participants.)

To post a message:

1. During an active chatroom session, select **Add text**.
2. Enter your message.
3. Select **Send**.

To set up a private chatroom:

1. During an active chatroom session, select **1->1**.
2. Select a chatter with whom you’d like to launch a private chatroom.

To exit a chatroom:

- ▶ Select **Leave**.





Note: To avoid inadvertent data usage charges, you should sign out of chatrooms when you are ready to exit.

Downloading Premium Services Content

With Sprint PCS Vision and your new wireless phone, you have access to a dynamic variety of Premium Service content, such as downloadable Games, Ringers, Screen Savers, and other applications. The basic steps required to access and download Premium Service content are outlined below.

Accessing the Download Menus

To access the Sprint PCS Vision download menus:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Select the type of file you wish to download (**Games, Ringers, Screen Savers, or Applications**) and press .
4. Select **Get New** and press . (The browser will launch and take you to the corresponding download menu.)

To access the Sprint PCS Vision download menus from the Web browser:


- ▶ From the Sprint PCS Vision home page, select **Games, Ringers, or Screen Savers** to go to the corresponding download menu. (For more information on navigating the Web, see “Navigating the Web” on page 221.)

Selecting an Item to Download

You can search for available items to download in a number of ways:

- **Featured** displays a rotating selection of featured items.
- **Browse Category** allows you to narrow your search to a general category, such as Movie/TV Themes for Ringers or College Logos for Screen Savers. (There may be several pages of available content in a list. Select **Next9** to view additional items.)
- **Search** allows you to use your keypad to enter search criteria to locate an item. You may enter an entire word or title or perform a partial-word search (for example, entering “goo” returns “Good Ol’ Boy,” “The Good, the Bad, and the Ugly,” and “Goofy - Club”).


Downloading an Item

Once you've selected an item you wish to download, highlight it and press  or **OK** (left softkey). You will see a summary page for the item including its title, the vendor, the download detail, the file size, and the cost. Links allow you to view the **License Details** page, which outlines the price, license type, and length of license for the download, and the **Terms of Use** page, which details the Premium Services Terms of Use and your responsibility for payment.

To download a selected item:

1. From the information page, select **Buy**. (The item will download automatically. When the **New Download** screen appears, the item has been successfully downloaded to your phone.)

Note: If you have not previously purchased an item, you will be prompted to create your purchasing profile.

2. Select an option to continue:
 - Select **Next** (left softkey) to assign the downloaded item (or to launch, in the case of a game or application).
Your Sprint PCS Vision session will end and you will be redirected to the appropriate phone menu screen.
 - Press  to quit the browser and return to standby mode.







Accessing Games

You can play a variety of entertaining and graphically-rich games on your phone. New games are easy to download and play.


Tip: For complete instructions on downloading, see “Downloading Premium Services Content” on page 238.

Downloading Games

To download an available game to your phone:





1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Highlight **Games** and press .
4. Highlight **Get New** and press . (The browser will launch and take you to the Games download menu.)
5. Use your navigation key to highlight and select a game you wish to download. (For more information on navigating the Web, see “Navigating the Web” on page 221.)
6. Select **Buy** from the item information page. (The game will download automatically. When the **New Download** screen appears, the game has been successfully downloaded to your phone.)

Note: If you have not previously purchased an item, you will be prompted to create your purchasing profile.


7. Select an option to continue:
 - Select **Next** (left softkey) to launch the downloaded game. Your Sprint PCS Vision session will end and you will be redirected to the appropriate phone menu screen.
 - Press  to quit the browser and return to standby mode.

Playing Games

To play a downloaded game on your phone:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Highlight **Games** and press .
4. Select the game you wish to play and press .
5. Press the left softkey if a prompt displays the days remaining on the game license.
6. Follow the onscreen instructions to play the game.

To quit a game:

1. When you are finished playing, press . (A prompt will display: "Resume the Application?")
2. Select **Yes** to continue playing.
– or –
Select **No** to exit.







Accessing Ringers

You can personalize your SCP-7400 by downloading and assigning different ringers to numbers in your Contacts list.


Tip: For complete instructions on downloading, see “Downloading Premium Services Content” on page 238.

Downloading Ringers

To download an available ringer to your phone:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Highlight **Ringers** and press .
4. Highlight **Get New** and press . (The browser will launch and take you to the Ringers download menu.)
5. Use your navigation key to highlight and select a ringer you wish to download. (For more information on navigating the Web, see “Navigating the Web” on page 221.)
6. From the item information page, select **Buy**. (The ringer will download automatically. When the **New Download** screen appears, the ringer has been successfully downloaded to your phone.)

Note: If you have not previously purchased an item, you will be prompted to create your purchasing profile.






7. Select an option to continue:
 - Select **Next** (left softkey) to assign the downloaded ringer. Your Sprint PCS Vision session will end and you will be redirected to the appropriate phone menu screen.
 - Press  to quit the browser and return to standby mode.

Note: You may store total of 2816 KB of downloaded data on your phone.



Assigning Downloaded Ringers

You can assign downloaded ringers directly from the Downloads menu or through your phone's Settings menu.

To assign a downloaded ringer from the Downloads menu:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Highlight **Ringers** and press .
4. Highlight a downloaded ringer and press **Options** (right softkey).
5. Highlight **Set as** and press .
6. Highlight **Voice Calls**, **Voicemail**, **Messaging**, **Calendar/Alarm**, **Start-up Tone**, **Power-off Tone** or **Phone Book** and press .

The following two items need an extra step:

- **Voice Calls** requires you to highlight **With Caller ID** or **No caller ID** and press .
- **Phone Book** requires you to highlight the Contacts entry you want to assign and press .

(A message appears confirming that the ringer has been assigned.)

To assign a downloaded ringer from the Settings menu:

- ▶ Please see one of the following:
 - “Selecting Ringer Types for Voice Calls” on page 38.
 - “Selecting Ringer Types for Voicemail, Messages, or Calendar/Alarm” on page 39.
 - “Setting a Start-up/Power-off Tone” on page 40.
 - “Selecting a Ringer and Image Type for an Entry” on page 98.

Note: You may assign a ringer to more than one type of call.

Purchasing Ringers

You can purchase ringers directly from your phone by following the instructions on page 238 or through www.qwestwireless.com.







Accessing Screen Savers

Download unique images to use as screen savers – or make it easy to tell who’s calling by assigning specific images to numbers in your Contacts list.


Tip: For complete instructions on downloading, see “Downloading Premium Services Content” on page 238.

Downloading Screen Savers

To download an available Screen Saver to your phone:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Highlight **Screen Savers** and press .
4. Highlight **Get New** and press . (The browser will launch and take you to the Screen Savers download menu.)
5. Use your navigation key to highlight and select a Screen Saver you wish to download. (For more information on navigating the Web, see “Navigating the Web” on page 221.)
6. From the item information page, select **Buy**. (The screen saver will download automatically. When the **New Download** screen appears, the screen saver has been successfully downloaded to your phone.)

Note: If you have not previously purchased an item, you will be prompted to create your purchasing profile.







7. Select an option to continue:
 - Select **Next** (left softkey) to assign the downloaded screen saver. Your Sprint PCS Vision session will end and you will be redirected to the appropriate phone menu screen.
 - Press  to quit the browser and return to standby mode.

Note: You may store total of 2816 KB of downloaded data on your phone.

Assigning Downloaded Screen Savers

Downloaded Screen Savers may be assigned directly from the Downloads menu or through the Settings menu.

To assign a downloaded Screen Saver from the Downloads menu:

1. Press  to access the main menu.
2. Select **Downloads** and press .
3. Highlight **Screen Savers** and press .
4. Highlight a downloaded Screen Saver and press **Options** (right softkey).
5. Select **Set as** and press .
6. Highlight one of **Incoming Calls**, **Screen Saver**, or **Phone Book** and press . The following item needs an extra step:
 - **Phone Book** requires you to highlight your desired Contacts entry and press .

(A message appears confirming that the image has been assigned.)

Note: Depending on the data, you can select where to assign downloaded images: Image data can be assigned to Incoming Calls, Screen Saver, or Phone Book. Animation data can be assigned to Standby, Outgoing Calls, or Service Search.

Note: You may assign a Screen Saver to more than one task.

Purchasing Screen Savers

You can purchase Screen Savers directly from your phone by following the instructions on page 238, or through www.qwestwireless.com.



Exploring the Web

With Web access on your wireless phone, you can browse full-color graphic versions of your favorite Websites, making it easier than ever to stay informed while on the go. Follow sports scores and breaking news and weather and shop on your phone anywhere on the network provided to you.

In addition to the features already covered in this section, the Sprint PCS Vision home page offers access to these colorful, graphically rich Web categories. Many sites are available under more than one menu – choose the one that's most convenient for you.

- **News.** Get up-to-the-minute news regarding finance, business, sports, and entertainment at sites like CNNtoGo, Bloomberg, USA Today, and ABCNews.
- **Weather.** Access The Weather Channel to get current weather conditions and forecasts.
- **Entertainment.** Get the latest buzz on your favorite stars as well as movie and music reviews at Websites like E! Online, Pocket BoxOffice™, and TastNtalk.
- **Sports.** Enjoy current news, statistics, and sports scores, as well as updates of events in progress at ESPN.com and other sports sites.

Using the Browser Menu


Navigating the Web from your phone using the Sprint PCS Vision home page is easy once you get the hang of it. For details on how to navigate the Web, select menu items, and more, see “Navigating the Web” on page 221.

Although the Sprint PCS Vision home page offers a broad and convenient array of sites and services for you to browse, not all sites are represented, and certain functions, such as going directly to specific Websites, are not available. For these and other functions, you will need to use the browser menu. The browser menu offers additional functionality to expand your use of the Web on your wireless phone.

Opening the Browser Menu

The browser menu may be opened anytime you have an active Sprint PCS Vision session, from any page you are viewing.

To open the browser menu:

- ▶ Press  (right softkey) from any page during an active Sprint PCS Vision session. (The browser menu will display.)
(To launch a Sprint PCS Vision session, please see “Launching a Sprint PCS Vision Connection” on page 219.)



Options available under the browser menu include:

- **Home.** Returns the browser to the Sprint PCS Vision home page.
- **Forward.** Allows you to go forward to the pages you have visited.
- **Mark this page.** Allows you to create new bookmarks.
- **View Bookmarks.** Allows you to view and access bookmarked sites.
- **Search.** Launches a Google search.
- **Show URL.** Displays the URL (Website address) of the site you’re currently viewing.
- **Go to URL....** Allows you to navigate directly to a Website by entering its URL (Website address).
- **History.** Displays the pages you have visited.
- **Refresh this page.** Reloads the current Web page.
- **More....** Displays the additional menu options. (Restart Browser, Send Page, and Preferences.)

Creating a Bookmark

Bookmarks allow you to store the address of your favorite Websites for easy access at a later time.



To create a bookmark:

1. Launch the Web page you want to mark.
2. Press  (right softkey) to go to the browser menu.
3. Select **Mark this page** and press  or **OK** (left softkey).

Note: Bookmarking a page does not store the page contents, just its address. Some pages cannot be bookmarked. Whether a particular Web page may be marked is controlled by its creator.



Accessing a Bookmark

To access a bookmark:

1. Access the browser menu by pressing  (right softkey).
2. Select **View Bookmarks** and press **OK** (left softkey).
3. Highlight the bookmark you'd like to access and press  or **OK** (left softkey) to go to the Website.



Editing a Bookmark

To edit a bookmark:

1. Launch the Web and press  (right softkey) to access the browser menu.
2. Select **View Bookmarks** and press **OK** (left softkey).
3. Select the bookmark you wish to edit and press  (right softkey).
4. Select **Edit Address** or **Edit Title** and press **OK** (left softkey).
5. Press **Edit** (right softkey), use your keypad to edit the address or title, and press **OK** (left softkey).
6. To save the bookmark, press **OK** (left softkey).

Deleting a Bookmark


To delete a bookmark:

1. Launch the Web and press  (right softkey) to access the browser menu.
2. Select **View Bookmarks** and press **OK** (left softkey).
3. Highlight the bookmark you wish to erase and press  (right softkey).
4. Select **Delete** and press **OK** (left softkey).
5. Press **Yes** (right softkey).

Tip: To delete all bookmarks, select **Delete All** during step 4 above.


Moving a Bookmark

To move a bookmark:

1. Access the **View Bookmarks** menu as outlined above in steps 1-2, and press  (right softkey).
2. Select **Reorder** and press **OK** (left softkey).
3. Highlight the bookmark you wish to move and press **Move** (left softkey).
4. Move the bookmark to a new location by pressing the navigation key up or down and press **Drop** (left softkey).
5. When you're finished, press **Finish** (right softkey).

Going to a Specific Website


To go to a particular Website by entering a URL (Website address):

1. Launch the Web and press  (right softkey) to display the browser menu.
2. Select **Go to URL...** and press **OK** (left softkey).
3. Select **Address** and press **OK** (left softkey).
4. Use your keypad to enter the URL of the Website you wish to go to and press **OK** (left softkey).

Note: Not all Websites are viewable on your phone.

Reloading a Web Page


To reload (refresh) a Web page:

1. Launch the Web and press  (right softkey) to display the browser menu.
2. Select **Refresh this page** and press **OK** (left softkey).

Restarting the Web Browser

If the Web browser appears to be malfunctioning or stops responding, you can usually fix the problem by simply restarting the browser.


To restart the Web browser:

1. From an active Sprint PCS Vision connection, press  (right softkey) to display the browser menu.
2. Select **More...** and press **OK** (left softkey).
3. Select **Restart Browser** and press **OK** (left softkey).

Sending a Web Page



This feature allows you to send a URL (Website address) you're viewing through SMS text messaging.

To send a Web page:

1. From an active Sprint PCS Vision connection, press  (right softkey) to display the browser menu.
2. Select **More...** and press **OK** (left softkey).
3. Select **Send Page** and press **OK** (left softkey).
4. To complete and send a Web Page, follow steps 5-13 in "Sending a Text Message" on page 227.

Adjusting the Browser Sound Volume

To adjust the browser sound volume:

1. From an active Sprint PCS Vision connection, press  (right softkey) to display the browser menu.
2. Select **More...** and press **OK** (left softkey).
3. Select **Preferences** and press **OK** (left softkey).
4. Select **Sound Volume** and press **OK** (left softkey).
5. Select your desired volume level by pressing the navigation key up or down and press .

Sprint PCS Vision FAQs


How will I know when my phone is ready for Sprint PCS Vision service?

When your phone is ready, your User Address will be displayed in the Phone#/UserID menu. Go to **Settings > Phone Info > Phone#/User ID**.

How do I sign-in for the first time?

You are automatically signed in to access Sprint PCS Vision services when you turn on your phone.



How do I know when my phone is connected to Sprint PCS Vision services?

Your phone automatically connects when Sprint PCS Vision service is used or an incoming message arrives. Your phone will also display the  icon. (Connecting takes about 10-12 seconds.)

Can I make calls and use Sprint PCS Vision services at the same time?

You cannot use voice and Sprint PCS Vision services simultaneously. If you receive a call while Sprint PCS Vision service is active, the call will be forwarded to voicemail. You can place an outgoing call anytime, but it will interrupt any in-progress Sprint PCS Vision session.

When is my data connection active?

Your connection is active when data is being transferred. Outgoing calls are allowed; incoming calls go directly to voicemail. When active, the  (Sending) or  (Receiving) indicator flashes on your phone's display screen.

When is my data connection dormant?

If no data is received for 10 seconds, the connection goes dormant. When the connection is dormant, voice calls are allowed. (The connection may become active again quickly.) If no data is received for an extended period of time, the connection will terminate.

Can I sign out of data services?

You can sign out without turning off your phone; however, you will not be able to browse the Web or use other Sprint PCS Vision services. While signed out, you can still place or receive phone calls, check voicemail, and use other voice services. You may sign in again at any time. To sign out, go to **Settings > PCS Vision > Disable Vision** in your phone's menu.

Safety Guidelines

Safety

In This Section

- ◆ **Getting the Most Out of Your Reception**
 - ◆ **Maintaining Safe Use of and Access to Your Phone**
 - ◆ **Caring for the Battery**
 - ◆ **Acknowledging Special Precautions and the FCC Notice**
 - ◆ **Consumer Information on Wireless Phones**
 - ◆ **Owner's Record**
 - ◆ **User's Guide Proprietary Notice**
-

Part of getting the most out of your new wireless phone is learning how the phone works and how to care for it. This section outlines performance and safety guidelines that help you understand the basic features of your phone's operation.

Getting the Most Out of Your Reception

Keeping Tabs on Signal Strength

The quality of each call you make or receive depends on the signal strength in your area. Your phone informs you of the current signal strength by displaying a number of bars next to the signal strength icon. The more bars displayed, the stronger the signal. If you're inside a building, being near a window may give you better reception.

Understanding the Power Save Feature

If your phone is unable to find a signal after 15 minutes of searching, a Power Save feature is automatically activated. If your phone is active, it periodically rechecks service availability; you can also check it yourself by pressing any key. Anytime the Power Save feature is activated, a message is displayed on the screen. When a signal is found, your phone returns to standby mode.

Understanding How Your Phone Operates

Your phone is basically a radio transmitter and receiver. When it's turned on, it receives and transmits radiofrequency (RF) signals. When you use your phone, the system handling your call controls the power level. This power can range from 0.01μ watts to 0.2 watts in digital mode.

Knowing Radio Frequency Safety

The design of your wireless phone complies with updated NCRP standards described below.

In 1991-92, the Institute of Electrical and Electronics Engineers (IEEE) and the American National Standards Institute (ANSI) joined in updating ANSI's 1982 standard for safety levels with respect to human exposure to RF signals. More than 120 scientists, engineers and physicians from universities, government health agencies and industries developed this updated standard after reviewing the available body of research. In 1993, the Federal Communications Commission (FCC) adopted this updated standard in a regulation. In August 1996, the FCC adopted hybrid standard consisting of the existing ANSI/IEEE standard and the guidelines published by the National Council of Radiation Protection and Measurements (NCRP).

Maintaining Your Phone's Peak Performance

There are several simple guidelines to operating your phone properly and maintaining safe, satisfactory service.

- Hold the phone with the antenna raised, fully-extended, and over your shoulder.
- Try not to hold, bend, or twist the phone's antenna.
- Don't use the phone if the antenna is damaged.
- Speak directly into the mouthpiece.
- Avoid exposing your phone and accessories to rain or liquid spills. If your phone does get wet, immediately turn the power off and remove the battery.

Note: For the best care of your phone, only authorized personnel should service your phone and accessories. Faulty service may void the warranty.

Maintaining Safe Use of and Access to Your Phone

FAILURE TO FOLLOW THE INSTRUCTIONS OUTLINED MAY LEAD TO SERIOUS PERSONAL INJURY AND POSSIBLE PROPERTY DAMAGE

Using Your Phone While Driving

Talking on your phone while driving (or operating the phone without a hands-free device) is prohibited in some jurisdictions. Laws vary as to specific restrictions. Remember that safety always comes first.

When using your phone in the car:

- Get to know your phone and its features, such as speed dial and redial.
- When available, use a hands-free device.
- Position your phone within easy reach.
- Let the person you are speaking to know you are driving; if necessary, suspend the call in heavy traffic or hazardous weather conditions.
- Do not take notes or look up phone numbers while driving.
- Dial sensibly and assess the traffic; if possible, place calls when stationary or before pulling into traffic.
- Do not engage in stressful or emotional conversations that may divert your attention from the road.
- Dial **9 1 1** to report serious emergencies. It's free from your wireless phone.
- Use your phone to help others in emergencies.
- Call roadside assistance or a special non-emergency wireless number when necessary.

Tip: To purchase an optional hands-free car kit, call Qwest Wireless® Repair at 1-877-879-0611.

Following Safety Guidelines

To operate your phone safely and efficiently, always follow any special regulations in a given area. Turn your phone off in areas where use is forbidden or when it may cause interference or danger.

Using Your Phone Near Other Electronic Devices

Most modern electronic equipment is shielded from radiofrequency (RF) signals. However, RF signals from wireless phones may affect inadequately shielded electronic equipment.

RF signals may affect improperly installed or inadequately shielded electronic operating systems and/or entertainment systems in motor vehicles. Check with the manufacturer or their representative to determine if these systems are adequately shielded from external RF signals. Also check with the manufacturer regarding any equipment that has been added to your vehicle.

Consult the manufacturer of any personal medical devices, such as pacemakers and hearing aids, to determine if they are adequately shielded from external RF signals.

Note: Always turn off the phone in health care facilities and request permission before using the phone near medical equipment.

Turning Off Your Phone Before Flying

Turn off your phone before boarding any aircraft. To prevent possible interference with aircraft systems, the U.S. Federal Aviation Administration (FAA) regulations require you to have permission from a crew member to use your phone while the plane is on the ground. To prevent any risk of interference, FCC regulations prohibit using your phone while the plane is in the air.

Turning Off Your Phone in Dangerous Areas

To avoid interfering with blasting operations, turn your phone off when in a blasting area or in other areas with signs indicating two-way radios should be turned off. Construction crews often use remote-control RF devices to set off explosives.

Turn your phone off when you're in any area that has a potentially explosive atmosphere. Although it's rare, your phone and accessories could generate sparks. Sparks can cause an explosion or fire, resulting in bodily injury or even death. These areas are often, but not always, clearly marked. They include:

- Fueling areas such as gas stations.
- Below deck on boats.
- Fuel or chemical transfer or storage facilities.
- Areas where the air contains chemicals or particles such as grain, dust, or metal powders.
- Any other area where you would normally be advised to turn off your vehicle's engine.

Note: Never transport or store flammable gas, liquid or explosives in the compartment of your vehicle that contains your phone or accessories.

Restricting Children's Access to Your Phone

Your phone is not a toy. Do not allow children to play with it as they could hurt themselves and others, damage the phone or make calls that increase your invoice.

Caring for the Battery

Protecting Your Battery

The guidelines listed below help you get the most out of your battery's performance.

- Use only Qwest-approved batteries and chargers. These chargers are designed to maximize battery life. Using other batteries or chargers voids your warranty and may cause damage.
- In order to avoid damage, charge the battery only in temperatures that range from 32° F to 113° F (0° C to 45° C).
- Don't use the battery charger in direct sunlight or in high humidity areas, such as the bathroom.
- Never dispose of the battery by incineration.
- Keep the metal contacts on top of the battery clean.
- Don't attempt to disassemble or short-circuit the battery.
- The battery may need recharging if it has not been used for a long period of time.
- It's best to replace the battery when it no longer provides acceptable performance. It can be recharged hundreds of times before it needs replacing.
- Don't store the battery in high temperature areas for long periods of time. It's best to follow these storage rules:

Less than one month:

-4° F to 140° F (-20° C to 60° C)

More than one month:

-4° F to 113° F (-20° C to 45° C)

Disposal of Lithium Ion (Lilon) Batteries

For safe disposal options of your Lilon batteries, contact your nearest authorized service center.

Special Note: Be sure to dispose of your battery properly. In some areas, the disposal of batteries in household or business trash may be prohibited.

Note: For safety, do not handle a damaged or leaking Lilon battery.

Acknowledging Special Precautions and the FCC Notice

FCC Notice

This phone may cause TV or radio interference if used in close proximity to receiving equipment. The FCC can require you to stop using the phone if such interference cannot be eliminated.

Vehicles using liquefied petroleum gas (propane or butane) must comply with the National Fire Protection Standard (NFPA-58). For a copy of this standard, contact the National Fire Protections Association, One Batterymarch Park, Quincy, MA 02269, Attn.: Publication Sales Division.

Cautions

Any changes or modifications to your phone not expressly approved in this document could void your warranty for this equipment and void your authority to operate this equipment. Only use approved batteries, antennas and chargers. The use of any unauthorized accessories may be dangerous and void the phone warranty if said accessories cause damage or a defect to the phone.

Although your phone is quite sturdy, it is a complex piece of equipment and can be broken. Avoid dropping, hitting, bending or sitting on it.

Body-Worn Operation

To maintain compliance with FCC RF exposure guidelines, if you wear a handset on your body, use the Qwest supplied or approved carrying case, holster or other body-worn accessory. If you do not use a body-worn accessory, ensure the antenna is at least 2.2 cm from your body when transmitting. Use of non-Qwest approved accessories may violate FCC RF exposure guidelines.

For more information about RF exposure, visit the FCC Website at www.fcc.gov.

Specific Absorption Rates (SAR) for Wireless Phones

The SAR is a value that corresponds to the relative amount of RF energy absorbed in the head of a user of a wireless handset.

The SAR value of a phone is the result of an extensive testing, measuring and calculation process. It does not represent how much RF the phone emits. All phone models are tested at their highest value in strict laboratory settings. But when in operation, the SAR of a phone can be substantially less than the level reported to the FCC. This is because of a variety of factors including its proximity to a base station antenna, phone design and other factors. What is important to remember is that each phone meets strict federal guidelines. Variations in SARs do not represent a variation in safety.

All phones must meet the federal standard, which incorporates a substantial margin of safety. As stated above, variations in SAR values between different model phones do not mean variations in safety. SAR values at or below the federal standard of 1.6 W/kg are considered safe for use by the public.

The highest reported SAR values of the SCP-7400 are:

AMPS/CDMA modes (Part 22):

Head: 1.390 W/kg; Body-worn: 0.940 W/kg

PCS mode (Part 24):

Head: 0.951 W/kg; Body-worn: 1.150 W/kg

FCC Radiofrequency Emission

This phone meets the FCC Radiofrequency Emission Guidelines.

FCC ID number: AEZSCP-74H. More information on the phone's SAR can be found from the following FCC Website: <http://www.fcc.gov/oet/fccid>.

Consumer Information on Wireless Phones

(The following information comes from a consumer information Website jointly sponsored by the U.S. Food and Drug Administration (FDA) and the Federal Communications Commission (FCC), entitled “Cell Phone Facts: Consumer Information on Wireless Phones.” The information reproduced herein is dated July 29, 2003. For further updates, please visit the Website: <http://www.fda.gov/cellphones/qa.html>.)

What is radiofrequency energy (RF)?

Radiofrequency (RF) energy is another name for radio waves. It is one form of electromagnetic energy that makes up the electromagnetic spectrum. Some of the other forms of energy in the electromagnetic spectrum are gamma rays, x-rays and light. Electromagnetic energy (or electromagnetic radiation) consists of waves of electric and magnetic energy moving together (radiating) through space. The area where these waves are found is called an electromagnetic field.

Radio waves are created due to the movement of electrical charges in antennas. As they are created, these waves radiate away from the antenna. All electromagnetic waves travel at the speed of light. The major differences between the different types of waves are the distances covered by one cycle of the wave and the number of waves that pass a certain point during a set time period. The wavelength is the distance covered by one cycle of a wave. The frequency is the number of waves passing a given point in one second. For any electromagnetic wave, the wavelength multiplied by the frequency equals the speed of light. The frequency of an RF signal is usually expressed in units called hertz (Hz). One Hz equals one wave per second. One kilohertz (kHz) equals one thousand waves per second, one megahertz (MHz) equals one million waves per second, and one gigahertz (GHz) equals one billion waves per second.

RF energy includes waves with frequencies ranging from about 3000 waves per second (3 kHz) to 300 billion waves per second (300 GHz). Microwaves are a subset of radio waves that have frequencies ranging from around 300 million waves per second (300 MHz) to three billion waves per second (3 GHz).

How is radiofrequency energy used?

Probably the most important use of RF energy is for telecommunications. Radio and TV broadcasting, wireless phones, pagers, cordless phones, police and fire department radios, point-to-point links and satellite communications all rely on RF energy.

Other uses of RF energy include microwave ovens, radar, industrial heaters and sealers, and medical treatments. RF energy, especially at microwave frequencies, can heat water. Since most food has a high water content, microwaves can cook food quickly. Radar relies on RF energy to track cars and airplanes as well as for military applications. Industrial heaters and sealers use RF energy to mold plastic materials, glue wood products, seal leather items such

as shoes and pocketbooks, and process food. Medical uses of RF energy include pacemaker monitoring and programming.

How is radiofrequency radiation measured?

RF waves and RF fields have both electrical and magnetic components. It is often convenient to express the strength of the RF field in terms of each component. For example, the unit “volts per meter” (V/m) is used to measure the electric field strength, and the unit “amperes per meter” (A/m) is used to express the magnetic field strength. Another common way to characterize an RF field is by means of the power density. Power density is defined as power per unit area. For example, power density can be expressed in terms of milliwatts (one thousandth of a watt) per square centimeter (mW/cm² or microwatts (one millionth of a watt) per square centimeter (μW/cm²).

The quantity used to measure how much RF energy is actually absorbed by the body is called the Specific Absorption Rate or SAR. The SAR is a measure of the rate of absorption of RF energy. It is usually expressed in units of watts per kilogram (W/kg) or milliwatts per gram (mW/g).

What biological effects can be caused by RF energy?

The biological effects of radiofrequency energy should not be confused with the effects from other types of electromagnetic energy.

Very high levels of electromagnetic energy, such as is found in X-rays and gamma rays can ionize biological tissues. Ionization is a process where electrons are stripped away from their normal locations in atoms and molecules. It can permanently damage biological tissues including DNA, the genetic material. Ionization only occurs with very high levels of electromagnetic energy such as X-rays and gamma rays. Often the term radiation is used when discussing ionizing radiation (such as that associated with nuclear power plants).

The energy levels associated with radiofrequency energy, including both radio waves and microwaves, are not great enough to cause the ionization of atoms and molecules. Therefore, RF energy is a type of non-ionizing radiation. Other types of non-ionizing radiation include visible light, infrared radiation (heat) and other forms of electromagnetic radiation with relatively low frequencies.

Large amounts of RF energy can heat tissue. This can damage tissues and increase body temperatures. Two areas of the body, the eyes and the testes, are particularly vulnerable to RF heating because there is relatively little blood flow in them to carry away excess heat.

The amount of RF radiation routinely encountered by the general public is too low to produce significant heating or increased body temperature. Still, some people have questions about the possible health effects of low levels of RF energy. It is generally agreed that further research is needed to determine what effects actually occur and whether they are dangerous to people. In the meantime, standards-setting organizations and government agencies are continuing to monitor the latest scientific findings to determine whether changes in safety limits are needed to protect human health.

FDA, EPA and other US government agencies responsible for public health and safety have worked together and in connection with WHO to monitor developments and identify research needs related to RF biological effects.

What levels of RF energy are considered safe?

Various organizations and countries have developed standards for exposure to radiofrequency energy. These standards recommend safe levels of exposure for both the general public and for workers. In the United States, the FCC has used safety guidelines for RF environmental exposure since 1985.

The FCC guidelines for human exposure to RF electromagnetic fields are derived from the recommendations of two expert organizations, the National Council on Radiation Protection and Measurements (NCRP) and the Institute of Electrical and Electronics Engineers (IEEE). In both cases, the recommendations were developed by scientific and engineering experts drawn from industry, government, and academia after extensive reviews of the scientific literature related to the biological effects of RF energy.

Many countries in Europe and elsewhere use exposure guidelines developed by the International Commission on Non-Ionizing Radiation Protection (ICNIRP). The ICNIRP safety limits are generally similar to those of the NCRP and IEEE, with a few exceptions. For example, ICNIRP recommends different exposure levels in the lower and upper frequency ranges and for localized exposure from certain products such as hand-held wireless telephones. Currently, the World Health Organization is working to provide a framework for international harmonization of RF safety standards.

The NCRP, IEEE, and ICNIRP all have identified a whole-body Specific Absorption Rate (SAR) value of 4 watts per kilogram (4 W/kg) as a threshold level of exposure at which harmful biological effects may occur. Exposure guidelines in terms of field strength, power density and localized SAR were then derived from this threshold value. In addition, the NCRP, IEEE, and ICNIRP guidelines vary depending on the frequency of the RF exposure. This is due to the finding that whole-body human absorption of RF energy varies with the frequency of the RF signal. The most restrictive limits on whole-body exposure are in the frequency range of 30-300 MHz where the human body absorbs RF energy most efficiently. For products that only expose part of the body, such as wireless phones, exposure limits in terms of SAR only are specified.

The exposure limits used by the FCC are expressed in terms of SAR, electric and magnetic field strength, and power density for transmitters operating at frequencies from 300 kHz to 100 GHz. The specific values can be found in two FCC bulletins, OET Bulletins 56 and 65:

<http://www.fcc.gov/oet/info/documents/bulletins/#56>;

<http://www.fcc.gov/oet/info/documents/bulletins/#65>.

Why has the FCC adopted guidelines for RF exposure?

The FCC authorizes and licenses products, transmitters, and facilities that generate RF and microwave radiation. It has jurisdiction over all transmitting services in the U.S. except those specifically operated by the Federal

Government. While the FCC does not have the expertise to determine radiation exposure guidelines on its own, it does have the expertise and authority to recognize and adopt technically sound standards promulgated by other expert agencies and organizations, and has done so. (Our joint efforts with the FDA in developing this website is illustrative of the kind of inter-agency efforts and consultation we engage in regarding this health and safety issue.)

Under the National Environmental Policy Act of 1969 (NEPA), the FCC has certain responsibilities to consider whether its actions will significantly affect the quality of the human environment. Therefore, FCC approval and licensing of transmitters and facilities must be evaluated for significant impact on the environment. Human exposure to RF radiation emitted by FCC-regulated transmitters is one of several factors that must be considered in such environmental evaluations. In 1996, the FCC revised its guidelines for RF exposure as a result of a multi-year proceeding and as required by the Telecommunications Act of 1996.

Radio and television broadcast stations, satellite-earth stations, experimental radio stations and certain wireless communication facilities are required to undergo routine evaluation for RF compliance when they submit an application to the FCC for construction or modification of a transmitting facility or renewal of a license. Failure to comply with the FCC's RF exposure guidelines could lead to the preparation of a formal Environmental Assessment, possible Environmental Impact Statement and eventual rejection of an application. Technical guidelines for evaluating compliance with the FCC RF safety requirements can be found in the FCC's OET Bulletin 65.
<http://www.fcc.gov/oet/info/documents/bulletins/#65>

Low-powered, intermittent, or inaccessible RF transmitters and facilities are normally excluded from the requirement for routine evaluation for RF exposure. These exclusions are based on standard calculations and measurement data indicating that a transmitting station or equipment operating under the conditions prescribed is unlikely to cause exposures in excess of the guidelines under normal conditions of use. Such exclusions are not exclusions from compliance, but, rather, exclusions from routine evaluation. The FCC's policies on RF exposure and categorical exclusion can be found in Section 1.1307(b) of the FCC's Rules and Regulations [(47 CFR 1.1307(b))].

How can I obtain the Specific Absorption Rate (SAR) value for my wireless phone?

The FCC requires that wireless phones sold in the United States demonstrate compliance with human exposure limits adopted by the FCC in 1996. The relative amount of RF energy absorbed in the head of a wireless telephone-user is given by the Specific Absorption Rate (SAR), as explained above. The FCC requires wireless phones to comply with a safety limit of 1.6 watts per kilogram (1.6 W/kg) in terms of SAR.

Information on SAR for a specific phone model can be obtained for many recently manufactured phones using the FCC identification (ID) number for that

model. The FCC ID number is usually printed somewhere on the case of the phone. Sometimes it may be necessary to remove the battery pack to find the number. Once you have the ID number, go to the following Web address: www.fcc.gov/oet/fccid. On this page, you will see instructions for entering the FCC ID number. Type the FCC ID number exactly as requested (the Grantee Code is the first three characters, the Equipment Product Code is the rest of the FCC ID number). Then click on "Start Search." The "Grant of Equipment Authorization" for your telephone should appear. Read through the grant for the section on "SAR Compliance," "Certification of Compliance with FCC Rules for RF Exposure" or similar language. This section should contain the value(s) for typical or maximum SAR for your phone.

Phones and other products authorized since June 2, 2000, should have the maximum SAR levels noted directly on the "Grant of Equipment Authorization." For phones and products authorized between about mid-1998 and June 2000, detailed information on SAR levels is typically found in the exhibits associated with the grant. Once a grant is accessed, the exhibits can be viewed by clicking on "View Exhibit." Grants authorized prior to 1998 are not part of the electronic database but, rather, have been documented in the form of paper records.

The FCC database does not list phones by model number. However, consumers may find SAR information from other sources as well. Some wireless phone manufacturers make SAR information available on their own Web sites. In addition, some non-government Web sites provide SARs for specific models of wireless phones. However, the FCC has not reviewed these sites and makes no guarantees of their accuracy. Finally, phones certified by the Cellular Telecommunications and Internet Association (CTIA) are required to provide SAR information to consumers in the instructional materials that come with the phones.

Do hands-free kits for wireless phones reduce risks from exposure to RF emissions?

Since there are no known risks from exposure to RF emissions from wireless phones, there is no reason to believe that hands-free kits reduce risks. Hands-free kits can be used with wireless phones for convenience and comfort. These systems reduce the absorption of RF energy in the head because the phone, which is the source of the RF emissions, will not be placed against the head. On the other hand, if the phone is mounted against the waist or other part of the body during use, then that part of the body will absorb more RF energy. Wireless phones marketed in the U.S. are required to meet safety requirements regardless of whether they are used against the head or against the body. Either configuration should result in compliance with the safety limit.

Do wireless phone accessories that claim to shield the head from RF radiation work?

Since there are no known risks from exposure to RF emissions from wireless phones, there is no reason to believe that accessories that claim to shield the head from those emissions reduce risks. Some products that claim to shield the

user from RF absorption use special phone cases, while others involve nothing more than a metallic accessory attached to the phone. Studies have shown that these products generally do not work as advertised. Unlike “hand-free” kits, these so-called “shields” may interfere with proper operation of the phone. The phone may be forced to boost its power to compensate, leading to an increase in RF absorption. In February 2002, the Federal Trade Commission (FTC) charged two companies that sold devices that claimed to protect wireless phone users from radiation with making false and unsubstantiated claims. According to FTC, these defendants lacked a reasonable basis to substantiate their claim.

What are wireless telephone base stations?

Fixed antennas used for wireless telecommunications are referred to as cellular base stations, cell stations, PCS (“Personal Communications Service”) stations or telephone transmission towers. These base stations consist of antennas and electronic equipment. Because the antennas need to be high in the air, they are often located on towers, poles, water tanks, or rooftops. Typical heights for freestanding base station towers are 50-200 feet.

Some base stations use antennas that look like poles, 10 to 15 feet in length, that are referred to as “omni-directional” antennas. These types of antennas are usually found in rural areas. In urban and suburban areas, wireless providers now more commonly use panel or sector antennas for their base stations. These antennas consist of rectangular panels, about 1 by 4 feet in dimension. The antennas are usually arranged in three groups of three antennas each. One antenna in each group is used to transmit signals to wireless phones, and the other two antennas in each group are used to receive signals from wireless phones.

At any base station site, the amount of RF energy produced depends on the number of radio channels (transmitters) per antenna and the power of each transmitter. Typically, 21 channels per antenna sector are available. For a typical cell site using sector antennas, each of the three transmitting antennas could be connected to up to 21 transmitters for a total of 63 transmitters. However, it is unlikely that all of the transmitters would be transmitting at the same time.

When omni-directional antennas are used, a cellular base station could theoretically use up to 96 transmitters, but this would be very unusual, and, once again, it is unlikely that all transmitters would be in operation simultaneously. Base stations used for PCS communications generally require fewer transmitters than those used for cellular radio transmissions, since PCS carriers usually have a higher density of base station antenna sites.

Are wireless telephone base stations safe?

The electromagnetic RF signals transmitted from base station antennas stations travel toward the horizon in relatively narrow paths. For example, the radiation pattern for an antenna array mounted on a tower can be likened to a thin pancake centered around the antenna system. The individual pattern for a single array of sector antennas is wedge-shaped, like a piece of pie. As with all forms of electromagnetic energy, the power decreases rapidly as one moves away from

the antenna. Therefore, RF exposure on the ground is much less than exposure very close to the antenna and in the path of the transmitted radio signal. In fact, ground-level exposure from such antennas is typically thousands of times less than the exposure levels recommended as safe by expert organizations. So exposure to nearby residents would be well within safety margins.

Cellular and PCS base stations in the United States are required to comply with limits for exposure recommended by expert organizations and endorsed by government agencies responsible for health and safety. Measurements made near cellular and PCS base station antennas mounted on towers have confirmed that ground-level exposures are typically thousands of times less than the exposure limits adopted by the FCC. In fact, in order to be exposed to levels at or near the FCC limits for cellular or PCS frequencies an individual would essentially have to remain in the main transmitted radio signal (at the height of the antenna) and within a few feet from the antenna. This is, of course, very unlikely to occur.

When cellular and PCS antennas are mounted on rooftops, RF levels on that roof or on others near by would probably be greater than those typically encountered on the ground. However, exposure levels approaching or exceeding safety guidelines should be encountered only very close to or directly in front of the antennas. In addition, for sector-type antennas, typically used for such rooftop base stations, RF levels to the side and in back of these antennas are insignificant. General guidelines on antenna installations and circumstances that might give rise to a concern about an facility's conformance with FCC regulations can be found in A Local Government Official's Guide to Transmitting Antenna RF Emission Safety: Rules, Procedures, and Practical Guidance. This Guide can be accessed at: <http://www.fcc.gov/oet/rfsafety>.

Who regulates exposure to radiation from microwave ovens, television sets and computer monitors?

The Food and Drug Administration is responsible for protecting the public from harmful radiation emissions from these consumer products.

Does the FCC routinely monitor radiofrequency radiation from antennas?

The FCC does not have the resources or the personnel to routinely monitor the emissions for all the thousands of transmitters that are subject to FCC jurisdiction. However, the FCC does have measurement instrumentation for evaluating RF levels in areas that may be accessible to the public or to workers. If there is evidence for potential non-compliance with FCC exposure guidelines for a FCC-regulated facility, staff from the FCC's Office of Engineering and Technology or the FCC Enforcement Bureau can conduct an investigation, and, if appropriate, perform actual measurements. Circumstances that could give rise to a concern about an facility's conformance with FCC regulations can be found in A Local Government Official's Guide to Transmitting Antenna RF Emission Safety: Rules, Procedures, and Practical Guidance. This Guide can be accessed at: <http://www.fcc.gov/oet/rfsafety>. Potential exposure problems should

be brought to the FCC's attention by contacting the FCC RF Safety Program at: 202-418-2464 or by email: rf-safety@fcc.gov.

Does the FCC maintain a database that includes information on the location and technical parameters of all the transmitting towers it regulates?

Each of the FCC Bureaus maintains its own licensing database system for the service(s) it regulates (e.g., television, cellular service, satellite earth stations.) The FCC issues two types of licenses: site specific and market based. In the case of site specific licensed facilities, technical operating information is collected from the licensee as part of the licensing process. However, in the case of market based licensing (e.g., PCS, cellular), the licensee is granted the authority to operate a radio communications system in a geographic area using as many facilities as are required, and the licensee is not required to provide the FCC with specific location and operating parameters of these facilities.

Information on site specific licensed facilities can be found the "General Menu Reports" (GenMen) at <http://gulfoss2.fcc.gov/cgi-bin/ws.exe/genmen/index.htm>.

The various FCC Bureaus also publish on at least a weekly basis, bulk extracts of their licensing databases. Each licensing database has its own unique file structure. These extracts consist of multiple, very large files. The FCC's Office of Engineering and Technology (OET) maintains an index to these databases at <http://www.fcc.gov/oet/info/database/fadb.html>. Entry points into the various databases include frequency, state/county, latitude/longitude, call-sign and licensee name. For further information on the Commission's existing databases, you can contact Donald Campbell at dcampbel@fcc.gov or 202-418-2405.

Can local and state governmental bodies establish limits for RF exposure?

Although some local and state governments have enacted rules and regulations about human exposure to RF energy in the past, the Telecommunications Act of 1996 requires the Federal Government to control human exposure to RF emissions. In particular, Section 704 of the Act states that, "No State or local government or instrumentality thereof may regulate the placement, construction, and modification of personal wireless service facilities on the basis of the environmental effects of radio frequency emissions to the extent that such facilities comply with the Commission's regulations concerning such emissions." Further information on federal authority and FCC policy is available in a fact sheet from the FCC's Wireless Telecommunications Bureau at www.fcc.gov/wtb.

Do wireless phones pose a health hazard?

The available scientific evidence does not show that any health problems are associated with using wireless phones. There is no proof, however, that wireless phones are absolutely safe. Wireless phones emit low levels of radiofrequency energy (RF) in the microwave range while being used. They also emit very low levels of RF when in the stand-by mode. Whereas high levels of RF can produce health effects (by heating tissue), exposure to low level RF that does not

produce heating effects causes no known adverse health effects. Many studies of low level RF exposures have not found any biological effects. Some studies have suggested that some biological effects may occur, but such findings have not been confirmed by additional research. In some cases, other researchers have had difficulty in reproducing those studies, or in determining the reasons for inconsistent results.

What is FDA's role concerning the safety of wireless phones?

Under the law, FDA does not review the safety of radiation-emitting consumer products such as wireless phones before they can be sold, as it does with new drugs or medical devices. However, the agency has authority to take action if wireless phones are shown to emit radiofrequency energy (RF) at a level that is hazardous to the user. In such a case, FDA could require the manufacturers of wireless phones to notify users of the health hazard and to repair, replace or recall the phones so that the hazard no longer exists.

Although the existing scientific data do not justify FDA regulatory actions, FDA has urged the wireless phone industry to take a number of steps, including the following:

- Support needed research into possible biological effects of RF of the type emitted by wireless phones;
- Design wireless phones in a way that minimizes any RF exposure to the user that is not necessary for device function; and
- Cooperate in providing users of wireless phones with the best possible information on possible effects of wireless phone use on human health

FDA belongs to an interagency working group of the federal agencies that have responsibility for different aspects of RF safety to ensure coordinated efforts at the federal level. The following agencies belong to this working group:

- National Institute for Occupational Safety and Health
- Environmental Protection Agency
- Federal Communications Commission
- Occupational Safety and Health Administration
- National Telecommunications and Information Administration

The National Institutes of Health participates in some interagency working group activities, as well.

FDA shares regulatory responsibilities for wireless phones with the Federal Communications Commission (FCC). All phones that are sold in the United States must comply with FCC safety guidelines that limit RF exposure. FCC relies on FDA and other health agencies for safety questions about wireless phones.

FCC also regulates the base stations that the wireless phone networks rely upon. While these base stations operate at higher power than do the wireless phones themselves, the RF exposures that people get from these base stations are typically thousands of times lower than those they can get from wireless

phones. Base stations are thus not the primary subject of the safety questions discussed in this document.

What kinds of phones are the subject of this update?

The term “wireless phone” refers here to hand-held wireless phones with built-in antennas, often called “cell,” “mobile,” or “PCS” phones. These types of wireless phones can expose the user to measurable radiofrequency energy (RF) because of the short distance between the phone and the user’s head. These RF exposures are limited by Federal Communications Commission safety guidelines that were developed with the advice of FDA and other federal health and safety agencies. When the phone is located at greater distances from the user, the exposure to RF is drastically lower because a person’s RF exposure decreases rapidly with increasing distance from the source. The so-called “cordless phones,” which have a base unit connected to the telephone wiring in a house, typically operate at far lower power levels, and thus produce RF exposures well within the FCC’s compliance limits.

What are the results of the research done already?

The research done thus far has produced conflicting results, and many studies have suffered from flaws in their research methods. Animal experiments investigating the effects of radiofrequency energy (RF) exposures characteristic of wireless phones have yielded conflicting results that often cannot be repeated in other laboratories. A few animal studies, however, have suggested that low levels of RF could accelerate the development of cancer in laboratory animals. However, many of the studies that showed increased tumor development used animals that had been genetically engineered or treated with cancer-causing chemicals so as to be pre-disposed to develop cancer in the absence of RF exposure. Other studies exposed the animals to RF for up to 22 hours per day. These conditions are not similar to the conditions under which people use wireless phones, so we don’t know with certainty what the results of such studies mean for human health.

Three large epidemiology studies have been published since December 2000. Between them, the studies investigated any possible association between the use of wireless phones and primary brain cancer, glioma, meningioma, or acoustic neuroma, tumors of the brain or salivary gland, leukemia, or other cancers. None of the studies demonstrated the existence of any harmful health effects from wireless phone RF exposures. However, none of the studies can answer questions about long-term exposures, since the average period of phone use in these studies was around three years.

What research is needed to decide whether RF exposure from wireless phones poses a health risk?

A combination of laboratory studies and epidemiological studies of people actually using wireless phones would provide some of the data that are needed. Lifetime animal exposure studies could be completed in a few years. However, very large numbers of animals would be needed to provide reliable proof of a cancer promoting effect if one exists. Epidemiological studies can provide data

that is directly applicable to human populations, but 10 or more years' follow-up may be needed to provide answers about some health effects, such as cancer. This is because the interval between the time of exposure to a cancer-causing agent and the time tumors develop - if they do - may be many, many years. The interpretation of epidemiological studies is hampered by difficulties in measuring actual RF exposure during day-to-day use of wireless phones. Many factors affect this measurement, such as the angle at which the phone is held, or which model of phone is used.

What is FDA doing to find out more about the possible health effects of wireless phone RF?

FDA is working with the U.S. National Toxicology Program and with groups of investigators around the world to ensure that high priority animal studies are conducted to address important questions about the effects of exposure to radiofrequency energy (RF).

FDA has been a leading participant in the World Health Organization International Electromagnetic Fields (EMF) Project since its inception in 1996. An influential result of this work has been the development of a detailed agenda of research needs that has driven the establishment of new research programs around the world. The Project has also helped develop a series of public information documents on EMF issues.

FDA and the Cellular Telecommunications & Internet Association (CTIA) have a formal Cooperative Research and Development Agreement (CRADA) to do research on wireless phone safety. FDA provides the scientific oversight, obtaining input from experts in government, industry, and academic organizations. CTIA-funded research is conducted through contracts to independent investigators. The initial research will include both laboratory studies and studies of wireless phone users. The CRADA will also include a broad assessment of additional research needs in the context of the latest research developments around the world.

What steps can I take to reduce my exposure to radiofrequency energy from my wireless phone?

If there is a risk from these products—and at this point we do not know that there is—it is probably very small. But if you are concerned about avoiding even potential risks, you can take a few simple steps to minimize your exposure to radiofrequency energy (RF). Since time is a key factor in how much exposure a person receives, reducing the amount of time spent using a wireless phone will reduce RF exposure.

- If you must conduct extended conversations by wireless phone every day, you could place more distance between your body and the source of the RF, since the exposure level drops off dramatically with distance. For example, you could use a headset and carry the wireless phone away from your body or use a wireless phone connected to a remote antenna.

Again, the scientific data do not demonstrate that wireless phones are harmful. But if you are concerned about the RF exposure from these products, you can use measures like those described above to reduce your RF exposure from wireless phone use.

What about children using wireless phones?

The scientific evidence does not show a danger to users of wireless phones, including children and teenagers. If you want to take steps to lower exposure to radiofrequency energy (RF), the measures described above would apply to children and teenagers using wireless phones. Reducing the time of wireless phone use and increasing the distance between the user and the RF source will reduce RF exposure.

Some groups sponsored by other national governments have advised that children be discouraged from using wireless phones at all. For example, the government in the United Kingdom distributed leaflets containing such a recommendation in December 2000. They noted that no evidence exists that using a wireless phone causes brain tumors or other ill effects. Their recommendation to limit wireless phone use by children was strictly precautionary; it was not based on scientific evidence that any health hazard exists.

What about wireless phone interference with medical equipment?

Radiofrequency energy (RF) from wireless phones can interact with some electronic devices. For this reason, FDA helped develop a detailed test method to measure electromagnetic interference (EMI) of implanted cardiac pacemakers and defibrillators from wireless telephones. This test method is now part of a standard sponsored by the Association for the Advancement of Medical Instrumentation (AAMI). The final draft, a joint effort by FDA, medical device manufacturers, and many other groups, was completed in late 2000. This standard will allow manufacturers to ensure that cardiac pacemakers and defibrillators are safe from wireless phone EMI.

FDA has tested hearing aids for interference from handheld wireless phones and helped develop a voluntary standard sponsored by the Institute of Electrical and Electronic Engineers (IEEE). This standard specifies test methods and performance requirements for hearing aids and wireless phones so that no interference occurs when a person uses a “compatible” phone and a “compatible” hearing aid at the same time. This standard was approved by the IEEE in 2000.

FDA continues to monitor the use of wireless phones for possible interactions with other medical devices. Should harmful interference be found to occur, FDA will conduct testing to assess the interference and work to resolve the problem.

Which other federal agencies have responsibilities related to potential RF health effects?

Certain agencies in the Federal Government have been involved in monitoring, researching or regulating issues related to human exposure to RF radiation.

These agencies include the Food and Drug Administration (FDA), the Environmental Protection Agency (EPA), the Occupational Safety and Health Administration (OSHA), the National Institute for Occupational Safety and Health (NIOSH), the National Telecommunications and Information Administration (NTIA) and the Department of Defense (DOD).

By authority of the Radiation Control for Health and Safety Act of 1968, the Center for Devices and Radiological Health (CDRH) of the FDA develops performance standards for the emission of radiation from electronic products including X-ray equipment, other medical devices, television sets, microwave ovens, laser products and sunlamps. The CDRH established a product performance standard for microwave ovens in 1971 limiting the amount of RF leakage from ovens. However, the CDRH has not adopted performance standards for other RF-emitting products. The FDA is, however, the lead federal health agency in monitoring the latest research developments and advising other agencies with respect to the safety of RF-emitting products used by the public, such as cellular and PCS phones.

The FDA's microwave oven standard is an emission standard (as opposed to an exposure standard) that allows specific levels of microwave leakage (measured at five centimeters from the oven surface). The standard also requires ovens to have two independent interlock systems that prevent the oven from generating microwaves the moment that the latch is released or the door of the oven is opened. The FDA has stated that ovens that meet its standards and are used according to the manufacturer's recommendations are safe for consumer and industrial use. More information is available from: www.fda.gov/cdrh.

The EPA has, in the past, considered developing federal guidelines for public exposure to RF radiation. However, EPA activities related to RF safety and health are presently limited to advisory functions. For example, the EPA now chairs an Inter-agency Radiofrequency Working Group, which coordinates RF health-related activities among the various federal agencies with health or regulatory responsibilities in this area.

OSHA is responsible for protecting workers from exposure to hazardous chemical and physical agents. In 1971, OSHA issued a protection guide for exposure of workers to RF radiation [29 CFR 1910.97]. However, this guide was later ruled to be only advisory and not mandatory. Moreover, it was based on an earlier RF exposure standard that has now been revised. At the present time, OSHA uses the IEEE and/or FCC exposure guidelines for enforcement purposes under OSHA's "general duty clause" (for more information see: <http://www.osha-slc.gov/SLTC/radiofrequencyradiation/index.html>).

NIOSH is part of the U.S. Department of Health and Human Services. It conducts research and investigations into issues related to occupational exposure to chemical and physical agents. NIOSH has, in the past, undertaken to develop RF exposure guidelines for workers, but final guidelines were never adopted by the agency. NIOSH conducts safety-related RF studies through its Physical Agents Effects Branch in Cincinnati, Ohio.

The NTIA is an agency of the U.S. Department of Commerce and is responsible for authorizing Federal Government use of the RF electromagnetic spectrum. Like the FCC, the NTIA also has NEPA responsibilities and has considered adopting guidelines for evaluating RF exposure from U.S. Government transmitters such as radar and military facilities.

The Department of Defense (DOD) has conducted research on the biological effects of RF energy for a number of years. This research is now conducted primarily at the U.S. Air Force Research Laboratory located at Brooks Air Force Base, Texas. The DOD Web site for RF biological effects information is listed with other sites in conjunction with a question on other sources of information, below.

Who funds and carries out research on the biological effects of RF energy?

Research into possible biological effects of RF energy is carried out in laboratories in the United States and around the world. In the U.S., most research has been funded by the Department of Defense, due to the extensive military use of RF equipment such as radar and high-powered radio transmitters. In addition, some federal agencies responsible for health and safety, such as the Environmental Protection Agency (EPA) and the U.S. Food and Drug Administration (FDA), have sponsored and conducted research in this area. At the present time, most of the non-military research on biological effects of RF energy in the U.S. is being funded by industry organizations. More research is being carried out overseas, particularly in Europe.

In 1996, the World Health Organization (WHO) established the International EMF Project to review the scientific literature and work towards resolution of health concerns over the use of RF technology. WHO maintains a Web site that provides extensive information on this project and about RF biological effects and research (www.who.ch/peh-emf).

FDA, EPA and other US government agencies responsible for public health and safety have worked together and in connection with WHO to monitor developments and identify research needs related to RF biological effects.

How does FCC Audit Cell Phone RF?

After FCC grants permission for a particular cellular telephone to be marketed, FCC will occasionally conduct “post-grant” testing to determine whether production versions of the phone are being produced to conform with FCC regulatory requirements. The manufacturer of a cell phone that does not meet FCC’s regulatory requirements may be required to remove the cell phone from use and to refund the purchase price or provide a replacement phone, and may be subject to civil or criminal penalties. In addition, if the cell phone presents a risk of injury to the user, FDA may also take regulatory action. The most important post-grant test, from a consumer’s perspective, is testing of the RF emissions of the phone. FCC measures the Specific Absorption Rate (SAR) of the phone, following a very rigorous testing protocol. As is true for nearly any scientific measurement, there is a possibility that the test measurement may be

less than or greater than the actual RF emitted by the phone. This difference between the RF test measurement and actual RF emission is because test measurements are limited by instrument accuracy, because test measurement and actual use environments are different, and other variable factors. This inherent variability is known as “measurement uncertainty.” When FCC conducts post-grant testing of a cell phone, FCC takes into account any measurement uncertainty to when determining whether regulatory action is appropriate. This approach ensures that when FCC takes regulatory action, it will have a sound, defensible scientific basis.

FDA scientific staff reviewed the methodology used by FCC to measure cell phone RF and agreed it is an acceptable approach, given our current understanding of the risks presented by cellular phone RF emissions. RF emissions from cellular phones have not been shown to present a risk of injury to the user when the measured SAR is less than the safety limits set by FCC (an SAR of 1.6 W/kg). Even in a case where the maximum measurement uncertainty permitted by current measurement standards was added to the maximum permissible SAR, the resulting SAR value would be well below any level known to produce an acute effect. Consequently, FCC’s approach with measurement uncertainty will not result in consumers being exposed to any known risk from the RF emitted by cellular telephones.

FDA will continue to monitor studies and literature reports concerning acute effects of cell phone RF, and concerning chronic effects of long-term exposure to cellular telephone RF (that is, the risks from using a cell phone for many years). If new information leads FDA to believe that a change to FCC’s measurement policy may be appropriate, FDA will contact FCC and both agencies will work together to develop a mutually-acceptable approach.

Owner's Record

The model number, regulatory number and serial number are located on a nameplate inside the battery compartment. Record the serial number in the space provided below. This will be helpful if you need to contact us about your phone in the future.

Model: Sanyo SCP-7400

Serial No.:

User's Guide Proprietary Notice

CDMA Technology is licensed by QUALCOMM Incorporated under one or more of the following patents:

4,901,307 5,109,390 5,267,262 5,416,797

5,506,865 5,544,196 5,657,420 5,101,501

5,267,261 5,414,796 5,504,773 5,535,239

5,600,754 5,778,338 5,228,054 5,337,338

5,710,784 5,056,109 5,568,483 5,659,569

5,490,165 5,511,073

T9 Text Input is licensed by Tegic Communications and is covered by U.S. Pat. 5,818,437, U.S. Pat. 5,953,541, U.S. Pat. 6,011,554 and other patents pending.

User's Guide template version 3D (09-01-03)

Index

A

- Abbreviated Dialing 31, 60
- Advanced Information 111
- Airplane Mode 54
- Alarm Clock 111
- Alert Notification 43
- Answering Calls 22
- Any Key Answer 59
- Area Name 48
- Auto Answer 57
- Auto Delete 166
- Automatic Speech Recognition
 - Activating 123
 - Available Commands 123
 - Digit Training 129
 - Finding Contacts 125
 - Help 130
 - Making a Call 124
 - Making a Ready Link Call 128
 - Phone Status 130
 - Voice Tag 126

B

- Background 51
- Backlight Time Length 46
- Battery
 - Capacity 17
 - Charging 18
 - Disposal 257
 - Installing 17
 - Removing 17
 - Standby Time 17
 - Talk Time 17

C

- Calculator 113
- Calendar 101
- Call Alarm
 - Adding 104
 - Alerts 105
 - Editing 106
 - Erasing 106, 109

Menu 105

Viewing 106

Call Forwarding 216

Call Guard 80

Call History

- Erasing 90
- Making a Call 88
- Options 88
- Prepending 90
- Saving 89
- Viewing 87

Call Waiting 214

Callback Number 65

Caller ID 214

Calling in Lock Mode 70

Chat 237

Contacts

- Adding 92, 95
- Dialing 30
- Editing 95, 97
- Erasing 73
- Finding 29, 93, 125
- Options 94
- Saving 28
- Secret 99

Call Waiting 214

Callback Number 65

Caller ID 214

Calling in Lock Mode 70

Chat 237

Contacts

- Adding 92, 95
- Dialing 30
- Editing 95, 97
- Erasing 73
- Finding 29, 93, 125
- Options 94
- Saving 28
- Secret 99

Adding 92, 95

Dialing 30

Editing 95, 97

Erasing 73

Finding 29, 93, 125

Options 94

Saving 28

Secret 99

D

Dialing

- Abbreviated 31, 60
- Contacts 30, 124
- Numbers With Pauses 29
- Options 21
- Speed Dialing 31, 96, 154

Digit Training 129

Display Settings

- Area Name 48
- Background 51
- Backlight Time Length 46
- Display Screen 47
- Font Size 52
- Greeting 45
- Incoming Calls 47
- Main Menu 50
- My Buddy 51

Numbers With Pauses 29

Options 21

Speed Dialing 31, 96, 154

Digit Training 129

Display Settings

- Area Name 48
- Background 51
- Backlight Time Length 46
- Display Screen 47
- Font Size 52
- Greeting 45
- Incoming Calls 47
- Main Menu 50
- My Buddy 51

Area Name 48

Background 51

Backlight Time Length 46

Display Screen 47

Font Size 52

Greeting 45

Incoming Calls 47

Main Menu 50

My Buddy 51

- Screen Saver 50
- Standby Mode 49
- Downloading
 - Accessing Menus 238
 - Assigning 119
 - Confirming 117
 - Data Size 120
 - Erasing 73, 121
 - Files 114
 - Icon Indication 118
 - Settings 118
 - Sorting 119
 - Viewing Memory 120

E

- Emergency Calling 26
- Emoticons 36
- End-of-Call Options 28
- Event
 - Adding 102
 - Alerts 103
 - Editing 106
 - Erasing 106, 109
 - Menu 103
 - Viewing 106

F

- Faceplate 15
- FCC Notice 258
- Features 14
- Font Size 52, 232

G

- Games
 - Downloading 240
 - Playing 241
- Greeting 45

H

- Hard Pause 29
- Headset Mode 62
- Help 6

I

- Icon Indication 12, 118, 167, 177
- In Camcorder Folder 178

- In Camera Folder 168
- In-Call Options 27
- Input Mode
 - Alphabet Mode 34
 - Emoticons 36
 - Numbers 35
 - Preset Suffixes 35
 - Smileys 36
 - Symbols 35
 - T9 Text Mode 33
- Instant Messaging 236

K

- Key Press Echo 41

L

- Language 66
- Limit Use 71
- Location Settings 53
- Lock Code 70
- Locking
 - Phone 68
 - Picture and Video 69
 - ReadyLink Calls 70
 - Voice Calls 69

M

- Making Calls 20
- Making ReadyLink Call 141, 142, 143
- Meeting Mode 61
- Menu Diagram 83
- Message Notification 64
- Messaging
 - Displaying 226
 - Folder
 - Creating 233
 - Drafts 228
 - Editing 233
 - Erasing 234, 235
 - Outbox 229
 - Font Size 232
 - Moving a Message 234
 - Options 229
 - Prepending 232

- Sending 227, 228, 229
- Sprint PCS Picture Mail 226
- Storage 226
- Mini-Flashlight 66
- Missed Call Notification 26, 144
- Multimedia Player
 - FAQs 202
 - Options 197, 201
 - Playing 199, 224
 - Purchasing 223
- Muting 25
- My Buddy 51

N

- Net Guard 220

O

- Online Sprint PCS Picture Mail
 - Auto Delete 166
 - Downloading 191
 - Managing 189
 - Options 193
 - Sending 192
 - Uploading 190
- Open/Close Flip Option 58

P

- Phone Number
 - Dialing with Pauses 29
 - Displaying 19
 - Finding 29
 - Saving 28
- Phone Status 130
- Pictures
 - Auto Delete 166
 - Downloading 191
 - Flash 162
 - Icon Indication 167
 - Multiple Shots 163
 - Options 161, 168, 172, 179, 182
 - Self-timer 162
 - Sending 183
 - Settings 165
 - Shutter Sound 165
 - Status Area 166

- Storing 168
- Taking 159
- Uploading 190
- Zoom 164
- Plus Code 30
- Power-off Tone 40
- Premium Services Content 238
- Prepend Dialing 90, 232
- Preset Messages 64
- Preset Suffixes 35

Q

- Quiet Ringer 23
- Qwest Services
 - Call Forwarding 216
 - Call Waiting 214
 - Caller ID 214

R

- ReadyLink
 - Adding 148, 149
 - Alert 139, 156
 - Contacts List 140
 - Copying 146
 - Default View 157
 - Editing 150
 - Erasing 152
 - Finding 147
 - Floor Display 157
 - Floor Tone 39
 - Making Calls
 - by Entering Number 143
 - by Using ASR 128
 - Contact 141
 - Group 142
 - Options 146
 - Preparing 138
 - ReadyLink Guard 155
 - Receiving 145
 - Restarting 154
 - Ringer Types 155
 - Saving 147
 - Setting 138
 - Speakerphone 156

- Speed Dialing 154
- Updating 153
- Resetting
 - Phone 74
 - Picture Account 74
- Return to Idle 63
- Ringer
 - Assigning 243
 - Downloading 242
 - Purchasing 243
 - Tone Length 40
 - Types 38
 - Volume 25, 41
- Roaming
 - Analog Networks 78
 - Digital Networks 77
 - Setting 79
- S**
 - Safety Guidelines 252
 - Saved to Phone Folder 171, 181
 - Scheduler
 - Calendar 101
 - Call Alarm 104
 - Erasing 108, 109
 - Event 102
 - Memory 109
 - Setting Holidays 101
 - To Do 107
 - Screen Call
 - Activating 134
 - Erasing 136
 - Recording 135, 136
 - Reviewing 136
 - Selecting Announcement 135
 - Screen Savers
 - Assigning 245
 - Downloading 244
 - Purchasing 245
 - Secret Mode 99
 - Security Menu
 - Accessing 68
 - Changing the Lock Code 70
 - Locking 68
 - Resetting 74
 - Unlocking Phone 3, 69
 - Shortcut 56
 - Side Key Guard 59
 - Signature 65
 - Silence All 44
 - Sleep Mode 63
 - Sound Settings
 - Silence All 44
 - Start-up/Power-off Tone 40
 - Volume Settings 25, 41
 - Speakerphone 24
 - Special Numbers 72
 - Speed Dialing 31, 96, 154
 - Sprint PCS Picture Mail
 - Password 160
 - Sprint PCS Vision
 - Chat 237
 - Downloading 238
 - Enabling and Disabling 75
 - FAQs 251
 - Games 240
 - Launching 219
 - Ringers 242
 - Screen Savers 244
 - Web 246
 - Standby Time 17
 - Start-up Tone 40
 - Symbols 35
- T**
 - T9 Text Input 33
 - Talk Time 17
 - Three-Way Call 215
 - To Do Items
 - Adding 107, 108
 - Deleting 108, 109
 - Editing 107
 - Viewing 107
 - Tone Length 40
 - TTY 55
 - Turning On and Off 16
 - 2-Second Pause 29

U

- Unlocking Phone 3, 69
- Unmute 25
- User Address 110
- User Name 218

V

- Version 110
- Videos
 - Auto Delete 166
 - Cue Sound 176
 - Downloading 191
 - Icon Indication 177
 - Options 174
 - Self-timer 162
 - Sending 185
 - Settings 176
 - Storing 178
 - Taking 173
 - Uploading 190
 - Zoom 175

Voice Memo

- Erasing 133
- Recording 131
- Reviewing 132

Voice Prompt 40

Voice Tags

- Erasing 73, 127
- Finding 94
- Making a Call 126
- Programming 126
- Reviewing 127

Voicemail

- Button Guide 209
- Clearing Message Icon 212
- Details 212
- Menu Key 213
- Message Alerts 208
- Notification 207
- Options 210
- Retrieving 208
- Setting Up 4, 207

Volume Settings

- During a Conversation 25

Muting 25

- Ringer 25

W

Web

- Launching 219
- Navigating 221
- Net Guard 220

World Clock 49, 113